

Oracle® Application Server

Oracle Application Server 4.0 Error Messages

Release 4.0.8

August 1999

ORACLE®

Oracle Application Server 4.0 Error Messages

Release 4.0.8

Copyright © 1996, 1999, Oracle Corporation. All rights reserved.

The programs are not intended for use in any nuclear, aviation, mass transit, medical, or other inherently dangerous applications. It shall be the licensee's responsibility to take all appropriate fail-safe, backup, redundancy, and other measures to ensure the safe use of such applications if the programs are used for such purposes, and Oracle Corporation disclaims liability for any damages caused by such use of the programs.

The programs (which include both the software and documentation) contain proprietary information of Oracle Corporation; they are provided under a license agreement containing restrictions on use and disclosure and are also protected by copyright, patent, and other intellectual and industrial property laws. Reverse engineering, disassembly, or decompilation of the programs is prohibited.

The information contained in this document is subject to change without notice. If you find any problems in the documentation, please report them to us in writing. Oracle Corporation does not warrant that this document is error free. Except as may be expressly permitted in your license agreement for these programs, no part of these programs may be reproduced or transmitted in any form or by any means, electronic or mechanical, for any purpose, without the express written permission of Oracle Corporation.

If the programs are delivered to the U.S. Government or anyone licensing or using the programs on behalf of the U.S. Government, the following notice is applicable:

Restricted Rights Notice Programs delivered subject to the DOD FAR Supplement are "commercial computer software" and use, duplication, and disclosure of the programs, including documentation, shall be subject to the licensing restrictions set forth in the applicable Oracle license agreement. Otherwise, programs delivered subject to the Federal Acquisition Regulations are "restricted computer software" and use, duplication, and disclosure of the programs shall be subject to the restrictions in FAR 52.227-19, Commercial Computer Software - Restricted Rights (June, 1987). Oracle Corporation, 500 Oracle Parkway, Redwood City, CA 94065.

Oracle is a registered trademark, and the Oracle logo, NLS*WorkBench, Pro*COBOL, Pro*FORTRAN, Pro*Pascal, SQL*Loader, SQL*Module, SQL*Net, SQL*Plus, Oracle7, Oracle Server, Oracle Server Manager, Oracle Call Interface, Oracle7 Enterprise Backup Utility, Oracle TRACE, Oracle WebServer, Oracle Web Application Server, Oracle Application Server, Oracle Network Manager, Secure Network Services, Oracle Parallel Server, Advanced Replication Option, Oracle Data Query, Cooperative Server Technology, Oracle Toolkit, Oracle MultiProtocol Interchange, Oracle Names, Oracle Book, Pro*C, and PL/SQL are trademarks or registered trademarks of Oracle Corporation. All other company or product names mentioned are used for identification purposes only and may be trademarks of their respective owners.

Contents

Oracle Application Server 4.0 Messages

00000 - 00600 : Generic Messages	4
04500 - 04750 : Dispatcher, vpm messages.....	6
04751 - 04999 : Dispatcher, vpm messages.....	11
05000 - 05499 : Oracle PL/SQL Cartridge errors.....	15
05300 - 05399 : PL/SQL Cartridge Log Messages	18
05400 - 05499 : External Listener Registration Errors and Messages.....	22
05500 - 05599 : Oracle PL/SQL Cartridge Administration errors and messages	23
05550 - 05600 : Oracle PL/SQL Cartridge Administration - DAD errors and messages	28
05600 - 05699 : Oracle Web Database Administration errors	32
05700 - 05799 : Oracle Web Listener Configuration errors and messages	33
05800 - 05899 : Oracle Web Request Broker Administration messages	39
05900 - 05999 : Oracle Application Server Registration errors and messages.....	45
06000 - 06099 : JWeb Cartridge errors and messages	46
06110 - 06150 : Oracle Application Server Cartridge Message.....	48
06151 - 06199 : Java-PL/SQL errors and messages	49
06400 - 06599 : LiveHTML Cartridge	50
06600 - 06699 : Auth Server messages.....	57
06700 - 06799 : Auth Server Logging Msgs	62
06800 - 06899 : Cartridge Configuration Administration (CGI-bin).....	72
07500 - 07599 : Oracle Application Server Proxy errors and messages.....	74
07700 - 07800 : Error message for upgrade/migration utility	75
07750 - 07899 : Messages for migration tool from oas4043 to oas4064.....	81
08200 - 08299 : Oracle Application Server Logger Admin messages	93
08300 - 08399 : Oracle Application Server Auth Services Admin messages	95

08400 - 08500 : Oracle Application Server Config Provider Error Messages	96
08600 - 08799 : Oracle Application Server Log Module Messages.....	97
08800 - 08899 : Oracle Application Server Controller OWSCTL Messages	101
09000 - 09099 : Oracle Application Server STATus (owsstat) Messages	107
09100 - 09189 : Oracle Web Configuration writer.....	108
09190 - 09199 : wrcfreg syntax messages	116
10000 - 10099 : Web Request Broker Execution Engine (wrbc) defined in wrer.h.....	117
10100 - 10199 : Web Request Broker Services.....	119
10200 - 10299 : WRB TX Services.....	120
10300 - 10599 : HTTP Daemon Adapter messages	125
10600 - 10699 : WRB ICX Services.....	128
10700 - 10799 : WRB CONTENT Service Error messages	134
10800 - 10999 : Cartridge server / Cartridge server factory	137
11000 - 11099 : Apache Adapter specific messages.....	139
20000 - 20099 : GENERIC STRINGS for wladmin(NLS)	142
20100 - 20199 : GENERIC STRINGS for csadmin(NLS)	143
20200 - 20299 : Oracle Application Server Manager Messages	154
20300 - 24999 : ECO/Java.....	159
25000 - 25999 : RM Proxy	160
26000 - 26099 : Monitoring daemon messages.....	167
26800 - 27999 : Management helper library messages and config provider server messages.	168
28000 - 29000 : Session	183
29000 - 29299 : OTS Administration Error Messages.....	185
OMN-205-OMN-11034 : ORB Error Messages	189
OWB-01001-OWB-02002 : ODBC Error Messages.....	208

Preface

Audience

The information contained in this book is intended to assist you in interpreting error messages generated in Oracle Application Server 4.0.

The Oracle Application Server Documentation Set

This table lists the Oracle Application Server documentation set.

Title of Book	Part No.
Oracle Application Server 4.0.8 Documentation Set	A66971-02
Oracle Application Server Overview and Glossary	A60115-03
Oracle Application Server Installation Guide for Sun SPARC Solaris 2.x	A58755-03
Oracle Application Server Installation Guide for Windows NT	A58756-03
Oracle Application Server Administration Guide	A60172-03
Oracle Application Server Security Guide	A60116-03
Oracle Application Server Performance and Tuning Guide	A60120-03
Oracle Application Server Developer's Guide: PL/SQL and ODBC Applications	A66958-02
Oracle Application Server Developer's Guide: JServlet Applications	A73043-01
Oracle Application Server Developer's Guide: LiveHTML and Perl Applications	A66960-02
Oracle Application Server Developer's Guide: EJB, ECO/Java and CORBA Applications	A69966-01
Oracle Application Server Developer's Guide: C++ CORBA Applications	A70039-01
Oracle Application Server PL/SQL Web Toolkit Reference	A60123-03
Oracle Application Server PL/SQL Web Toolkit Quick Reference	A60119-03

Title of Book	Part No.
Oracle Application Server JServlet Toolkit Reference	A73045-01
Oracle Application Server JServlet Toolkit Quick Reference	A73044-01
Oracle Application Server Cartridge Management Framework	A58703-03
Oracle Application Server 4.0.8 Release Notes	A66106-03

Conventions

This table lists the typographical conventions used in this manual.

Convention	Example	Explanation
bold	oas.h owsctl wrbcfg www.oracle.com	Identifies file names, utilities, processes, and URLs
italics	<i>file1</i>	Identifies a variable in text; replace this place holder with a specific value or string.
angle brackets	<filename>	Identifies a variable in code; replace this place holder with a specific value or string.
courier	owsctl start wrb	Text to be entered exactly as it appears. Also used for functions.
square brackets	[-c string]	Identifies an optional item.
	[on off]	Identifies a choice of optional items, each separated by a vertical bar (), any one option can be specified.
braces	{yes no}	Identifies a choice of mandatory items, each separated by a vertical bar ().
ellipses	n,...	Indicates that the preceding item can be repeated any number of times.

The term “Oracle Server” refers to the database server product from Oracle Corporation.

The term “**oracle**” refers to an executable or account by that name.

The term “*oracle*” refers to the owner of the Oracle software.

Technical Support Information

Oracle Global Support can be reached at the following numbers:

- In the USA: **Telephone: 1.650.506.1500**
- In Europe: **Telephone: +44 1344 860160**
- In Asia-Pacific: **Telephone: +61. 3 9246 0400**

Please prepare the following information before you call, using this page as a check-list:

- ☐ your CSI number (if applicable) or full contact details, including any special project information
- ☐ the complete release numbers of the Oracle Application Server and associated products
- ☐ the operating system name and version number
- ☐ details of error codes and numbers and descriptions. Please write these down as they occur. They are critical in helping WWCS to quickly resolve your problem.
- ☐ a full description of the issue, including:
 - **What** - What happened? For example, the command used and its result.
 - **When** -When did it happen? For example, during peak system load, or after a certain command, or after an operating system upgrade.
 - **Where** -Where did it happen? For example, on a particular system or within a certain procedure or table.
 - **Extent** - What is the extent of the problem? For example, production system unavailable, or moderate impact but increasing with time, or minimal impact and stable.
- ☐ Keep copies of any trace files, core dumps, and redo log files recorded at or near the time of the incident. WWCS may need these to further investigate your problem. For a list of trace and log files, see “Configuration and Log Files” in the *Administration Guide*.

For installation-related problems, please have the following additional information available:

- ☐ listings of the contents of \$ORACLE_HOME (Unix) or %ORACLE_HOME% (NT) and any staging area, if used.

-
- ❑ installation logs (**install.log**, **sql.log**, **make.log**, and **os.log**) typically stored in the **\$ORACLE_HOME/orainst** (Unix) or **%ORACLE_HOME%\orainst** (NT) directory.

Documentation Sales and Client Relations

In the United States:

- To order hardcopy documentation, call Documentation Sales: **1.800.252.0303**.
- For shipping inquiries, product exchanges, or returns, call Client Relations: **1.650.506.1500**.

In the United Kingdom:

- To order hardcopy documentation, call Oracle Direct Response: **+44 990 332200**.
- For shipping inquiries and upgrade requests, call Customer Relations: **+44 990 622300**.

Reader's Comment Form

Oracle Application Server 4.0 Error Messages

Oracle Corporation welcomes your comments and suggestions on the quality and usefulness of this publication. Your input is an important part of the information used for revision.

- Did you find any errors?
- Is the information clearly presented?
- Do you need more information? If so, where?
- Are the examples correct? Do you need more examples?
- What features did you like most about this manual?

If you find any errors or have suggestions for improvement, please indicate the topic, chapter, and page number below:

Please send your comments to:

Oracle Application Server Documentation Manager
Oracle Corporation
500 Oracle Parkway
Redwood Shores, CA 94065

If you would like a reply, please provide your name, address, and telephone number below:

Thank you for helping us improve our documentation.

Oracle Application Server 4.0 Messages

Many messages listed here contain variables such as:

`%(1)s` : error writing file `%(2)s`

The variables are replaced by user-specific information at the time you receive the message.

Contents

- [00000 - 00600 : Generic Messages](#)
- [04500 - 04750 : Dispatcher, vpm messages.](#)
- [04751 - 04999 : Dispatcher, vpm messages](#)
- [05000 - 05499 : Oracle PL/SQL Cartridge errors](#)
- [05300 - 05399 : PL/SQL Cartridge Log Messages](#)
- [05400 - 05499 : External Listener Registration Errors and Messages](#)
- [05500 - 05599 : Oracle PL/SQL Cartridge Administration errors and messages](#)
- [05550 - 05600 : Oracle PL/SQL Cartridge Administration - DAD errors and messages](#)
- [05600 - 05699 : Oracle Web Database Administration errors](#)
- [05700 - 05799 : Oracle Web Listener Configuration errors and messages](#)
- [05800 - 05899 : Oracle Web Request Broker Administration messages](#)
- [05900 - 05999 : Oracle Application Server Registration errors and messages](#)
- [06000 - 06099 : JWeb Cartridge errors and messages](#)
- [06110 - 06150 : Oracle Application Server Cartridge Message](#)

-
- 06151 - 06199 : Java-PL/SQL errors and messages
 - 06400 - 06599 : LiveHTML Cartridge
 - 06600 - 06699 : Auth Server messages
 - 06700 - 06799 : Auth Server Logging Msgs
 - 06800 - 06899 : Cartridge Configuration Administration (CGI-bin)
 - 07500 - 07599 : Oracle Application Server Proxy errors and messages
 - 07700 - 07800 : Error message for upgrade/migration utility
 - 08200 - 08299 : Oracle Application Server Logger Admin messages
 - 08300 - 08399 : Oracle Application Server Auth Services Admin messages
 - 08400 - 08500 : Oracle Application Server Config Provider Error Messages
 - 08600 - 08799 : Oracle Application Server Log Module Messages
 - 08800 - 08899 : Oracle Application Server Controller OWSCTL Messages
 - 09000 - 09099 : Oracle Application Server STATUS (owsstat) Messages
 - 09100 - 09189 : Oracle Web Configuration writer
 - 09190 - 09199 : wrcreg syntax messages
 - 10000 - 10099 : Web Request Broker Execution Engine (wrbc) defined in wrer.h
 - 10100 - 10199 : Web Request Broker Services
 - 10200 - 10299 : WRB TX Services
 - 10300 - 10599 : HTTP Daemon Adapter messages
 - 10600 - 10699 : WRB ICX Services
 - 10700 - 10799 : WRB CONTENT Service Error messages
 - 10800 - 10999 : Cartridge server / Cartridge server factory
 - 11000 - 11099 : Apache Adapter specific messages
 - 20000 - 20099 : GENERIC STRINGS for wladmin(NLS)
 - 20100 - 20199 : GENERIC STRINGS for csadmin(NLS)
 - 20200 - 20299 : Oracle Application Server Manager Messages
 - 20300 - 24999 : ECO/Java
 - 25000 - 25999 : RM Proxy

-
- 26000 - 26099 : Monitoring daemon messages
 - 26800 - 27999 : Management helper library messages and config provider server messages
 - 28000 - 29000 : Session
 - 29000 - 29299 : OTS Administration Error Messages
 - OMN-205-OMN-11034 : ORB Error Messages
 - OWB-01001-OWB-02002 : ODBC Error Messages

00000 - 00600 : Generic Messages

00000 “%(1)s : normal, successful completion”

Cause: Normal exit.

Action: None.

00001 “%(1)s : unable to open file %(2)s”

Cause: The file may not exist or may not be readable to the signalling program.

Action: Verify the file's existence in the file-system. Check file and directory permissions and ownership, as well as the ownership of the signalling process.

00002 “%(1)s : error reading file %(2)s”

Cause: Usually an operating system error. If the problem had been file permissions or non-existence, error 1 would have been signalled.

Action: Check your operating system log for errors.

00003 “%(1)s : error writing file %(2)s”

Cause: Usually an operating system error. If the problem had been file permissions or non-existence, error 1 would have been signalled.

Action: Check your operating system log for errors.

00004 “%(1)s : unable to open directory %(2)s”

Cause: The directory may not be readable/listable to the signalling program.

Action: Check existence of directory and file system permissions.

00010 “%(1)s : file format error when reading %(2)s”

Cause: The signalling program expected a specific file format, which it did not find.

Action: Analyze the file for incorrect formatting.

00011 “Installation not completed. Root.sh must be run”

Cause: The signalling program checked if **root.sh** completed successfully.

Action: Run **root.sh** as indicated by your installation guide.

00020 “%(1)s : out of memory when requesting %(2)s bytes”

Cause: The operating system was not able to supply the requested amount of memory.

Action: Reduce the number of running programs on the machine and retry the operation.

00600 “%(1)s: internal error, arguments [(2)s][(3)s][(4)s][(5)s][(6)s]”

Cause: This is the generic internal error number for NDW program exceptions. This indicates that a process has encountered an exceptional condition.

Action: Report as a bug - the first argument is the internal error number.

04500 - 04750 : Dispatcher, vpm messages.

04500 "Unable to get %(1)s information from ADP"

Cause: The Oracle Application Server dispatcher was unable to retrieve the specified value from ADP.

Action: Ignore. The browser may not provide such information.

04501 "The system has low memory"

Cause: There may be too many processes running.

Action: Reclaim memory by terminating extra processes, or increase the swap space.

04502 "Unable to dispatch a request to a cartridge"

Cause: A network error or low memory.

Action: Check if the remote cartridge is still alive, check swap space.

04503 "Unable to get a %(1)s cartridge"

Cause: Unable to get a cartridge, resulted from either expired session or cartridges of this type is not available.

Action: Session expired? Otherwise check if cartridges can be brought up manually

04504 "URI exceeds maximum allowed buffer"

Cause: For security reason, there is a limit on the maximum length of URI.

Action: None.

04505 "Request '%(1)s' will be dispatched to %(2)s cartridge"

Cause: Based on the uri and virtual path mapping.

Action: None.

04506 "Can not read inputs from configuration provider"

Cause: Configuration Provider may have internal error.

Action: Check Configuration Provider status.

04507 "Has no information about cartridge name %(1)s"

Cause: Cartridge is listed in virtual path manager, but not in resource manager.

Action: Check the configuration.

04508 "ORAWEB_HOME is undefined"

Cause: ORAWEB is not defined.

Action: Set ORAWEB_HOME

04509 "Unable to dynamically load %(1)s because of %(2)s"

Cause: The shared library cannot be loaded.

Action: Verify the existence of any undefined symbols.

04510 "Unable to find symbol %(2)s in shared library %(1)s"

Cause: The shared library does not contain the symbol.

Action: Verify the existence of this symbol.

04511 "Error in grabbing cartridge type %(1)s from the subsystem"

Cause: The subsystem, currently only CORBA model, has an error in Creating this type of cartridge.

Action: First make sure the cartridge can be manually brought up. Secondly, check the broker status.

04512 "Request %(1)s has internal error due to Error 04511"

Cause: All the waiting requests return internal errors if the subsystems cannot bring up the cartridge.

Action: Solve error 4511 and then this problem is solved too.

04513 "Request %(1)s has internal error due to cartridge execution error"

Cause: The cartridge execution, currently only CORBA supported, returns an error or throws an exception. cannot bring up the cartridge.

Action: Check if the cartridge is still alive.

04514 "Subsystem COA gets an exception %(1)s invoking remote %(2)s"

Cause: An exception is thrown, while preparing or doing remote method.

Action: Check the exception.

04515 "Subsystem COA async. methods %(1)s gets an exception %(2)s"

Cause: An exception is thrown, at async. method's event handler.

Action: Check what the exception is and check the target object's status.

04516 "Subsystem COA async. methods %(1)s gets a wrong return value"

Cause: A wrong error value is returned, at async. method's event handler.

Action: Check what the target object's status.

04517 "Subsystem COA has an error in bringing up catered type %(1)s"

Cause: The broker indicates that it has an error in bringing up this type of cartridge.

Action: Check broker's status.

04518 "Operation %(1)s throws unexpected exception %(2)s which comes from %(3)s:%(4)d"

Cause: An expected exception is thrown from a particular operation.

Action: Turn on full logging to get more information.

04519 "Unable to complete %(1)s. Cannot do asynchronous ORB operation"

Cause: This particular operation fails."

Action: Turn on full logging to get more information.

04520 "Entering routine %(1)s"

Cause: Executing this particular function/component.

Action: For tracing purpose only.

04521 "Error: routine %(1)s fails due to %(2)s"

Cause: Cannot finish the particular routine.

Action: Turn on full logging to get more information.

04522 "Successfully exiting routine %(1)s"

Cause: Successfully executing the particular routine.

Action: For tracing purpose only.

04523 "Non fatal execution logic error %(1)s:(%2)d detected. Additional info: %(3)s"

Cause: Unexpected logic error.

Action: Please notify Oracle.

04524 "The cartridge execute throws exception %(1)s with error code %(2)d"

Cause: This exception is thrown by cartridge's execute method.

Action: Check the cartridges' logs.

04525 "The cartridge execute throws unknown exception %(1)s"

Cause: An undefined exception is thrown by cartridge's execute method.

Action: Check the cartridges' logs.

04526 "For tracing only: %s"

Cause: For tracing only.

Action: None.

04527 "Operation %(1)s fails, symptom:%(2)s"

Cause: A particular operation fails.

Action: Turn on full logging for more information.

04528 "Dispatcher starts processing a/an %(1)s request, uri '%(2)s', uuid '%(3)s', uri protected (y/n): '%(4)c'"

Cause: For tracing only.

Action: None.

04529 "Cannot not get cartridge for request '%(1)s'"

Cause: Dispatcher indicates that it could find a cartridge for this request.

Action: Turn on full logging for more information.

04530 "Cannot return file '%(1)s' for request uri '%(2)s' due to wrong mimetype"

Cause: the mimetype is not recognized by HTTP listener / adapter.

Action: Turn on full logging for more information; investigate HTTP listener configuration.

04531 "Requests' longest waiting period for cartridges type '%(1)s' is %(2)d heart-beat"

Cause: for tracing only, indicate how long a request can wait for a particular type of cartridge.

Action: To change the value, turn on full logging for more information.

04532 "Request %(1)s has timed out"

Cause: Arequest has been waiting for a free cartridge too long.

Action: Turn on full logging to get information from broker and cartridges; tuning may be necessary.

04533 "Cannot get %(1)s in section %(2)s from configuration"

Cause: Some information is missing in the configuration.

Action: Either modify wrb.app directly or use the administration tool to modify the file.

04534 "Dispatcher's error routine invoked for request %(1)s"

Cause: Error is detected by adapter for this particular request. It may be caused by network error or user-defined error.

Action: Turn on full logging to get more information.

04535 "Will 'cancel' request %(1)s"

Cause: Adapter detects a broken network and notifies the dispatcher which will cancel the in-progress request.

Action: Check logs from cartridge to see more details.

04536 "Sending the 'cancel' notification for request %(1)s"

Cause: Adapter detects a broken network for this request.

Action: Check logs from cartridge to see more details.

04537 "The cartridge abort routine throws exception %(1)s for request %(2)s"

Cause: This exception is thrown by cartridge's abort method.

Action: Check the cartridges' logs.

04751 - 04999 : Dispatcher, vpm messages

04751 "Unable to get host %(1)s IP address"

Cause: The broker cannot resolve the host's IP address.

Action: Check if it's a valid hostname.

04752 "Host %(1)s is duplicate for cartridge type %(2)s"

Cause: The hostname is defined either in default hosts or in the cartridge's own host list already.

Action: Ignore it.

04753 "Factory at %(d)s is not recognized"

Cause: Only factories 'registered' in the configuration can be accepted.

Action: Update the configuration.

04754 "Unregister a factory not found at %(d)s"

Cause: This factory is neither recognized nor registered.

Action: Update the configuration.

04755 "Unable to register a dispatcher"

Cause: This most likely results from low memory.

Action: Check the swap space.

04756 "Unable to unregister a dispatcher"

Cause: This register has never been registered.

Action: Check the log output for a possible registration failure.

04757 "Unable to bring up cartridge, type %(1)s, at IP %(2)d"

Cause: The factor at the specified IP is not able to bring up cartridges.

Action: Check the log output, and also try to manually bring up cartridges.

04758 "Action %(1)s fails due to low memory"

Cause: Low memory.

Action: Check the swap space.

04759 "Not host is available to create Cartridge %(1)s"

Cause: Either Cartridge Server Factories are down or Maximum Cartridges are reached for all hosts.

Action: Bring up Cartridge Server Factory if not done so already.

04760 "Disable Host %(1)d for Cartridge %(2)s"

Cause: Maximum Cartridge has reached.

Action: Check the swap space.

04761 "Error encountered when reading wrb.app: %s"

Cause: **wrb.app** is not correct.

Action: Verify **wrb.app** has valid information.

04762 "Broker's internal structure does not contained %s"

Cause: **wrb.app** is not correct or internal error.

Action: Verify **wrb.app** has valid information.

04763 "Cartridge server %s is not a valid name"

Cause: Incorrect cartridge server name given to broker.

Action: Check the cartridge server name is valid and in **wrb.app**.

04764 "Unable to bring up cartridge server, type %(1)s, at IP %(2)d"

Cause: The factor at the specified IP is not able to bring up cartridge servers.

Action: Check the log output, and also try to manually bring up cartridge servers.

04765 "Unable to bring up cartridge instance factories, cartridge server %(1)s, at IP %(2)d"

Cause: The factor at the specified IP is not able to bring up cartridge instance factories.

Action: Check the log output, and also try to manually bring up cartridge instance factories.

04767 "Cartridge server, type %(1)s, at IP %(2)d creation timeouts."

Cause: The factor at the specified IP is not able to bring up cartridge servers.

Action: Check the log output, and also try to manually bring up cartridge servers.

04770 "Host %(1)s is running out of Virtual Memory and disabled temporarily for Cartridge %(2)s instance creation"

Action: Increase the node's virtual memory size.

04771 "RM proxy object reference for host %(d)s is not found in broker"

Cause: RM proxy did not register properly or during advanced failure recovery, broker cleans up some already dead object reference.

Action: None.

04772 "%s"

Cause: Advanced failure recovery debugging message.

Action: Depending on the message, either internal or setup error.

04773 "Failure Recovery: Restart %s"

Cause: Standard failure recovery restarting process.

Action: None.

04774 "Failure Recovery: %s "

Cause: Standard failure recovery message.

Action: Depending on the message, either debugging message or internal error.

04775 "(%u, %u, %s)"

Cause: Message used by show state. Not an error.

04776 "(Total Instances, Creating Instances, Creation State for Host)"

Cause: Message used by show state. Not an error.

04777 "(%u, %u, %u)"

Cause: Message used by show state. Not an error.

04778 "(Total Servers, Creating Servers, Terminating Servers)"

Cause: Message used by show state. Not an error.

04779 "[Cartridges]"

Cause: Message used by show state. Not an error.

04780 "NOT RUNNING"

Cause: Message used by show state. Not an error.

04781 "DISABLED"

Cause: Message used by show state. Not an error.

04782 "AVAILABLE"

Cause: Message used by show state. Not an error.

04783 "[Cartridge Servers]"

Cause: Message used by show state. Not an error.

04784 "WEB"

Cause: Message used by show state. Not an error.

04785 "CORBA"

Cause: Message used by show state. Not an error.

04793 "Operation %(1)s returns exception %(2)s"

Cause: CORBA exception thrown while RM is making a request to other component

Action: Check the appropriate components's log for more info's

04794 "Virtual memory of host %(1)s is reported at %(2)u and recorded as %(3)u"

Debug message.

04795 "Host % (1)s is running out of virtual memory (at % (2)u). Unable to create more cartridge server for application %(3)s"

Cause: Machine is running out of virtual memory.

Action: Create the virtual memory size of the machine.

04796 "Shutting down Cartridge Server % (1)s pid % (2)u at % (3)s to free virtual memory"

Cause: Machine is running low on virtual memory.

Action: Create the virtual memory size of the machine

05000 - 05499 : Oracle PL/SQL Cartridge errors

05100 "Unable to connect due to Oracle error %(1)d"

Cause: The Oracle PL/SQL Cartridge was unable to connect to the specified Database due to an Oracle error.

Action: See the corresponding Oracle error. Common errors are: invalid user-name/password - check the PL/SQL Cartridge configuration file; Oracle not available - start up the database.

05101 "Execution failed due to Oracle error %(1)d"

Cause: Oracle database error or possible URL syntax error.

Action: See the Oracle error on the error stack. Or, verify the URL syntax is as follows: http://<listener>/application/virtual_directory/<plsql>.

05102 "Initialization failed due to error %(1)d"

Cause: Oracle database error.

Action: See the Oracle error on the error stack.

05103 "Error %(1)d during initialization"

Cause: Oracle database error.

Action: See the Oracle error on the error stack.

05104 "Unable to attach to host database: [(1)s], [(2)s], [(3)s]"

Cause: Oracle database error.

Action: See the Oracle error on the error stack. The parameters in the error are [ORACLE_HOME], [ORACLE_SID], [SQLNET V2 SERVICE].

05105 "Agent : authorization failed due to error %(1)d"

Cause: Oracle database error.

Action: See the Oracle error on the error stack.

05106 "Unable to open transaction resource manager: [(1)s], [(2)s], [(3)s]"

Cause: TXN Resource Manager cannot be opened.

Action: The parameters in the error are [USER_NAME], [ORACLE_SID], [SQLNET V2 SERVICE].

05107 "TXN Resource Manager cannot be closed"

Cause: TXN Resource Manager cannot be closed.

Action: Check configuration.

05108 "TXN Resource Info cannot be obtained"

Cause: TXN Resource Info cannot be obtained.

Action: Check configuration.

05110 "No stored procedure specified to call"

Cause: PL/SQL Cartridge requires the PATH_INFO environment variable to be set. PATH_INFO is set based on information passed through the URL after the virtual path name and before the "?" or end of the URL.

Action: specify a stored procedure name after the virtual path name in the URL.

05111 "No stored procedure matches this call with the arguments passed"

Cause: The procedure and parameters passed to PL/SQL Cartridge don't match any existing stored procedures.

Action: verify that there is a stored procedure (not function) with no RECORD parameters which matches the parameters passed. If no value was passed for a parameter, be sure that the stored procedure was declared to have a default value for that parameter. Check for typographical errors.

05112 "Too many procedures matches this call"

Cause: The procedure and parameters passed to PL/SQL cartridge match too many existing stored procedures.

Action: This should only happen if there are overloaded stored procedures, and that in two different versions of the procedure, a given parameter is declared in one as a scalar and the other as a PL/SQL table.

05113 "Protection violation accessing PL/SQL procedure %s"

Cause: Somebody trying to access the owa packages directly through URL.

Action: This should only happen if somebody is trying to access the PL/SQL Cartridge packages/procedures directly through URLs. If you want this to be enabled, modify the configuration through PL/SQL Agent administration pages.

05150 "HTTP server Error - environment variable %(1)s is NULL or non-existent"

Cause: The HTTP server or other invoking application did not set the listed environment variable.

Action: Contact your HTTP server or other invoking application vendor.

05151 "Port %(1)s not in list of valid ports : %(2)s"

Cause: The network port that the invoking HTTP server is listening on is not a valid port for this PL/SQL Cartridge Agent.

Action: Add this port to the list of valid ports for this Agent, or access this agent through a HTTP server listening on a valid port.

05200 "Agent %(1)s not found in configuration file"

Cause: The first piece of the virtual path name in the URL did not correspond to a PL/SQL Cartridge Agent in the configuration file.

Action: Correct the URL, or create the desired agent.

05201 "Agent parameter %(1)s not found for agent %(2)s"

Cause: A parameter required by the Oracle PL/SQL Cartridge was not found in the configuration file along with the specified agent.

Action: Modify the PL/SQL Cartridge agent configuration using the PL/SQL Cartridge administration form.

05202 "No agents are found in wrb.app or owa.cfg file"

Cause: A agent parameter section required by the PL/SQL cartridge was not found either in the **wrb.app** file or in the **owa.cfg** file.

Action: Modify the PL/SQL cartridge configuration using the PL/SQL cartridge administration form.

05203 "Database Access Descriptor section not found for %(1)s"

Cause: A Database Access Descriptor (DAD) section required by the PL/SQL cartridge was not found in the **wrb.app** file along with the specified agent.

Action: Modify or create a new DAD section for the PL/SQL cartridge using the PL/SQL cartridge administration form.

05300 - 05399 : PL/SQL Cartridge Log Messages

05301 "Activating a new instance of the %s Cartridge; version %s"

Cause: Logging message.

Action: None.

05302 "Successfully activated the %s Cartridge"

Cause: Logging message.

Action: None.

05303 "Deactivating the %s Cartridge"

Cause: Logging message.

Action: None.

05304 "Successfully deactivated the %s Cartridge"

Cause: Logging message.

Action: None.

05305 "Reactivating the %s Cartridge"

Cause: Logging message.

Action: None.

05306 "Successfully reactivated the %s Cartridge"

Cause: Logging message.

Action: None.

05307 "Loading agents ..."

Cause: Logging message.

Action: None.

05308 "%s"

Cause: Logging message.

Action: None.

05309 "Logging on as user: %s"

Cause: Logging message.

Action: None.

05310 "Logging off"

Cause: Logging message.

Action: None.

05311 "Attaching to host: %s"

Cause: Logging message.

Action: None.

05312 "ORACLE_HOME: %s, ORACLE_SID: %s, CONNECT_STRING: %s"

Cause: Logging message.

Action: None.

05314 "Initializing agent: %s"

Cause: Logging message.

Action: None.

05315 "Client Charset: %s, DB Charset: %s"

Cause: Logging message.

Action: None.

05316 "Custom authentication is %s"

Cause: Logging message.

Action: None.

05317 "Attaching to trans%s, %s"

Cause: Logging message.

Action: None.

05318 "Detaching from transaction"

Cause: Logging message.

Action: None.

05319 "Executing within a transaction. No login necessary"

Cause: Logging message.

Action: None.

05321 "Detaching from all hosts ..."

Cause: Logging message.

Action: None.

05322 "Successfully detached from all hosts"

Cause: Logging message.

Action: None.

05323 "Warning: Version mismatch between PL/SQL packages %d.%d and %s Cartridge %s or execution of PL/SQL init block failed"

Cause: Logging message.

Action: None.

05330 "Authorizing request by agent: %s"

Cause: Logging message.

Action: None.

05331 "Successfully authorized agent: %s"

Cause: Logging message.

Action: None.

05332 "Authorizing with new username %s"

Cause: Logging message.

Action: None.

05333 "Authorization failed for agent: %s"

Cause: Logging message.

Action: None.

05340 "Executing request by agent: %s"

Cause: Logging message.

Action: None.

05341 "Invoking %s ..."

Cause: Logging message.

Action: None.

05342 "Execution complete, Elapsed time: %d, Bytes: %d"

Cause: Logging message.

Action: None.

05343 "Execution failed"

Cause: Logging message.

Action: None.

05350 "Parameter[%d]: %s"

Cause: Logging message.

Action: None.

05351 "Value[%d]: %s"

Cause: Logging message.

Action: None.

05400 - 05499 : External Listener Registration Errors and Messages

05401 "No registered listeners found"

Cause: No external listeners were found in the **owl.cfg** file.

Action: Use the External Registration utility to first register external listeners.

05402 "Home directory for external listener installation not specified"

Cause: The External Home field in the wlexreg utility front page was not specified.

Action: Fill the External Home field in the wlexreg utility with the home directory of the external installation.

05403 "Listeners successfully registered: %(1)s"

Cause: Information Message.

Action: None.

05404 "Listeners successfully unregistered: %(1)s"

Cause: Information Message.

Action: None.

05405 "Unrecognized listener software: %(1)s"

Cause: The listener software passed to the wlexreg utility was not recognized.

Action: Specify the listener software that the Oracle Application Server is known to support.

05406 "No listeners registered."

Cause: The listener names or the port numbers of the listeners to be registered are in conflict with existing listeners.

Action: Check existing listener names and port numbers in the **owl.cfg** file for uniqueness.

05407 "No listeners unregistered."

Cause: The specified listeners do not exist in **owl.cfg**.

Action: Check the **owl.cfg** file.

05500 - 05599 : Oracle PL/SQL Cartridge Administration errors and messages

05500 "PL/SQL Agent %(1)s successfully written"

Cause: Information Message.

Action: None.

05501 "PL/SQL Agent %(1)s successfully modified"

Cause: Information Message.

Action: None.

05502 "PL/SQL Agent %(1)s successfully deleted"

Cause: Information Message.

Action: None.

05503 "Password for PL/SQL Agent %(1)s successfully modified"

Cause: Information Message.

Action: None.

05504 "PL/SQL Agent %(1)s successfully written. Verify the PL/SQL output in %(2)s"

Cause: The PL/SQL Agent Administration program successfully wrote the specified agent and performed all actions requested. The program, however, cannot detect errors which may have occurred while installing the PL/SQL.

Action: Check the output in the file specified and verify that there are not unexpected error messages.

05520 "PL/SQL Agent %(1)s not deleted because it does not exist"

Cause: Information Message.

Action: None.

05521 "PL/SQL Agent %(1)s submission failed because the passwords submitted do not match"

Cause: The password and the "confirm password" field do not match.

Action: Retype both passwords and re-submit the form.

05522 "PL/SQL Agent %(1)s submission failed because password identification was selected and the submitted password was NULL"

Cause: The form submitted indicated that the PL/SQL Agent should use a password to connect to the database, however no password was provided.

Action: Select operating system authentication for this agent, or provide a password for the given PL/SQL Agent Database User.

05523 "PL/SQL Agent %(1)s submission failed because value for mandatory parameter %(2)s is NULL"

Cause: Value for mandatory parameter: NULL.

Action: Fill in the specified field and re-submit the form.

05524 "PL/SQL Agent %(1)s submission failed because both %(2)s and %(3)s are NULL"

Cause: One of the two parameters listed must not be null.

Action: Fill in one of the listed fields and re-submit the form.

05525 "PL/SQL Agent %(1)s submission failed because a agent with the same name already exists"

Cause: Agents with the same name cannot coexist.

Action: Choose another name for the PL/SQL Agent you are attempting to create, or delete the existing agent.

05526 "PL/SQL Agent %(1)s submission failed due to error %(2)s"

Cause: External (Database) error.

Action: See the associated error and take the appropriate action.

05527 "PL/SQL Agent %(1)s submission failed because the %(2)s Username and Password are invalid"

Cause: Either the PL/SQL Agent Database User name and password, or the DBA username and password, is not a valid username/password combination for the specified database.

Action: Correct the username and password and re-submit the form.

05528 "PL/SQL Agent %(1)s submission failed because the DBA User submitted does not have %(2)s privileges"

Cause: DBA user has insufficient privileges.

Action: Choose a different Oracle username and password for the DBA user submitted, or have the specified privilege granted to this user by another DBA.

05529 "PL/SQL Agent %(1)s to modify does not exist"

Cause: The user chose to modify an existing PL/SQL Agent, however that agent does not exist. This error should not occur unless the agent to modify was deleted from a different form after this agent modification form was generated.

Action: Create a new PL/SQL Agent.

05530 "PL/SQL Agent %(1)s submission failed because the NLS Language could not be determined"

Cause: The PL/SQL Cartridge Administration package was unable to lookup the NLS Language for the specified database.

Action: Specify the value explicitly or submit a valid dba username and password.

05531 "PL/SQL Agent %(1)s submission failed because neither Server Manager, nor SQLDBA could be run"

Cause: The PL/SQL Cartridge Administration package was unable to install the Oracle Application Server Developer's Toolkit which must be done from Server Manager (line mode) or SQLDBA.

Action: Install either Server Manager or SQLDBA in the ORACLE_HOME where the PL/SQL Cartridge administration is installed.

05532 "Transaction %(1)s successfully written."

Cause: Information Message.

Action: None.

05533 "Transaction %(1)s successfully modified."

Cause: Information Message.

Action: None.

05534 "Transaction %(1)s successfully deleted."

Cause: Information Message.

Action: None.

05535 "Transaction %(1)s submission failed because value for mandatory parameter %(2)s is NULL"

Cause: Value for mandatory parameter: NULL.

Action: Fill in the specified field and re-submit the form.

05536 "Transaction %(1)s submission failed because PL/SQL Agent %(2)s does not exist in wrb.app file"

Cause: wrb.app is corrupt.

Action: Need to reload the PL/SQL Agent administration page for this PL/SQL Agent.

05537 "Transaction %(1)s submission failed because a transaction with this name already exists."

Cause: Creation of duplicate transactions not legal.

Action: Specify a different name for this transaction.

05538 "PL/SQL Agent %(1)s submission failed because neither Server Manager, nor SQLDBA could be run"

Cause: The PL/SQL Cartridge Administration package was unable to install the Oracle Application Server Developer's Toolkit which must be done from Server Manager (line mode) or SQLDBA.

Action: Install either Server Manager or SQLDBA in the ORACLE_HOME where the PL/SQL Cartridge administration is installed.

05539 "PL/SQL Agent %(1)s submission failed because the specified DAD is missing from WRB configuration file"

Cause: Invalid DAD is specified.

Action: Make sure that DAD specified is in the WRB configuration file.

05540 "Submission failed because the specified DAD %(1)s does not have username stored in WRB configuration file"

Cause: The specified DAD was created with 'Store the user name and password in the DAD' option DISABLED.

Action: Either select a different DAD which has its username stored or change this DAD to store the username using DAD Administration form.

05541 "Submission failed because the DBA Username for the remote database accessed by specified DAD is not specified"

Cause: The specified DAD accesses a remote Database, hence needing the DBA Username and password to install the PL/SQL toolkit.

Action: Please specify the correct DBA Username and Password for the remote database accessed by this DAD.

05542 "PL/SQL Agent %(1)s submission failed due to error %(2)s"

Cause: External (Database) error.

Action: See the associated error and take the appropriate action.

05550 - 05600 : Oracle PL/SQL Cartridge Administration - DAD errors and messages

05550 "DAD %(1)s successfully written"

Cause: Information Message.

Action: None.

05551 "DAD %(1)s successfully modified"

Cause: Information Message.

Action: None.

05552 "DAD %(1)s successfully deleted"

Cause: Information Message.

Action: None.

05553 "Password for DAD %(1)s successfully modified"

Cause: Information Message.

Action: None.

05554 "DAD %(1)s successfully written. Verify the output in %(2)s"

Cause: The PL/SQL Cartridge Administration program successfully wrote the specified DAD and performed all actions requested. The program, however, cannot detect errors which may have occurred while installing the PL/SQL.

Action: Check the output in the file specified and verify that there are not unexpected error messages.

05560 "DAD %(1)s not deleted because it does not exist"

Cause: Information Message.

Action: None.

05561 "DAD %(1)s submission failed because the passwords submitted do not match"

Cause: The password and the "confirm password" field do not match.

Action: Retry both passwords and re-submit the form.

05562 "DAD %(1)s submission failed because password identification was selected and the submitted password was NULL"

Cause: The form submitted indicated that the DAD should use a password to connect to the database, however no password was provided.

Action: Select operating system authentication for this DAD, or provide a password for the give PL/SQL Agent Database User.

05563 "DAD %(1)s submission failed because value for mandatory parameter %(2)s is NULL"

Cause: Value for Mandatory parameter: NULL.

Action: Fill in the specified field and re-submit the form.

05564 "DAD %(1)s submission failed because both %(2)s and %(3)s are NULL"

Cause: One of the two parameters listed must not be null.

Action: Fill in one of the listed fields and re-submit the form.

05565 "DAD %(1)s submission failed because a DAD with the same name already exists"

Cause: Two DADs with the same name cannot coexist.

Action: Choose another name for the DAD you are attempting to create, or delete the existing DAD.

05566 "DAD %(1)s submission failed due to error %(2)s"

Cause: External (Database) error.

Action: See the associated error and take the appropriate action.

05567 "DAD %(1)s submission failed because the %(2)s Username and Password are invalid"

Cause: Either the DAD Database User name and password, or the DBA username and password, is not a valid username/password combination for the specified database.

Action: Correct the username and password and re-submit the form.

05568 "DAD %(1)s submission failed because the DBA User submitted does not have %(2)s privileges"

Cause: DBA user has insufficient privileges.

Action: Choose a different Oracle username and password for the DBA user submitted, or have the specified privilege granted to this user by another DBA.

05569 "DAD %(1)s submission failed because the DBA Username and Password are invalid"

Cause: DBA Username and password submitted are invalid.

Action: Check and resubmit with correct info.

05570 "DAD %(1)s submission failed because the NLS Language could not be determined"

Cause: The PL/SQL Cartridge Administration package was unable to lookup the NLS Language for the specified database.

Action: Specify the value explicitly or submit a valid dba username and password.

05571 "DAD %(1)s submission failed because neither Server Manager, nor SQLDBA could be run"

Cause: The PL/SQL Cartridge Administration package was unable to install the Oracle Application Server Developer's Toolkit which must be done from Server Manager (line mode) or SQLDBA.

Action: Install either Server Manager or SQLDBA in the ORACLE_HOME where the PL/SQL Cartridge administration is installed.

05573 "Specified Host: %(1)s is remote, specify Network Service Name to use to connect to the Database"

Cause: Specified host is remote, hence Network Service Name is a mandatory parameter.

Action: Specify the network service name (connect string) for the database.

05574 "Section: %(1)s does not exist in site.app"

Cause: **site.app** must have got corrupted.

Action: Please make sure that you have the correct **site.app** in right place.

05575 "Cannot write Section: %(1)s into site.app"

Cause: **site.app** might not have the write permission set on it.

Action: Please make sure that you set the write permission for **site.app**.

05577 "Cannot make this DAD Transactional because it does not have connect string."

Cause: To enable a DAD for Transactions, it should contain a connect string.

Action: Go to the specified DAD page under Oracle Application Server/DB Access Descriptor and specify connect string for the DAD.

05578 “Cannot make this DAD Transactional because it does not have username/password.”

Cause: To enable a DAD for Transactions, it should contain a username/password stored in it.

Action: Go to the specified DAD page under Oracle Application Server/DB Access Descriptor and make sure that you do have the “Store the username and password in the DAD” checkbox checked.

05600 - 05699 : Oracle Web Database Administration errors

05600 "Startup of database %(1)s successful"

Cause: Information Message.

Action: None.

05601 "Shutdown of database %(1)s successful"

Cause: Information Message.

Action: None.

05610 "Startup of database %(1)s failed due to error %(2)s"

Cause: External (database) error.

Action: See the associated error and take the appropriate action.

05611 "Shutdown of database %(1)s failed due to error %(2)s"

Cause: External (database) error.

Action: See the associated error and take the appropriate action.

05620 "DB Admin : no database selected"

Cause: A button was pressed to startup or shutdown the database, but no database had been selected.

Action: Return to the administration screen and select a database.

05621 "DB Admin : %(1)s is already running."

Cause: A request was made to start up a database, but that database is already running.

Action: If you would like to restart the database, shut it down first or choose "Startup Force."

05622 "DB Admin : %(1)s is already shut down"

Cause: A request was made to shut down a database, but that database is already shut down.

Action: None.

05623 "DB Admin : parameter file %(1)s is larger than maximum size %(2)s bytes"

Cause: The initialization file listed was larger than the maximum allowable size.

Action: Reduce the size of the initialization file.

05700 - 05799 : Oracle Web Listener Configuration errors and messages

05700 "Configuration for Web Listener %(1)s successfully written"

Cause: Information Message.

Action: None.

05701 "Configuration for Web Listener %(1)s successfully deleted"

Cause: Information Message.

Action: None.

05710 "Value submitted for %(1)s must not be NULL"

Cause: Value cannot be NULL.

Action: Type a value for the specified parameter and re-submit the form.

05711 "Port %(1)s is already in use by the Oracle Web Administration Server"

Cause: The port specified for service creation or modification is already in use by the Oracle Application Server Administration Server.

Action: Choose another port to run one of the Web Listeners on.

05712 "The Oracle Web Listener %(1)s is already configured to run on port %(2)s"

Cause: The port specified for service creation or modification is already in use by another Oracle Web Listener.

Action: Choose another port to run one of the Web Listeners.

05713 "Value for %(1)s must be between %(2)s and %(3)s"

Cause: Value out of range.

Action: Specify a value between the two limits and resubmit the form.

05714 "For ports less than %(1)s, the effective userid must be %(2)s"

Cause: Ports below that specified require superuser privileges to run a Web Listener on it.

Action: Configure the Web Listener to run on a unrestricted port, or set the effective userid for this Web Listener the superuser.

05715 "An Oracle Web Listener named %(1)s already exists"

Cause: Listener names must be unique.

Action: Name the submitted listener something else.

05716 "Port Number %(1)s is duplicated in the Addresses and Ports list"

Cause: Port numbers must be unique.

Action: Remove duplication and resubmit the form.

05717 "Fill out form has unknown input field format"

Cause: Oracle admbin/.html files have probably been tampered with.

Action: Restore original files.

05718 "The Web Listener %(1)s was successfully started."

Cause: Information Message.

Action: None.

05719 "The Web Listener %(1)s was successfully reloaded."

Cause: Information Message.

Action: None.

05720 "The Web Listener %(1)s was successfully signalled to stop"

Cause: Information Message.

Action: None.

05721 "The Web Listener %(1)s failed to start:"

Cause: Information Message (followed by the cause).

Action: See the associated error message.

05722 "The Web Listener %(1)s failed to reload:"

Cause: Information Message (followed by the cause).

Action: See the associated error message.

05723 "The Web Listener %(1)s was not stopped"

Cause: Information Message (followed by the cause).

Action: See the associated error message.

05724 "Error in listener configuration format in file or input form"

Cause: Listener Config file in wrong or corrupted format.

Action: Please abide by the listener config file syntax if edited manually.

05725 "WRB Configuration file not copied from %(1)s to %(2)s"

Cause: Copying of file failed due to system error.

Action: Make sure wladmin utility has permission to read/write.

05726 "Listener Name %(1)s must be an alpha-numeric string"

Cause: Listener Name cannot be NON-alpha-numeric string.

Action: Only alphanumeric strings are accepted for listener name.

05727 "Listener Name %(1)s too long"

Cause: Since cfg, app files are sv<lsnrName>.<ext>, the length of the listener name is limited.

Action: Use a shorter name.

05728 "Given Listener Name %(1)s is reserved"

Cause: The listener name chosen is a reserved word.

Action: Use a different name.

05729 "Given User ID %(1)s is invalid"

Cause: Given User ID does not exist on the system.

Action: Specify a valid/existing User ID.

05730 "Given Group ID %(1)s is invalid"

Cause: Given Group ID does not exist on the system.

Action: Specify a valid/existing Group ID.

05731 "Admin Listener Running as User '%(1)s' needs to be running as 'root'"

Cause: Listeners cannot be created other than by user 'root'.

Action: Configure 'admin' listener to run as root, then create listener.

05732 "Cannot change ownership of %(1)s"

Cause: Insufficient privileges for the 'admin' listener.

Action: Please make sure the 'admin' listener is running as 'root'.

05734 "No users specified. Hence, no changes recorded."

Cause: No users specified for the protection scheme.

Action: Enter one or more users and retry.

05735 "No groups specified. Hence, no changes recorded."

Cause: No groups specified for the protection scheme.

Action: Enter one or more groups and retry.

05736 "No realms specified. Hence, no changes recorded."

Cause: No realms specified for the protection scheme.

Action: Enter one or more realms and retry.

05737 "User[% (1)s] specified in Group[% (2)s] does not exist"

Cause: The user does not exist under this protection scheme.

Action: Either remove this user from the group or add the user under this protection scheme and retry.

05738 "Group[% (1)s] specified in Realm[% (2)s] does not exist"

Cause: The group does not exist under this protection scheme.

Action: Either remove this group from the realm or add the group under this protection scheme and retry.

05739 "Password missing for User[% (1)s]"

Cause: No password specified for the user.

Action: Enter password for the user and retry.

05740 "Basic Protection Scheme deleted successfully"

Cause: Information Message.

Action: None.

05741 "Digest Protection Scheme deleted successfully"

Cause: Information Message.

Action: None.

05742 "Basic protection scheme information recorded successfully"

Cause: Information Message.

Action: None.

05743 "Digest protection scheme information recorded successfully"

Cause: Information Message.

Action: None.

05744 "No information to record"

Cause: Information Message.

Action: None.

05745 "Failed due to insufficient privileges to create <%(1)s> directory under <\$ORAWEB_HOME/../../admin/\$ORAWEB_SITE/httpd_...>"

Cause: The CGI-bin cannot create the above-mentioned directory under <\$ORAWEB_HOME/../../admin/\$ORAWEB_SITE/httpd_HOSTNAME> (non-OFA) or <\$ORACLE_BASE/admin/ows/\$ORAWEB_SITE/httpd_HOSTNAME> (OFA). To create the listener it needs to be able to do this.

Action: You must give sufficient privilege to the node-manager owner to write to the <.../httpd_> directory. Or have the node-manager owned by user with this privilege.

05746 "Parameter 'Port' not specified in configuration file: %s."

Cause: Possibly the specified configuration file is invalid. If not, parameter 'Port' is missing from the configuration file.

Action: Use the correct Configuration file for Apache Listener (httpd.conf). And make sure parameter 'Port' is specified in the above configuration file.

05747 "Trusted"

Cause: Token for translation

Action: None

05748 "Untrusted"

Cause: Token for translation

Action: None

05749 "This certificate is not present in the database."

Cause: The certificate database has become inconsistent. This could be because the database has got corrupted or some other admin. user has deleted the certificate.

Action: None

05750 "Certificate(s) deleted"

Cause: The certificates were deleted successfully.

Action: None

05751 “An error occurred while parsing the certificate”

Cause: An error occurred while parsing the certificate that the user is trying to add.

Action: Check the type of the certificate

05752 “Cannot add certificate. The certificate database is full”

Cause: The certificate database can accommodate only a certain number of certificates.

Action: Delete the certificates that are not useful.

05753 “Certificate %s added successfully”

Cause: The certificate was added to the certificate database.

Action: None

05754 “Certificate %s is now %s”

Cause: The certificate state was updated

Action: None

05755 “Do not Trust”

Cause: Token for translation

Action: None

05756 “Trust”

Cause: Token for translation

Action: None

05758 “One or more of the FORM parameters are incorrect”

Cause: A corruption occurred in the template

Action: Fix the template

05800 - 05899 : Oracle Web Request Broker Administration messages

05801 "The input from the form in the HTML file %(1)s has incorrect format"

Cause: Form has unexpected input field/value.

Action: Make sure only the OWS HTML templates are used to make submissions to the Oracle Application Server Manager utilities.

05802 "The input parameter %(1)s must not be empty"

Cause: Required field not filled in submitted form.

Action: Fill in all required fields.

05803 "WRB Configuration for listener %(1)s successfully written"

Cause: Information Message.

Action: None.

05804 "The Oracle Application Server Manager found no record of the listener %(1)s"

Cause: Non-existent listener attempted to be accessed. owl.cfg might have been corrupted.

Action: Make sure a non-existent listener is not referred to.

05805 "Could not copy WRB configuration from listener %(1)s to listener %(2)s"

Cause: WRB configuration file of "from" listener may not exist. System file copying error.

Action: Make sure wrbadm utility has permissions to read and write, and the source file exists.

05806 "Successfully copied WRB configuration from listener %(1)s to listener %(2)s"

Cause: Information Message.

Action: None.

05807 "Successfully deleted WRB configuration for listener %(1)s"

Cause: Information Message.

Action: None.

05808 "Successfully deleted configuration of cartridge %(1)s for listener %(2)s"

Cause: Information Message.

Action: None.

05809 "Modification of cartridge %(1)s for listener %(2)s successfully completed"

Cause: Information Message.

Action: None.

05810 "Configuration of cartridge %(1)s for listener %(2)s not found"

Cause: Attempt to modify or delete a cartridge configuration that doesn't exist.

Action: Reload the WRB Configuration form to get current list of cartridges for this listener.

05811 "Cartridge section not found"

Cause: Attempt to modify or delete a cartridge configuration that doesn't exist.

Action: Reload the WRB Configuration form to get current list of cartridges.

05812 "WRB Configuration successfully written"

Cause: Information Message.

Action: None.

05813 "Successfully deleted WRB configuration"

Cause: Information Message.

Action: None.

05814 "Modification of cartridge %(1)s successfully completed"

Cause: Information Message.

Action: None.

05815 "Successfully deleted configuration of cartridge %(1)s"

Cause: Information Message.

Action: None.

05816 "Invalid or no wrb.app file"

Cause: Invalid or no **wrb.app** file.

Action: Reload the WRB Configuration form.

05817 "Cartridge %(1)s already registered"

Cause: Do not need to register this cartridge or name is spelled incorrectly.

Action: Specify a different name.

05818 "Completed Cartridge Registration successfully"

Cause: Information Message.

Action: None.

05819 "[Cartridge] section missing in wrb.app"

Cause: wrb.app is corrupted.

Action: Reload the WRB Configuration form.

05820 "Modification of VPM section %(1)s successfully completed"

Cause: Information Message.

Action: None.

05821 "Successfully deleted configuration of VPM section %(1)s"

Cause: Information Message.

Action: None.

05822 "Given VPM section not found"

Cause: Attempt to modify or delete a VPM section that doesn't exist.

Action: Reload the WRB Configuration form to get current list of VPM sections.

05823 "Given Virtual Path not found"

Cause: Invalid Virtual Path.

Action: Reload the WRB Configuration form to get current list of Virtual Paths.

05824 "Given Cartridge %(1)s Already Registered"

Cause: Cartridge already registered.

Action: Give a different name to the cartridge.

05825 "Successfully added Cartridge Registration"

Cause: Information Message.

Action: None.

05826 "Successfully modified Cartridge Registration"

Cause: Information Message.

Action: None.

05827 "Successfully deleted Cartridge Registration"

Cause: Information Message.

Action: None.

05828 "Cartridge %(1)s is not Registered"

Cause: Cartridge not registered.

Action: Specify name of a Registered Cartridge.

05829 "WRB System Parameters successfully written"

Cause: Information Message.

Action: None.

05830 "Unable to start Web Request Broker (wrb)"

Cause: External owsctl error.

Action: Please refer to owsctl utility documentation.

05831 "Unable to stop Web Request Broker (wrb)"

Cause: Information message (cause dynamically generated).

Action: Please refer to owsctl utility documentation.

05832 "Unable to query status of Web Request Broker (wrb)"

Cause: External owsctl error.

Action: Please refer to owsctl utility documentation.

05833 "Web Request Broker (wrb) started successfully"

Cause: Information Message.

Action: None.

05834 "Web Request Broker (wrb) stopped successfully"

Cause: Information Message.

Action: None.

05835 "Web Request Broker (wrb) queried successfully"

Cause: Information Message.

Action: None.

05836 "The 'Min'(minimum) # of cartridge instances cannot be negative"

Cause: Negative # of instances is invalid.

Action: Please enter a postive value.

05837 "The 'Max'(maximum) # of cartridge instances cannot be negative"

Cause: Negative # of instances is invalid.

Action: Please enter a postive value.

05838 "Cartridge '%(1)s' specified in '%(2)s' is not valid as it is not registered"

Cause: The specified cartridge is not registered.

Action: Please specify cartridge which has been registered or proceed to Cartridge Administration page to register this cartridge.

05839 "Cartridge '%(1)s' specified in '%(2)s' is not valid as it is a duplicate"

Cause: The specified cartridge is specified twice in the same section.

Action: Please delete the previous entry of this cartridge or chose a different registered cartridge.

05840 "Cartridge '%(1)s' specified in '%(2)s' is not valid because it does not have an entry in 'Applications and Objects'"

Cause: Missing entry for this cartridge in [Apps] in WRB Config file.

Action: Please specify cartridge which has an entry in 'Applications and Objects.'

05841 "Could not read Configuration file '%(1)s' in directory '%(2)s'"

Cause: Could be because the configuration file does not exist or the 'Admin listener' does not have sufficient privileges to read it.

Action: Check configuration file location/format.

05842 "Could not write Configuration file '%(1)s' in directory '%(2)s'"

Cause: Could be because the 'Admin listener' does not have sufficient privileges to write into the above directory.

Action: Make sure this directory has sufficient privileges for the 'Admin Listener' owner.

05843 "Virtual Path Manager (vpm) started successfully"

Cause: Information Message.

Action: None.

05844 "Unable to start Virtual Path Manager (vpm)"

Cause: Information Message.

Action: None.

05845 "Unable to stop Virtual Path Manager (vpm)"

Cause: Information Message.

Action: None.

05846 "Virtual Path Manager (vpm) stopped successfully"

Cause: Information Message.

Action: None.

05847 "Unable to initialize Virtual Path Manager (vpm)"

Cause: Information Message.

Action: None.

05848 "Virtual Path Manager (vpm) initialized successfully"

Cause: Information Message.

Action: None.

05900 - 05999 : Oracle Application Server Registration errors and messages

05900 "Registration successful. Thank-you for your time."

Cause: Information Message.

Action: None.

05901 "Please enter a value for field %(1)s"

Cause: The specified field is a required field for registration.

Action: Type a value into the specified field and re-submit the form.

06000 - 06099 : JWeb Cartridge errors and messages

06000 "Activating a new instance of the %(1)s Cartridge, version %(2)s"

Cause: Logging Message.

Action: None.

06001 "Java VM version= %(1)s"

Cause: Logging Message.

Action: None.

06002 "Configuration ..."

Cause: Logging Message.

Action: None.

06003 "%(1)s = %(2)s"

Cause: Logging Message.

Action: None.

06004 "Successfully activated the %(1)s Cartridge"

Cause: Logging Message.

Action: None.

06005 "Processing %(1)s Cartridge request: %(2)s"

Cause: Logging Message.

Action: None.

06006 "Instance request count is %(1)d"

Cause: Logging Message.

Action: None.

06007 "Invoking application: %(1)s ..."

Cause: Logging Message.

Action: None.

06008 "Maximum Request count reached. Exiting..."

Cause: Logging Message.

Action: None.

06009 "%(1)s request complete: bytes: %(2)d, elapsed time: %(3)d msec"

Cause: Logging Message.

Action: None.

06010 "Deactivating %(1)s Cartridge Instance"

Cause: Logging Message.

Action: None.

06011 "%(1)s Cartridge - Java VM message: %(2)s"

Cause: Logging Message.

Action: None.

06012 "%(1)s Cartridge - Java Error message : %(2)s"

Cause: Logging Message.

Action: None.

06110 - 06150 : Oracle Application Server Cartridge Message

06110 "%-8s Cartridge"

06151 - 06199 : Java-PL/SQL errors and messages

06151 "Connected to database as user %(1)s"

Cause: Connected to a database.

Action: None.

06152 "Disconnected from database connection %(1)s"

Cause: Disconnected from a database.

Action: None.

06153 "Executing PL/SQL procedure %(1)s in %(2)s"

Cause: Executing a PL/SQL procedure.

Action: None.

06154 "%(1)s complete: elapsed time = %(2)s msec"

Cause: A PL/SQL procedure is executed.

Action: None.

06155 "Database error occurred in connection %(1)s. Error message follows."

Cause: A database error occurred when Java-PL/SQL interacted the database.

Action: Check the included error message from the database and correct the problem.

06180 "Java wrapper-class %(1)s is generated for PL/SQL package %(1)s"

Cause: A Java class-wrapper is generated for a PL/SQL package.

Action: None.

06400 - 06599 : LiveHTML Cartridge

06401 "Activating a new instance of the %s Cartridge Version %s"

Cause: Logging Message.

Action: None.

06402 "Successfully activated the %s Cartridge"

Cause: Logging Message.

Action: None.

06403 "%s Cartridge Reloaded"

Cause: Logging Message.

Action: None.

06404 "Deactivating %s cartridge instance"

Cause: Logging Message.

Action: None.

06405 "Configuration ... "

Cause: Logging Message.

Action: None.

06450 "Instance request count is %d"

Cause: Logging Message.

Action: None.

06500 "Processing %s Cartridge Request: %s"

Cause: Logging Message.

Action: None.

06501 "Environement PATH_TRANSLATED not set"

Cause: Logging Message.

Action: None.

06502 "File Location: %s"

Cause: Logging Message.

Action: None.

06503 "Processing document..."

Cause: Logging Message.

Action: None.

06504 "Not a LiveHTML document. File being returned unprocessed"

Cause: File extension not registered as LiveHTML document.

Action: Add extension to cartridge configuration.

06505 "Maximum Request count reached. Exiting..."

Cause: Logging Message.

Action: None.

06506 "%s = %s"

Cause: Logging Message.

Action: None.

06507 "Error opening file: %s"

Cause: Most likely, file not found. Permissions problem is also a possibility.

06508 "Error parsing line (%d): %s"

Cause: Syntax error.

Action: Fix syntax.

06510 "Invalid value (%d): %s"

Cause: Value inappropriate for attribute.

Action: Use appropriate value.

06511 "Invalid Tag (%d): %s"

Cause: Tag not supported.

Action: Remove or fix tag name.

06512 "%s (%d): %s = %s"

Cause: Logging Message.

Action: None.

06513 "Invalid Attribute (%d): %s"

Cause: Attribute inappropriate for tag.

Action: Use appropriate attribute.

06514 "exec feature is disabled, tag not processed"

Cause: Logging Message.

Action: None.

06515 "%s Execution Done: bytes: %d, elapsed time: %d msec"

Cause: Logging Message.

Action: None.

06520 "included file must reside in a directory that descends from: %s"

Cause: Logging Message.

Action: None.

06521 "Error in parsing tag %s"

Cause: Logging Message.

Action: None.

06522 "File not found %s"

Cause: Logging Message.

Action: None.

06523 "Error in processing include file tag"

Cause: Logging Message.

Action: None.

06524 "Full path %s"

Cause: Logging Message.

Action: None.

06525 "Error (%d) in obtaining file info for file %s, Error number is %d"

Cause: Logging Message.

Action: None.

06531 "ICX request returned no data"

Cause: Logging Message.

Action: None.

06532 "Error in composing ICX URL's query string"**Cause:** Logging Message.**Action:** None.**06533 "Error in composing ICX URL's "****Cause:** Logging Message.**Action:** None.**06534 "ICX URL: %s"****Cause:** Logging Message.**Action:** None.**06535 "Failed to create ICX request handle"****Cause:** Logging Message.**Action:** None.**06536 "ICX authentication needed, current user/password will be used"****Cause:** Logging Message.**Action:** None.**06537 "ICX makeRequest Failed: %s"****Cause:** Logging Message.**Action:** None.**06538 "ICX makeRequest Succeeded"****Cause:** Logging Message.**Action:** None.**06539 "ICX returned HTML Doc Does Not Have <BODY> Tag"****Cause:** Logging Message.**Action:** None.**06540 "ICX Request Succeeded"****Cause:** Logging Message.**Action:** None.

06541 "ICX Service Not Loaded"

Cause: Logging Message.

Action: None.

06542 "Bad Parameters To ICX set AuthInfo Call"

Cause: Logging Message.

Action: None.

06543 "ICX Authentication Failed"

Cause: Logging Message.

Action: None.

06544 "Executing command failed"

Cause: Logging Message.

Action: None.

06545 "exec..cmd output not echoed, cmdecho is OFF"

Cause: Logging Message.

Action: None.

06546 "Error in getting exec file %s"

Cause: Logging Message.

Action: None.

06548 "Request Command url (icx) attribute failed"

Cause: Logging Message.

Action: None.

06549 "ICX diabled, Request:url not processed"

Cause: Logging Message.

Action: None.

06550 "ICX variable %s has no value found"

Cause: Logging Message.

Action: None.

06551 "Error in creating a pipe"

Cause: Logging Message.

Action: None.

06552 "Error in forking"

Cause: Logging Message.

Action: None.

06553 "Error in exec, errno is %d"

Cause: Logging Message.

Action: None.

06554 "Failed to initialize LiveHTML cartridge"

Cause: Fail to allocate memory to initialize LiveHTML.

Action: Increase memory or stop other applications and retry.

06555 "Failed to create Java Virtual Machine"

Cause: See the associated error message from Java Virtual Machine.

Action: Correct the error and retry.

06556 "Failed to destroy Java Virtual Machine"

Cause: See the associated error message from Java Virtual Machine.

Action: Correct the error and retry.

06557 "Failed to attach a thread to Java Virtual Machine"

Cause: See the associated error message from Java Virtual Machine.

Action: Correct the error and retry.

06558 "Failed to detach a thread to Java Virtual Machine"

Cause: See the associated error message from Java Virtual Machine.

Action: Correct the error and retry.

06559 "Failed to execute script page"

Cause: See the associated error message from Java Virtual Machine.

Action: Correct the error and retry.

06560 "Java Virtual Machine error: %s"

Cause: An error has occurred in Java Virtual Machine.

Action: This should be an internal error and a bug should be reported.

06600 - 06699 : Auth Server messages

06600 "Init error"

Cause: Could not initialize Authentication server CORBA object.

Action: Make sure network is up and that wrbasrv and wrbahsrv is running. Also, make sure that the medianet address server and other medianet processes are running.

06601 "Shutdown error"

Cause: Could not shutdown the Authentication server.

Action: Make sure network is up and that wrbasrv and wrbahsrv is running.

06602 "Unknown operation mode of %s"

Cause: The [AuthServ] section contains a value for Schemes that is unknown.

Action: Changed the [AuthServ] section to contain either **Schemes.INMEMORY** or **Schemes.ORB**.

06603 "Open library %s error: %s"

Cause: Could not open shared library.

Action: Ensure the shared library is indicated in the given path and has the correct permissions.

06604 "Library %s entry point %s error: %s"

Cause: Could not find the indicated entry point in the shared library.

Action: Make sure the version of the shared library is correct and is a valid Authentication server library.

06605 "Scheme %s not found."

Cause: The indicated scheme is not valid. There is no entry in the [AuthServ] section that contains the indicated scheme name.

Action: Ensure the [AuthServ] section refers to a valid scheme name.

06606 "Scheme ID %d not found"

Cause: Could not find the indicated scheme ID.

Action: Ensure the [AuthServ] section refers to a valid scheme name and that the network is up and that the **wrbasrv** and **wrbahsrv** processes are running.

06607 "Realm %s not found"

Cause: The indicated realm is not valid. The provider does not process the indicated realm or a network error occurred.

Action: Ensure the network is up and that the **wrbasrv** and **wrbahsrv** processes are running.

06608 "Realm ID %d not found"

Cause: Could not find the indicated scheme ID.

Action: Ensure the network is up and that the **wrbasrv** and **wrbahsrv** processes are running.

06609 "Scheme %s's lib not specified"

Cause: The [AuthServ] section refers to an authentication provider, but the shared library path is not specified.

Action: Ensure the authentication provider's shared library path is specified.

06610 "Scheme %s's impl ID not specified"

Cause: The [AuthServ] sections refers to an authentication provider, but the provider's implementation ID is not specified.

Action: Ensure the authentication provider's implementation ID is specified (and different from all other implementation IDs).

06611 "Invalid protect string format %s"

Cause: The protect string format is invalid.

Action: Ensure the protect string format is correct. The protect string format is documented in the administration guide. The general form is: "Scheme(Realm) [& or | Scheme2(Realm2) ...].

06612 "Insufficient authen. info"

Cause: There is not enough authentication information specified.

Action: There is probably a problem in the software where the client of the authentication server is not passing enough authentication information. Ensure the protect string is valid.

06613 "Inappropriate scheme-realm"

Cause: The authentication information specified is incorrect.

Action: There is probably a problem in the software where the client of the authentication server is not passing the correct authentication information. Ensure the protect string is valid.

06614 "Provider error in %s callback"

Cause: The authentication provider returned an error.

Action: Check the log file for additional information about the provider.

06615 "Authentication server not avail"

Cause: The authentication server is not available because we could not send a message to it.

Action: Ensure the **wrbasrv** process is running on the target machine and that the network is operational.

06616 "Auth scheme provider not avail"

Cause: The authentication server is not available because we could not send a message to it.

Action: Ensure the **wrbahsrv** process is running on the target machine and that the network is operational.

06617 "Bad argument in argv %s"

Cause: Invalid argument was passed to the Authentication server engine on the command line.

Action: Ensure the Authentication server processes **wrbasrv** and **wrbahsrv** are started without any arguments.

06618 "Out of Memory"

Cause: Out of memory.

Action: Increase the amount of RAM and/or swap space.

06619 "Service adaptor not ready"

Cause: The provider adaptor is not ready to receive messages.

Action: Ensure the **wrbahsrv** process is running and that the network is up.

06620 "Provider adaptor not ready"

Cause: The provider adaptor is not ready to receive messages.

Action: Ensure the **wrbahsrv** process is running and that the network is up.

06621 "Bad parameter(s)"

Cause: The Authentication server has detected a bad parameter passed into it from a client.

Action: Ensure there is enough memory on the system and enough swap space and that all protect strings are valid.

06622 "Bad authentication info type"

Cause: The Authentication server has detected a bad parameter passed into it from a client.

Action: Ensure there is enough memory on the system and enough swap space and that all protect strings are valid.

06623 "Duplicate realm"

Cause: There is a duplicate realm specified in the protect string.

Action: Ensure the protect string does not contain a duplicate realm value.

06624 "Internal error: %d"

Cause: There was an internal error with the indicated error code.

Action: This is probably a problem with the software and should be reported. Also, ensure the protect string is correct.

06625 "Unknown YS exception: %s"

Cause: There was an internal error generated by the CORBA software.

Action: This is probably a problem with the software and should be reported. Also, ensure the protect string is correct and that the network is up and running.

06626 "Bad Scheme Properties"

Cause: Could not determine the properties of a provider.

Action: Ensure the provider is up and running.

06627 "Context is invalid (either NULL or not as wras context)"

Cause: The client of the Authentication server passed in an invalid context.

Action: This is probably a problem with the client software and/or the Authentication server and should be reported.

06628 "Could not parse the protect string '%s' because the scheme name '%s' was not found"

Cause: Could not parse the indicated protect string because the indicated scheme name is not being implemented by any provider.

Action: Ensure the provider that implements the scheme is up and running and that the [AuthServ] section is valid.

06629 "Could not parse the protect string '%s' because the realm name '%s' was not found for scheme '%s'"

Cause: Could not parse the indicated protect string because the indicated scheme name is not being implemented by any provider.

Action: Ensure the provider that implements the scheme is up and running and that the [AuthServ] section is valid.

06630 "Cannot call in non-blocking mode using callback function"

Cause: Internal Error.

Action: Due to this type of error, please contact Oracle Worldwide Customer Support.

06631 "Cannot initialize the no-wait interface"

Cause: Internal Error.

Action: Due to this type of error, please contact Oracle Worldwide Customer Support.

06632 "Cannot invoke the do-op method on the no-wait interface"

Cause: Internal Error.

Action: Due to this type of error, please contact Oracle Worldwide Customer Support.

06633 "Auth server failure recovery mesg: %s"

Cause: Authentication server is not available.

Action: Make sure Authentication server is up.

06700 - 06799 : Auth Server Logging Msgs

06700 "Client interface has been initialized"

Cause: Logging Message.

Action: None.

06701 "Client interface has been terminated"

Cause: Logging Message.

Action: None.

06702 "Engine has been initialized"

Cause: Logging Message.

Action: None.

06703 "Engine has been terminated"

Cause: Logging Message.

Action: None.

06704 "Configuration section [%s] not found"

Cause: The indicated configuration section is not found.

Action: Ensure all providers have their own section in the **wrb.app** file. Also, make sure that the Authentication server has been configured with a Schemes item (for example, **Schemes.INMEMORY** or **Schemes.ORB**).

06705 "Scheme %s cannot dock because it is not CORBA mode (%d)"

Cause: The indicated scheme cannot dock because it has not been configured to run in CORBA mode.

Action: Ensure the provider for this scheme has been configured to run in CORBA mode and not INMEMORY mode.

06706 "Warning: %s setting \"%s\" not found"

Cause: Logging Message.

Action: None.

06707 "Scheme %s docked"

Cause: Logging Message.

Action: None.

06708 "Scheme %s's Implementation ID is \"%s\"."

Cause: Logging Message.

Action: None.

06709 "%s scheme config section not found"

Cause: Could not find the indicated configuration section in the **wrb.app** file.

Action: Verify the Authentication server configuration.

06710 "%s scheme has been initialized"

Cause: Logging Message.

Action: None.

06711 "%s scheme has been terminated"

Cause: Logging Message.

Action: None.

06712 "%s authentication failure: user %s, password \"%s\" is not authenticated. Wanted password \"%s\"."

Cause: Debugging message: authentication failed with reason.

Action: Verify username/password.

06713 "%s scheme: Duplicate user %s ignored."

Cause: The Authentication server encountered a duplicated user.

Action: Remove the redundant user.

06714 "%s authentication failure: User %s not found."

Cause: Could not find the indicated user in the **wrb.app** file.

Action: Add user to the **wrb.app** file.

06715 "%s scheme: Group %s has duplicate user %s."

Cause: The Authentication server encountered a duplicate user for a group.

Action: Remove the redundant user.

06716 "%s scheme: Could not find user %s for group %s."

Cause: Could not find the indicated user for the group.

Action: Add the user to the group.

06717 "%s scheme: Realm %s has duplicate group %s."

Cause: The realm specified a duplicate group.

Action: Remove the redundant group.

06718 "%s scheme: Could not find group %s for realm %s."

Cause: Could not find the indicated group for the realm.

Action: Add the group to the realm.

06719 "%s scheme: First character from %s in realm %s must be a '+' or '-'."

Cause: Invalid format. Format must be +<value> or -<value>.

Action: Ensure the format is correct. See the admin manual.

06720 "%s scheme: Invalid wildcard in %s in realm %s."

Cause: Invalid format. There are wildcards in incorrect places.

Action: Ensure the format is valid. See the Administration Guide.

06721 "%s scheme: Invalid format for %s in realm %s."

Cause: Invalid format.

Action: See the Administration Guide.

06722 "%s authentication failure: user %s, digest response \"%s\" is not authenticated. Wanted response \"%s\"."

Cause: Debugging message: authentication failed with reason.

Action: Verify username/password.

06723 "%s authentication failure: ip address of %s is not allowed for realm %s."

Cause: Debugging message: IP address not allowed.

Action: Verify configuration of allowed IP addresses.

06724 "%s authentication failure: domain %s is not allowed for realm %s."

Cause: Debugging message: Domain not allowed.

Action: Verify configuration of allowed domains.

06725 "%s authentication failure: user %s could not be authenticated against the Oracle database."

Cause: Debugging message: authentication failed with reason in Oracle database.

Action: Verify username/password in Oracle database.

06726 "%s scheme: Could not attach to the Oracle database using DAD %s, Oracle error is %s."

Cause: Using the DAD, could not attach to the Oracle database.

Action: Ensure the Oracle database is up and any SQLNet configuration is correct (for a remote database).

06727 "%s scheme: Could not logon to the Oracle database with username \"%s\" and password \"%s\", Oracle error is %d."

Cause: Could not log into the Oracle database.

Action: Ensure the Oracle database is up and any SQLNet configuration is correct (for a remote database).

06728 "%s scheme: Could not logon to the Oracle database with username \"%s\" and password \"%s\", Oracle error is %s."

Cause: Debugging message: could not log in with username/password.

Action: Ensure the username/password in the Oracle database is correct and that the Oracle database is up and any SQLNet configuration is correct (for a remote database).

06729 "%s scheme: Could not open a cursor to the Oracle database using DAD %s, Oracle error is %s."

Cause: Could not open the cursor.

Action: Ensure the Oracle database is up and any SQLNet configuration is correct (for a remote database).

06730 "%s scheme: Could not prepare the role %s. Role statement is %s, oracle error is %s."

Cause: Could not prepare the role.

Action: Ensure the Oracle database is up and any SQLNet configuration is correct (for a remote database). Also insure that the role exists.

06731 "%s scheme: Could not set the role %s for username %s in the Oracle database for group %s, Oracle error is %s."

Cause: Could not set the role.

Action: Ensure the Oracle database is up and any SQLNet configuration is correct (for a remote database). Also insure that the role exists and that the given user has access to the role.

06732 "%s scheme: Could not close the cursor to the Oracle database using DAD %s, Oracle error is %s."

Cause: Could not close the cursor.

Action: Ensure the Oracle database is up and any SQLNet configuration is correct (for a remote database).

06733 "%s scheme: Could not logoff from the Oracle database using DAD %s, Oracle error is %s."

Cause: Could not log off from the database.

Action: Ensure the Oracle database is up and any SQLNet configuration is correct (for a remote database).

06734 "%s scheme: Could not find the DAD entry in group %s for realm %s."

Cause: Cannot find the indicated DAD for the realm.

Action: Ensure the DAD exists and has been configured in the Oracle provider's realm.

06735 "%s scheme: Could not find the DAD %s."

Cause: Cannot find the DAD.

Action: Ensure the DAD exists.

06736 "%s scheme: Could not find the %s field for DAD %s."

Cause: Cannot find the indicated field in the DAD.

Action: Ensure the indicated field exists in the DAD.

06737 "%s scheme: Could not find neither an oracle_sid nor connect_string for DAD %s."

Cause: Cannot connect to Oracle database.

Action: Insure there is either an oracle_sid or connect_string in the DAD.

06738 "%s scheme: Both an oracle_sid and a connect_string for DAD %s is specified."

Cause: Cannot specify both an oracle_sid and a connect_string.

Action: Remove either the oracle_sid or the connect_string from the indicated DAD.

06739 "Fatal error %d: Could not initialize the configuration provider for %s. Exiting."

Cause: Could not initialize config provider.

Action: Ensure the **wrb.app** file exists and that the user that is bringing up the Oracle Application Server has sufficient rights.

06740 "Fatal error %d: Could not initialize the logger for %s. Exiting."

Cause: Could not initialize logger.

Action: Ensure the logger is configured correctly.

06741 "Could not start %s because we could not initialize the authentication service client interface. Error code = %d."

Cause: Could not start the indicated Authentication server process.

Action: Ensure the Authentication server configuration is correct and there is enough memory.

06742 "Could not start %s because we could not get the authentication server's engine context. Error code = %d."

Cause: Could not get Authentication server's engine context.

Action: Insure the Authentication server configuration is correct and there is enough memory.

06743 "Could not create the message queue for %s. Exception ID=%s."

Cause: **yocQueCreate** threw an exception.

Action: Make sure that there is no queue with the same name.

06744 "Could not create the implementation for %s. Exception ID=%s."

Cause: **yocImplCreate** threw an exception.

Action: Make sure that there is no implementation with the same name.

06745 "Could not create the object reference for the name server for %s. Exception ID=%s."

Cause: **yocObjCreate** threw an exception.

Action: Make sure that there is no implementation with the same name.

06746 "Could not register with the name server for %. Exception ID=%s."

Cause: Could not register with the name server.

Action: Make sure that the name server is responding (using `mnrm1s -r`) and that the name server does not already have the entry for the host with the same name.

06747 "Did not find any schemes for %. Check configuration."

Cause: When bringing up the process, there were no schemes defined in ORB mode. This is just a warning.

Action: Make sure that there are schemes in ORB mode. This is just a warning.

06748 "The WRB Authentication Host Server is now running."

Cause: Successfully brought up the wrbahsrv process.

Action: None.

06749 "The WRB Authentication Host Server could not be started. Check the log file for details."

Cause: Could not bring up the wrbahsrv process.

Action: See the log file for details.

06750 "The WRB Authentication Engine is now running."

Cause: Successfully brought up the wrbasrv process.

Action: None.

06751 "The WRB Authentication Engine could not be started. Check the log file for details."

Cause: Could not bring up the wrbasrv process.

Action: See the log file for details.

06752 "Debug: %s"

Cause: Used in generic debug messages.

Action: See the log file for details.

06753 "%s scheme: Duplicate acl %s ignored."

Cause: The Authentication server encountered a duplicated acl.

Action: Remove the redundant acl.

06754 "Duplicate Field %s in Item %s ignored"

Cause: The Authentication server encountered a duplicated entry for a server.

Action: Remove the redundant entry.

06755 "Incorrect value (%s) in Server %s, field %s"

Cause: The Authentication server encountered an incorrect value in an entry.

Action: Remove the incorrect value.

06756 "Invalid field %s in Server %s"

Cause: The Authentication server encountered an invalid field in an LDAP Server Section.

Action: Remove the incorrect field.

06757 "Incomplete Server Section for Server %s. %s Field(s) missing."

Cause: The Authentication server cannot find all entries that describe an LDAP Server.

Action: Check the **wrb.app** file for any missing entries for that server.

06758 "Incomplete RealmInfo Section for %s. %s Field(s) missing"

Cause: The Authentication server cannot find all entries that describe a Realm-Info.

Action: Check the **wrb.app** file for any missing entries for that RealmInfo.

06759 "%s does not correspond to an existing %s (Entry %s)"

Cause: The Authentication server cannot find a corresponding entry for that value.

Action: Check the **wrb.app** file for misspelling.

06760 "Duplicate Realm %s in [Cert] Section"

Cause: The Authentication server found a duplicate Realm name in the [Cert] Section.

Action: Remove the duplicate entry.

06761 "Failed to initialize session for LDAP Server %s."

Cause: The Authentication server could not initialize the session to the LDAP server.

Action: Check the server settings in **wrb.app**.

06762 "Failed to set options for LDAP Server %s. Error %s (error msg: %s)."

Cause: The Authentication server could not set the proper options for this LDAP Server.

Action: Check the availability of the server and try again.

06763 "Failed to login to LDAP Server %s. Error %s (error msg: %s)."

Cause: The Authentication server could not login to the specified LDAP Server.

Action: Check the username, password for the Admin user.

06764 "%s scheme: Could not allocate the OCI environment for DAD %s."

Cause: The Authentication server could not allocate an OCI environment.

Action: Make sure that you have enough memory.

06765 "%s scheme: Could not allocate an OCI handle for DAD %s."

Cause: The Authentication server could not allocate an OCI handle.

Action: Make sure that you have enough memory.

06766 "Search Failed for Server %s. Please look at LDAP Server log for details."

Cause: The Authentication server failed to complete an LDAP Search.

Action: Check your LDAP Server log file for details of the failure.

06767 "Missing section \"%s\" in %s"

Cause: The Authentication server cannot find the specified entry or the entry is incorrect.

Action: Check the **wrb.app** file for any missing or incorrect entries.

06768 "Syntax Error Detected while parsing acl <%s>"

Cause: The Authentication server could not parse an acl expression.

Action: Check this acl in the **wrb.app** file for syntax errors.

06769 "Timing: %s"

Cause: Used in performance measurements.

Action: Check the **wrb.log** file for timing info.

06770 "%s scheme has been initialized"

Cause: Logging Message.

Action: None.

06771 "%s scheme: could not reload the configuration provider."

Cause: Configuration provider process is down.

Action: Make sure the configuration provider is running.

06772 "%s scheme: could not decrypt password for user %s. Encrypted password is %s."

Cause: Security library error.

Action: Make sure decrypted password is less than 100 characters.

06773 "Crypt Auth Provider: Initialization failed with Exception %s."

Cause: Crypt provider failed to initialize

Action: Due to this type of error, please contact Oracle Worldwide Customer Support.

06774 "Duplicate group [%s] in Crypt Provider Configuration"

Cause: There is a duplicate group name in the Crypt Provider configuration

Action: Remove the duplicate name.

06775 "Missing [File] field in Crypt group: %s"

Cause: The [File] field in this group configuration is missing.

Action: Provide a valid file name as the value of this field.

06776 "Error [%d] while processing file: %s"

Cause: An error occurred while processing this Crypt provider file.

Action: Due to this type of error, please contact Oracle Worldwide Customer Support.

06777 "Exception [%s] in Crypt Monitoring thread while in function [%s]"

Cause: An error occurred in the crypt monitoring thread.

Action: Due to this type of error, please contact Oracle Worldwide Customer Support.

06778 "Received empty digital certificate for realm: %s"

Cause: No digital certificate was received from the listener.

Action: Make sure you have an SSL enabled HTTP connection, and that your crtridge has the 'GetClientCert' attribute enabled.

06800 - 06899 : Cartridge Configuration Administration (CGI-bin)

06801 "Given Minimum # of instances %(1)s is Invalid"

Cause: The given input value is not a positive number.

Action: Please input a positive number.

06802 "Given Maximum # of instances %(1)s is Invalid"

Cause: The given input value is not a positive number.

Action: Please input a positive number.

06803 "Cartridge with the name \"%(1)s\" already exists"

Cause: Cartridge with same name already exists.

Action: Please select a different name for this cartridge.

06804 "Cartridge \"%(1)s\" added successfully"

Cause: Information Message.

Action: None.

06806 "Successfully modified Cartridge Logger Configuration parameters"

Cause: Information Message.

Action: None.

06807 "Successfully deleted Cartridge Logger Configuration parameters"

Cause: Information Message.

Action: None.

06808 "Failure: Could not delete Cartridge %(1)s"

Cause: 'wrcfreg -d -c <cartridge_name>' command failed.

Action: Try this command manually. If this fails, please refer to wrcfreg documentation.

06809 "Successfully deleted Cartridge \"%(1)s\""

Cause: Information Message.

Action: None.

06810 "Cartridge \"%(1)s\" modified successfully"

Cause: Information Message.

Action: None.

06811 "Failure: Could not add cartridge `%(1)s'"

Cause: 'wrcfreg -i -c <cartridge_name> <cartridge file>' command failed.

Action: Try this command manually. If this fails, please refer to wrcfreg documentation.

06812 "Failure: Need web listener name to add cartridge `%(1)s'"

Cause: Listener dirmap info. found in cartridge info. file. Web listener name must be filled up to add the new cartridge.

Action: Fill up the Web listener name field in form.

06813 "Given Session Idle Time %(1)s is Invalid"

Cause: The given input value is not a positive number.

Action: Please input a positive number.

07500 - 07599 : Oracle Application Server Proxy errors and messages

07500 "Proxy switch could not be accessed"

Cause: Error while reading or writing proxy switch value.

Action: Check configuration file location/format.

07501 "Proxy Administration Form has invalid input values"

Cause: Form is being submitted with invalid field values.

Action: Check and correct field values.

07502 "Proxy switch successfully turned %(1)s"

Cause: Information Message.

Action: None.

07700 - 07800 : Error message for upgrade/migration utility

07700 "Successfully upgraded Oracle Application Server PL/SQL Agent DCDs"

Cause: Information Message.

Action: None.

07701 "Successfully upgraded Oracle Application Server `%(1)s'"

Cause: Information Message.

Action: None.

07702 "No Oracle WebServer PL/SQL Agent DCDs found to be upgraded."

Cause: No Oracle WebServer 2.x PL/SQL Agent DCDs have been defined.

Action: No Oracle WebServer 2.x PL/SQL Agent DCDs need be upgraded.

07703 "No Oracle WebServer chosen to be upgraded."

Cause: No Oracle WebServer 2.x have been defined.

Action: No Oracle WebServer 2.x need be upgraded.

07704 "Unable to open .app file `%(1)s' for upgrading Oracle Application Server `%(2)s'."

Cause: Unable to open the .app file for Oracle Application Server upgrade.

Action: Check if the .app file indicated exists and is readable and writable by the upgrade utility and redo the upgrade for this particular Oracle Application Server again after the current upgrade session is done.

07705 "Unable to open .cfg file `%(1)s' for upgrading Oracle Application Server `%(2)s'."

Cause: Unable to open the .cfg file for Oracle Application Server upgrade.

Action: Check if the .cfg file indicated exists and is readable and writable by the upgrade utility and redo the upgrade for this particular Oracle Application Server again after the current upgrade session is done.

07706 "Oracle Application Server `%(1)s' already registered with Oracle Application Server 4.0."

Cause: Oracle Application Server indicated has already registered with Oracle Application Server 4.0.

Action: Check if the owl.cfg file in Oracle Application Server 4.0 area to check the existence of the indicated Oracle Application Server. If it is there, remove it and redo the upgrade.

07707 "Unable to register Oracle Application Server `%(1)s' in Oracle Application Server 4.0."

Cause: Unable to register Oracle Application Server.

Action: Check if the **owl.cfg** file in Oracle Application Server 4.0 area is readable and writable by the upgrade utility and redo the upgrade.

07708 "Error occurs while trying to upgrade the SpyGlass Listener 1.2 to 2.1.%(1)s"

Cause: Error occurs while trying to upgrade the SpyGlass Listener 1.2 to 2.1.

Action: Check if you can manually upgrade by issuing command

```
sh $ORAWEB_HOME/admin/upgspyl2to21 sv<xxx>.cfg
```

07709 "Netscape Server `%(1)s' has been successfully migrated to Oracle Application Server 4.0."

Cause: Information Message.

Action: None.

07710 "Netscape Server `%(1)s' has name conflict with registered Oracle Application Server."

Cause: Oracle Application Server with name provided has already been registered. Migration tool is unable to migrate Netscape Server with the first 6 characters of the name identical with registered Oracle Application Server name.

Action: Please rename the Netscape server so that its first 6 characters of the name is not identical to any registered Oracle Application Server.

07711 "Illegal Netscape Server port number `%(1)s'."

Cause: User has inputted a bad Netscape Server port number.

Action: Port number should only be a number greater than 0.

07712 "Netscape Server `%(1)s' has been successfully configured for Oracle Web Request Broker."

Cause: Information Message.

Action: None.

07713 "Unable to copy file `%(1)s' to `%(2)s'."

Cause: Migration utility is unable to copy file.

Action: Make sure **wlmigrat** has permission to read and write and the source file exists.

07714 "Unable to update Netscape Server stop script `%(1)s'."

Cause: Migration utility is unable to update the Netscape server stop script.

Action: Make sure the file and directory are writable by migration utility.

07716 "There are no listeners to upgrade."

Cause: The upgrade utility cannot locate any listener.

Action: Make sure the path specified is correct.

07717 "The selected listener(s) already exist(s). Do you still want to upgrade?"

Cause: Listener(s) already exist(s).

Action: Click on Yes to upgrade or No to cancel.

07718 "The selected listener(s) has/have been upgraded."

Cause: Information Message.

Action: None.

07719 "Error occurred during upgrade. Please make sure the directories and listener cfg files are readable and writable."

Cause: The permissions of owl.cfg, listener configuration files, and/or directories are not readable or writable.

Action: Please change the permissions.

07720 "Can not locate the WRB configuration file. Please make sure the ORACLE_BASE or ORACLE_HOME and ORAWEB_SITE are correct."

Cause: ORACLE_BASE, ORACLE_HOME, or ORAWEB_SITE are not correct. wrb.app cannot be located."

Action: Please reenter these variables again.

07721 "The WRB has been upgraded."

Cause: Information Message.

Action: None.

07722 "There are no cartridges to upgrade."

Cause: The upgrade utility cannot locate any cartridges.

Action: Make sure the path specified is correct.

07723 "The Cartridge %(1)s has been upgraded successfully."

Cause: Information Message.

Action: None.

07724 "Cartridge %(1)s does not need an upgrade."

Cause: There are no virtual paths (excluding /sample/...) to be upgraded.

Action: If there are any genuine virtual paths whose name starts with /sample, then these need to be renamed.

07725 "%(1)s : Error occurred during cartridge upgrade"

Cause: Internal Error.

Action: Retry, if it persists, file a bug.

07726 "Cannot Upgrade 3.0 VRML cartridge: OracleWorlds not installed in OAS 4.0"

Cause: Oracle Application Server 4.0 does not have VRML/OracleWorlds installed.

Action: Install VRML/OracleWorlds on Oracle Application Server 4.0; then, retry this operation.

07727 "Cannot Upgrade 3.0 VRML cartridge: OracleWorlds not installed correctly on OAS 4.0"

Cause: Oracle Application Server 4.0 does not have VRML/OracleWorlds correctly installed.

Action: Install VRML/OracleWorlds on Oracle Application Server 4.0 again; then, retry this operation.

07728 "Could not completely upgrade 3.0 VRML cartridge: Agent missing from OAS 3.0"

Cause: Oracle Application Server 3.0 does not have the VRML agent.

Action: Check if [VRML_vrml] section exists in wrb.app; if yes, retry; if no, install VRML 3.0 correctly and retry again.

07729 "Warning: Upgrade from OracleWorlds config page"

Cause: Information Message.

Action: None.

07730 "All Cartridges have been upgraded successfully."

Cause: Information Message.

Action: None.

07731 "Upgrade failed because it could not backup %(1)s configuration file."

Cause: The upgrade utility creates a backup of the configuration file before starting. It will not proceed unless it can backup the file.

Action: Please make sure that the user account under which the admin listener is running has the privilege to read the configuration file.

07732 "Error: %(1)s Cartridge has already been upgraded to %(2)s Application."

Cause: The specified cartridge has already been upgraded.

Action: If you really want to upgrade again, delete the 4.0 Application then, retry.

07733 "Failed to upgrade %(1)s Cartridge because %(2)s Application could not be created."

Cause: The specified 4.0 Oracle Application Server Application could not be created.

Action: The above application is created by registering the .app file residing in the \$ORAWEB_HOME/../../cartx/<cartridge type>/install directory. Please make sure that the following files exist for the respective cartridge type: PLSQL -> \$ORAWEB_HOME/../../cartx/plsql/install/PLSQLSampApp.app. JavaWeb -> \$ORAWEB_HOME/../../cartx/jweb/install/JavaSampApp.app. PERL -> \$ORAWEB_HOME/../../cartx/perl/install/sampapp.app. LiveHTML -> \$ORAWEB_HOME/../../cartx/livehtml/install/sampapp.app

07734 "Failed to upgrade %(1)s Cartridge because %(2)s/%(3)s Cartridge could not be created."

Cause: The specified 4.0 Oracle Application Server Cartridge could not be created.

Action: The above 4.0 cartridge is created by registering the .app file residing in the \$ORAWEB_HOME/../../cartx/<cartridge type>/install directory. Please make sure that the following files exist for the respective cartridge type: PLSQL -> \$ORAWEB_HOME/../../cartx/plsql/install/plsql.app JavaWeb -> \$ORAWEB_HOME/../../cartx/jweb/install/JavaSampCart.app PERL -> \$ORAWEB_HOME/../../cartx/perl/install/sampcart.app LiveHTML -> \$ORAWEB_HOME/../../cartx/livehtml/install/sampcart.app. Also make sure

that the corresponding Application .app file (refer to OWS-7733) has the Cartx-List parameter set to the above mentioned file.

07735 "Error: Copy from %(1)s to %(2)s failed."

Cause: For upgraded perl cartridges to run, persist.pl needs to be copied from 4.0 to 3.0. This copy operation failed.

Action: Try to copy over "persist.pl" manually from \$ORAWEB_HOME/../../cartx/perl/lib(4.0) to \$ORAWEB_HOME/perl/lib(3.0).

07736 "Unable to update Netscape Server start script `%(1)s'."

Cause: Migration utility is unable to update the Netscape server start script.

Action: Make sure the file and its directory indicated is writable by migration utility.

07737 ""

Cause: Information Message. This number is only used internally.

Action: None

07738 "Unable to create NT service for listener %s"

Cause: This could be because the service with the same name already exists

Action: Remove the existing service OR rename the listener.

07750 - 07899 : Messages for migration tool from oas4043 to oas4064

07750 “Migrate Primary Node”

Cause: Informative Msg

Action: None

07751 “ Primary Node Migration Completed”

Cause: Informative Msg

Action: None

07752 “ Must specify a valid ORACLE_HOME.”

Cause: Avalid ORACLE_HOME was not specified.

Action: Give a valid ORACLE_HOME

07753 “ Given ORACLE_HOME is not accessible.”

Cause: Either the given ORACLE_HOME does not exist OR it does not have the right permissions OR it is not a directory at all.

Action: Give the correct ORACLE_HOME.

07754 “Given ORACLE_HOME is invalid.”

Cause: The given ORACLE_HOME exists but does not have the directory structure expected as in an OAS installation.

Action: Give the correct ORACLE_HOME of a valid OAS installation from which to migrate.

07755 “ Migration Tool Internal Error. Check log file.”

Cause: There can be many reasons including insufficient memory.

Action: Check the Log file. The log file name is usually reported to the user.

07756 “ Cannot locate configuration files. Check ORACLE_HOME”

Cause: The configuration files are wrb.app, site.app, etc. and they are not found in the expected directories.

Action: Is your installation a OFA based instalation? If yes, the migration tool is supposed to ask for the ORACLE_BASE. If this does not happen, try the URL for Migrating from OFA installation directly.

07757 “ Must choose a site.”

Cause: User did not choose the sitename to migrate

Action: User should choose a sitename

07758 “ Missing wrb.app/site.app file.”

Cause: The wrb.app or the site.app file is not found.

Action: Check the permissions of the directory which contains wrb.app: OAS 3.0.x (nonOFA) \$ORACLE_HOME/ows/admin/\$ORAWEB_SITE/wrb/config
OAS 3.0.x (OFA) \$ORACLE_BASE/admin/ows/\$ORAWEB_SITE/wrb/config
OAS 4.0.4.3 (non OFA) \$ORACLE_HOME/ows/admin/\$ORAWEB_SITE/wrb
OAS 4.0.4.3 (OFA) \$ORACLE_BASE/admin/ows/\$ORAWEB_SITE/wrb

07759 “ WRB Migration sucessfully completed.”

Cause: Informative Msg

Action: None.

07760 ‘ All listeners in primary node sucessfully migrated”

Cause: Informative Msg

Action: None

07761 “ File owl.cfg not found in %s”

Cause: owl.cfg file is not found

Action: check if ORACLE_HOME is o.k oas is installed, listeners are configured on this node.

07762 “ There are no listeners to migrate in this node.”

Cause: No listeners are configured in this node.

Action: none

07763 “Failed to make directory %s”

Cause: File system error: permission/ownership/disk space/etc

Action: Check if the path is accessible: permission/ownership/etc is o.k enough disk space is there.

07764 “ Listener %s already configured on this node”

Cause: A listener with the same name already exists in the OAS 4.0.7.x installation.

Action: If you still want to migrate the listener, you have to uninstall the listener from the OAS 4.0.7.x installation and then do a repeat migration

07765 “ Error copying file %s during listener Migration”

Cause: This is probably a file system error like permissions/ownership/disk space/etc.

Action: Check the permissions/ownership/disk space.

07766 “ Listener %s sucessfully migrated.”

Cause: Informative msg.

Action: None.

07767 “ Fatal error happened during listener migration.”

Cause: The fatal error is probably because of a file system problem.

Action: Correct the file system problem and repeat the migration.

07768 “ Migrate RemoteListener nodes”

Cause: Informative msg.

Action: None

07769 “ Either the ORACLE_HOME or the ORACLE_BASE must be specified.”

Cause: The ORACLE_HOME should be entered for non-OFA installation. The ORACLE_BASE should be entered for OFA installation.

Action: Give correct ORACLE_HOME or ORACLE_BASE.

07770 “ The site name must be entered.”

Cause: The sitename was not entered.”

Action: Enter the sitename.

07771 “ There are no remote listener nodes which need to be migrated.”

Cause: Migrate remote nodes is onlu required for those remote nodes which have listeners configured in them. The tool has found out that there are no such remote nodes in this site. hence the message.

Action: None.

07772 “ Fatal error happened during applications migration. All WRB configuration changes rolled back.’

Cause: The fatal erroe is probably because of a file system.

Action: Correct the file system problem and repeat the migration.

07773 “ All applications and cartridges sucessfully migrated”

Cause: Informative msg.

Action: None

07774 “ All listeners in the remote nodde sucessfully migrated”

Cause: Informative msg.

Action: None.

07775 “ Remote node migration complete.”

Cause: Informative msg.

Action: None.

07776 “ Error during backing up the WRB configuration files. Cannot proceed.”

Cause: Error occured when backing up the wrb.app and the site.app files. File permissions may be wrong.

Action: Check if the files exist. Verify permissions.

07777 “ Error during rolling back the WRB configuration files.”

Cause: Error occured when rolling back the wrb.app and site.app files. File permission may be wrong.

Action: Check if the files exist. Verify permissions.

07778 “ Unable to copy file ‘%s’ to ‘%s’.”

Cause: Migration utility is unable to copy file.

Action: Make sure wlmig has permission to read and write and the source file exists.

07779 “ Given ORACLE_BASE is not accessible.”

Cause: Either the given ORACLE_BASE does not exist OR it does not have the right permissions OR it is not a directory at all.

Action: Give the correct ORACLE_BASE.

07780 “ Cannot locate configuration directory. Check ORACLE_BASE”

Cause: In a OFA installation, the configuration directory is \$ORACLE_BASE/admin/ows. This message is displayed because this directory is not accessible.

Action: Check the ORACLE_BASE you entered. Also check if the file system permissions are ok so that the migration tool wlmig can access it.

07781 “ Cannot locate configuration files. Check ORACLE_BASE.”

Cause: The configuration files wrb.app, site.app, etc. and they are not found in the expected directories.

Action: Is your installation a OFA based installation? If not, the migrationtool is supposed to have asked for the ORACLE_HOME only. If this did not happen, you probably did not enter the correct ORACLE_HOME in the earlier screen.

07782 “ Must specify a valid ORACLE_BASE”

Cause: A valid ORACLE_BASE was not specified.

Action: Give a valid ORACLE_BASE.

07783 “ Cannot change ownership of configuration files for listener %s”

Cause: owslctl does not have setuid. The oasroot.sh script was probably not executed after installation.

Action: Execute oasroot.sh script in \$ORACLE_HOME/orainst/oasroot.sh as root.

07784 “ Note: Refer to file %s for a detailed migration log.”

Cause: Informative msg.

Action: None.

07785 “ Error during backing up the owl.cfg file. Cannot proceed”

Cause: Error occurred when backing up owl.cfg file. File/Dir permissions may be wrong.

Action: Check if the file exists. Verify permissions.

07786 “ No cartridges to Migrate.”

Cause: Informational msg. No cartridges were found in the wrb.app file.

Action: None.

07787 “ Error creating cartridge %s in Application %s”

Cause: The specified 4.0 cartridge could not be created.

Action: The above 4.0 cartridge is created by registering the .app file residing in the \$ORAWEB_HOME/../../CARTX/<cartridge type>/install directory. Please make sure that the following files exist for the respective cartridge type:
PLSQL-> \$ORAWEB_HOME/install/UpgradedPLSQLCart.app JavaWeb ->
\$ORAWEB_HOME/install/UpgradedJWebCart.app PERL ->
\$ORAWEB_HOME/installUpgradedPerlCart.app LiveHTML ->

\$ORAWEB_HOME/install/UpgradedLiveHTMLCart.app Also make sure that the corresponding Application .app file (refer to OWS-7733) has the cartxList parameter set to the above mentioned file.

07788 “ Error creating Application %s”

Cause: The specified 4.0 OAS Application could not be created.

Action: The above application is created by registering the .app file residing in the \$ORAWEB_HOME/./cartx/<cartridge type>/install directory. Please make sure that the following files exist for the respective cartridge type: PLSQL -> \$ORAWEB_HOME/install/UpgradedPLSQLApp.app JavaWeb -> \$ORAWEB_HOME/install/UpgradedJWebApp.app PERL -> \$ORAWEB_HOME/install/UpgradedPerlApp.app LiveHTML -> \$ORAWEB_HOME/install/UpgradedLiveHTMLApp.app Also ensure that the respective runtime is registered.

07789 “ Error reading configuration file wrb.app when migrating cartridge %s”

Cause: This could be because of misformatted wrb.app file or an Internal reerror.

Action: Try migration again.

07790 “ Cartridge %s already exists”

Cause: This could also be because the cartridge is already migrated.

Action: Remove/rename the corresponding cartridge in OAS 4.0 and redo the migration.

07791 “ Error while trying to deregister application %s”

Cause: The application probably does not exist

Action: None

07792 “ VRML cartridges are not migrated because they are not supported in OAS 4.0 .”

Cause: Informative msg.

Action: None

07793 “ Error encountered during migration of cartridge %s “

Cause: Error during cartridge migration.

Action: Look log file for detailed message

07794 “ The admin listener is not migrated”

Cause: Informative msg.

Action: None

07795 “ The listener %s is an external listener. It is not migrated.”

Cause: Informative msg.

Action: None.

07796 “ The ORAWEB_HOME#) message could not be updated in the registry. Please do this manually.”

Cause: Informative msg. The cartridges could not have migrated properly.

Action: None

07797 “ Cannot migrate because the located wrb.app file does not belong to OAS 4.0.4.3”

Cause: Either you entered the ORACLE_HOME of a non-4.0.4.3 installation OR you entered the website you created in a 4.0.4.3 installation.

Action: Only 4.0.4.3 installation will be migrated. So give the correct ORACLE_HOME/website name.

07798 “ OK”

Cause: Informative msg: Used in html pages to populate the ‘OK’ button.

Action: None

07799 “ DAD %s already exists”

Cause: The named DAD already exists probably because it is already configured.

Action: If you want the new DADs, you should delete the existing unwanted DADs and then retry migration.

07801 “ Error: cannot create file %s when during migration.”

Cause: No write permission, no disk space, or directory not exist.

Action: Check disk space, directory and its permission.

07802 “ Warning: Cannot get configure information for cartridge %s”

Cause: wrcf API

Action: Check wrcf message in log file.

07803 “ Warning: Cannot get PLSQL agent information for cartridge %s”

Cause: wrcf API

Action: Check wrcf message in log file.

07804 “ Warning: Cannot register virtual path %s for cartridge %s”

Cause: wrcf API.

Action: Check wrcf message in log file.

07805 “ Successfully added virtual path entry for cartridge %s”

Cause: Informative message.

Action: None.

07806 “ Warning: Cannot get virtual path entry for cartridge: %s”

Cause: wrcf API

Action: Check Wrcf message in log file.

07807 “ Successfully added [Apps] entry for cartridge %s.”

Cause: wrcf API.

Action: Check wrcf message in log file.

07808 “ Successfully added [Apps] entry for cartridge %s”

Cause: Informative message.

Action: None.

07809 “ Warning: Cannot get [Apps] entry for cartridge: %s”

Cause: wrcf API

Action: Check wrcf message in log file.

07810 “ Error: Cannot initialize wrcf context for wrb file %s”

Cause: wrcf API.

Action: Check wrcf message in log file.

07811 “ Warning: Cannot get Display Name for JavaCorba application %s”

Cause: wrcf API.

Action: Check wrcf message in log file.

07812 “ Warning: Cannot get the app file for the JavaCorba application %s”**Cause:** wrcf API.**Action:** Check wrcf message in log file.**07813 “ Warning: Invalid JavaCorba runtime app file name %s”****Cause:** old wrb.app file.**Action:** Fix the JavaCorba runtime app file name in the old wrb.app.**07814 “ Warning: Cannot get parameter JCOAppsDir for JavaCorba runtime.”****Cause:** Old wrb.app file.**Action:** Fix the JavaVorba runtime section in the old wrb.app.**07815 “ Warning: Cannot open file %s to get app file for application %s”****Cause:** No disk space no permission.**Action:** Check if the above file got created.**07816 “ Warning: Cannot register application %s”****Cause:** wrcf API.**Action:** Check wrcf message in the log file.**07817 “ Warning: JavaCorba tool %s failed to generate app file for application %s”****Cause:** JavaCorba tool.**Action:** Reference JavaCorba documentation.**07818 “ Successfully registered application %s”****Cause:** Informative message.**Action:** None.**07819 “ Warning: cannot get cartridge list for application %s”****Cause:** wrcf API**Action:** Check wrcf message in log file.**07820 “ Warning: there is no cartridge for application %s”****Cause:** Informative message**Action:** None.

07821 “Warning: Cannot register cartridge %s for application %s”

Cause: wrcf API

Action: Check wrcf message in log file.

07822 “ Successfully registered cartridge %s for application %s.”

Cause: Informative message.

Action: None.

07823 “ Error: Cannot get runtime list from wrb file %s.”

Cause: wrong wrb.app file.

Action: fix the wrb.app file.

07824 “ Error: Cannot get application list from wrb file %s.”

Cause: wrong wrb.app file.

Action: fix the wrong wrb.app file.

07825 “ Application %s not migrated: already exists in OAS 4.0.7.\n”

Cause: Informative message.

Action: None.

07826 “ Failed to migrate application %s: \n\tcannot get application’s runtime.”

Cause: wrcf file

Action: Check wrcf message in log file.

07827 “ Failed to migrate application %s: \n\tInvalid runtime for the application.”

Cause: runtime not supported by migration tool.

Action: None.

07828 “ Failed to migrate application %s: \n\tApplication’s runtime does not exist in new install.”

Cause: runtime is not installed in OAS 4.0.7.

Action: Install the runtime in OAS 4.0.7.

07829 “ Application %s migration failed. \n”

Cause: Informative message.

Action: Check log file for reason.

07830 “ Application %s migrated sucessfully. \n”

Cause: Informative message.

Action: None.

07831 “ Warning: Cannot get configure information for application %s.”

Cause: wrcf API

Action: Check wrcf message in log file.

07832 “ Note: Migration of JavaCorba application may take a while. Please wait...\n”

Cause: Informative message.

Action: None.

07833 “ Failed to open registry key %s.”

Cause: NT registry hive SOFTWARE\ORACLE at HKEY_LOCAL_MACHINE has problem.

Action: Check registry at SOFTWARE\ORACLE, fix any issues.

07834 “Failed to read %s from registry.”

Cause: NT registry hive SOFTWARE\ORACLE at HKEY_LOCAL_MACHINE has problem.

Action: Check registry at SOFTWARE\ORACLE, fix any issues.

07835 “ Failed to set value for %s into registry.”

Cause: NT registry hive SOFTWARE\ORACLE at HKEY_LOCAL_MACHINE has problem.

Action: Check registry at SOFTWARE\ORACLE, fix the HOME?\OAS40 sub-key.

07836 “ Failed to set ORACLE_HOME404 and ORAWEB_HOME404 in the registry or set them as environment variables.

Cause: May be the hive is locked by other process, or it is damaged.

Action: Manually set ORACLE_HOME404 and ORAWEB_HOME404 in the registry or set them as environment variables.

07899 “ Cannot migrate because the located wrb.app file does not belong to OAS 4.0.6.4 or OAS 4.0.7 “

Cause: Either you entered the ORACLE_HOME of a non-4.0.6.4, non-4.0.7 installation OR you entered the website name you created in a non-4.0.6.4, non-4.0.7 installation.

Action: Only 4.0.6.4 or 4.0.7 installations will be migrated. So give the correct ORACLE/website name.

08200 - 08299 : Oracle Application Server Logger Admin messages

08200 "Invalid or no wrb.app file"

Cause: Invalid or no **wrb.app** file.

Action: Reload the WRB Configuration form.

08201 "The input parameter %(1)s must not be empty"

Cause: Required field not filled in submitted form.

Action: Fill in all required fields.

08202 "Unsuccessful in writing the wrb.app file."

Cause: Does not have permission to write the **wrb.app** file in \$ORAWEB_HOME/admin directory.

Action: Make sure permissions are granted to create wrb.app file.

08203 "Logger Default settings successfully written."

Cause: Information Message.

Action: None.

08204 "[Logger] sections does not exist in wrb.app."

Cause: The **wrb.app** is corrupted.

Action: Need to copy just the [Logger] section from **servapp.dfl** to **wrb.app**.

08205 "Logger plsql package installation failed because neither Server Manager, nor SQLDBA could be run."

Cause: Logger plsql package cannot be installed. This must be done from Server Manager (line mode) or SQLDBA.

Action: Install either Server Manager or SQLDBA in the ORACLE_HOME where the Logger administration is installed.

08206 "%(1)s section does not exist in wrb.app."

Cause: The **wrb.app** is corrupted.

Action: Recreate the Dad again or PLSQL agent again.

08207 "%(1)s is empty in the %(2)s dad section."

Cause: Username, password, or oracle home field is missing in the dad section.

Action: Go to the dad administration page and modify the dad to write the username and password in the dad section.

08208 "Database Error."

Cause: External (Database) error.

Action: See the associated error and take the appropriate action.

08209 "%(1)s is not specified."

Cause: The dad or plsql agent is not installed.

Action: Install the dad or the plsql agent.

08210 "Logger tables successfully upgraded."

Cause: Information Message.

Action: None.

08300 - 08399 : Oracle Application Server Auth Services Admin messages

08301 "Basic Authentication Section Successfully written"

Cause: Information Message.

Action: None.

08302 "Digest Authentication Section Successfully written"

Cause: Information Message.

Action: None.

08303 "IP-based Authentication Section Successfully written"

Cause: Information Message.

Action: None.

08304 "Domain-based Authentication Section Successfully written"

Cause: Information Message.

Action: None.

08305 "Database Authentication Section Successfully written"

Cause: Information Message.

Action: None.

08306 "Authentication Service Configuration Info Successfully written"

Cause: Information Message.

Action: None.

08307 "Crypt Authentication Section Successfully updated."

Cause: Information Message

Action: None

08308 "Group File : %(1)s does not exist."

Cause: The specified file does not exist.

Action: Specify a valid group file containing user/passwords that exists.

08400 - 08500 : Oracle Application Server Config Provider Error Messages

08400 "No Response from Config Provider Server"

Cause: Config Provider Server (wrbcfg) may not be running, or could not be running on the expected port & IP address.

Action: Make sure "wrbcfg" and all other mn processes **mnaddrsrv**, **mnrpcnm-srv**, **mnorbsrv** are listening on the expected port and IP address.

08401 "Error reading OWS WRB Config File - Pathname: %(1)s, Filename: %(2)s"

Cause: Config file **wrb.app** is corrupted, or may not exist or setting for the ORAWEB_HOME env variable is incorrect.

Action: Ensure ORAWEB_HOME is set correctly, and make sure \$ORAWEB_HOME/admin/wrb.app is not corrupted.

08402 "Config Provider: Unable to load shared library %(1)s"

Cause: The shared library may not exists or does not have permission.

Action: Ensure this shared library exists and also has read permission.

08403 "Config Provider: No valid parser specified in wrcpinit()"

Cause: For the specified protocols, the shared objects could not be loaded and also unable to load the default INMEMORY parser.

Action: Make sure the protocols in wrcpinit() are specified correctly, and \$ORAWEB_HOME/lib has the shared libraries for the parsers i.e libwrcp.so

08600 - 08799 : Oracle Application Server Log Module Messages

08601 "Log Module has been initialized"

Cause: Information message.

Action: None.

08602 "Log Module has been terminated"

Cause: Information message.

Action: None.

08603 "Log Module can not open CLF/XLF database connection"

Cause: The log server or database is not up.

Action: Check log server and database. Make sure they have been started successfully.

08604 "Log Module can not write CLF/XLF data to the log server or database"

Cause: The log server or database is not up. Also, the CLF/XLF database table might be full.

Action: Check log server and database. Make sure they have been started successfully. Also, try to free up some tablespace in the database.

08605 "Log Module has logged a xlf entry successfully if XLF logging is ON"

Cause: Information message.

Action: None.

08606 "Missing %(1)s in DAD %(2)s section"

Cause: Missing information that are going to be used to log on to the database.

Action: Please add the missing field to the DAD section.

08607 "Log Server can not initialize client Configuration Provider"

Cause: The configuration provider may not be up or the **wrb.app** configuration file may not exist.

Action: Check to make sure configuration provider is up. Also please make sure **wrb.app** exists.

08608 "Log Server or client can not read %(1)s section"

Cause: The logger default section does not exist.

Action: Check to make sure the logger default section exists.

08609 "Missing %(1)s in %(2)s section"

Cause: Missing logger defaults information in the logger default section.

Action: Please add the missing field to the logger default section.

08610 "Incorrect log handle"

Cause: The log handle passed to the logger is not valid.

Action: Check to make sure the logger handle is the one returned by the open call.

08611 "Can not open log file %(1)s for writing"

Cause: The log file cannot be opened for logging.

Action: Check on the permission to open the log file and permission to read the directory where the log file resides.

08612 "Can not write to the log file %(1)s"

Cause: Log messages cannot be written to the log file.

Action: Check on the write permission to the log file and directory. Also make sure the disk is not full.

08613 "Can not open or write %(1)s for archiving"

Cause: The file cannot be opened or written for archiving.

Action: Check to make sure the logger has permission to open and write the file or directory. Also check to make sure disk is not full.

08614 "Can not log onto the database. Username, password, or sid or connect string is not defined or dad is not defined."

Cause: The username, password, or sid or connect string is not defined in the logger dad section, or the dad is not defined in the logger section.

Action: Please check to make sure these values exist or the dad is defined.

08615 "Can not initialize mutex"

Cause: Mutex cannot be initialized for critical sections.

Action: This is an internal error.

08616 "Can not load %(1)s"

Cause: The shared object cannot be loaded.

Action: Please check on the LD_LIBRARY_PATH to include \$ORAWEB_HOME/lib.

08617 "Can not read log file %(1)s. Make sure the log file exists and is the correct type (XLF, SYSMMSG, or ATTRIB)."

Cause: The log file may not exist or may be of the incorrect format.

Action: Please make sure the file exists and select the correct type.

08618 "Incorrect log type"

Cause: The log type is not XLF, SYSMMSG, or ATTRIB.

Action: Please make sure the type is correct.

08619 "Missing Map file"

Cause: The map file entry is NULL."

Action: Please enter the location of the map file."

08620 "Success: File upload is complete! Line(s) %(1)s are ignored."

Cause: The lines with these numbers are ignored during the upload, because some fields are missing.

Action: None.

08621 "Can not close log file"

Cause: Log file cannot be closed.

Action: Check on the write permission to the log file and directory.

08622 "Number of System Messages Logged to File"

Cause: Information message.

Action: None.

08623 "Number of System Messages Logged to Database"

Cause: Information message.

Action: None.

08624 "Last Fatal System Message"

Cause: Information message.

Action: None.

08625 "Never"

Cause: Information message.

Action: None.

08626 "Daily"

Cause: Information message.

Action: None.

08627 "Weekly"

Cause: Information message.

Action: None.

08628 "Monthly"

Cause: Information message.

Action: None.

08629 "NONE"

Cause: Information message.

Action: None.

08630 "File upload is complete!"

Cause: Information message.

Action: None.

08631 "One or more fields are missing. Please specify dad, type, and file."

Cause: The dad, type, or file field is missing.

Action: Supply the missing field and try again.

08800 - 08899 : Oracle Application Server Controller OWSCtl Messages

08801 "No process running for %s '%s'"

Cause: OWSCtl is unable to stop the named Web listener indicated because it is not running.

Action: Use 'owsctl status <server name>' to check if the process is up and running.

08802 "Oracle Web Listener '%s' does not exist"

Cause: OWSCtl is unable to find the named Oracle Web Listener indicated because it is not defined or registered.

Action: Check if the Oracle Web Listener is created.

08803 "Unable to change directory into '%s'"

Cause: OWSCtl is unable to change its current directory.

Action: Check if the directory exists and readable.

08804 "Unable to extract information for Oracle Web Listener '%s'."

Cause: OWSCtl is unable to extract information such as hostname, port number from the Oracle Web Listener sv(server).cfg file.

Action: Check if the Oracle Web Listener configuration file is corrupted.

08805 "Unable to determine PID file for Oracle Web Listener '%s' from '%s'."

Cause: OWSCtl is unable to determine the PID file from the Oracle Web Listener sv(server).cfg file.

Action: Check if the Oracle Web Listener configuration file is corrupted.

08806 "%s '%s' is already UP and running at pid %d."

Cause: Web Listener is up and running at pid indicated above.

Action: None.

08807 "%s '%s' is DOWN."

Cause: Web Listener is down and not running.

Action: None.

08808 "Unable to determine %s version by doing '%s'."

Cause: OWSCtl is unable to determine the Web Listener version.

Action: Try the command indicated to see if it prints version.

08809 "%s '%s' is being terminated."

Cause: Web Listener is being shutdown.

Action: None.

08810 "Unable to fork %s '%s'."

Cause: Unable to fork Web Listener.

Action: Make sure your machine is not overloaded with processes.

08811 "Unable to startup %s '%s'."

Cause: Unable to startup Web Listener.

Action: Make sure the Web Listener is installed correctly and Oracle Web WRB processes are running.

08812 "Out of memory trying to allocate %d bytes"

Cause: The system is running low in memory space and swap space.

Action: Check the system, terminate some non-active processes.

08813 "File '%s' does not exist"

Cause: Information Message.

Action: None.

08814 "Unable to write to file '%s%s'"

Cause: File is unwritable.

Action: Check the write permission of the file.

08815 "Unable to read from file '%s%s'"

Cause: File is unreadable.

Action: Check if the file exist and readable.

08816 "Unable to obtain application information for '%s'"

Cause: The application is not defined in \$ORAWEB_HOME/admin/wrb.app.

Action: None.

08817 "Unable to obtain application version for '%s'"

Cause: The application version is not defined.

Action: None.

08818 "Unable to load shared library: `%s'"

Cause: Information Message.

Action: None.

08819 "Unable to obtain hostname of the current machine"

Cause: No hostname is obtainable from the system.

Action: Check if the system network hostname is configurable properly.

08820 "Unable to start %s process `%s'"

Cause: Unable to start WRB or cartridge processes.

Action: Refer the error message echoed from the WRB process.

08821 "%s process `%s' is started up at pid %d"

Cause: Information Message.

Action: None.

08822 "Unable to fork new process for %s process `%s'"

Cause: Unable to fork process for WRB or cartridge processes.

Action: Check the system, terminate some non-active processes.

08823 "%s process `%s' is terminated"

Cause: Information Message.

Action: None.

08824 "All %s processes are terminated"

Cause: Information Message.

Action: None.

08825 "%s process `%s' is UP at pid %d"

Cause: Information Message.

Action: None.

08826 "%s process `%s' is DOWN"

Cause: Information Message.

Action: None.

08827 "Unable to find %s processes on `%s'"

Cause: Unable to find WRB or cartridge processes.

Action: Check if the WRB or Cartridge processes are running and check if \$ORAWEB_ADMIN/admin/ows/\$ORAWEB_SITE/wrb/config/.ows_<machine>.pid is readable.

08828 "%s processes are already running on current machine"

Cause: Unable to start WRB or Cartridge processes on the same machine.

Action: Make sure that only one of WRB or Cartridge are runnable on the same ORAWEB_HOME on the same machine.

08829 "Unable to startup up PULSE process. %s startup aborted."

Cause: Web Listener is not startup correctly and PULSE process cannot connect to it.

Action: Make sure the Web Listener is startup correctly.

08830 "Unable to fork new process for PULSE process `%s %s %s'"

Cause: Unable to fork new processes.

Action: Make sure your machine is not overloaded with processes.

08831 "Unable to start PULSE process `%s %s %s'"

Cause: Web Listener is not startup correctly and PULSE process cannot connect to it.

Action: Make sure the Web Listener is startup correctly.

08832 "Reload option is non-applicable for %s"

Cause: Information Message.

Action: None.

08833 "Unknown WRB or Cartridge process `%s'"

Cause: Unknown WRB or Cartridge is provided along with -p option to owscctl.

Action: Check for the process name. The valid process for WRB are: **mnad-drsrv**, **mnrpcnmsrv**, **mnorbsrv**, **wrbcfg**, **wrbasrv**, **wrbahsrv**, **wrblog** and **wrbroker**. The valid process for Cartridge are: **wrbksf**.

08834 "%s process `%s' is DOWN at pid %d"

Cause: Information Message.

Action: None.

08835 "%s process '%s' at pid %d is NOT running"

Cause: Information message.

Action: None.

08836 "%s process '%s' has NEVER been started"

Cause: Information message.

Action: None.

08837 "Oracle Web Status Monitor '%s' has ALREADY been running at pid %d"

Cause: Information message.

Action: None.

08838 "Oracle Web Status Monitor '%s' is not running"

Cause: Information message.

Action: none.

08839 "Oracle Web Status Monitor '%s' is UP at pid %d"

Cause: Information message.

Action: None.

08840 "Oracle Web Status Monitor '%s' is DOWN"

Cause: Information message.

Action: None.

08841 "Oracle Web Status Monitor '%s' at pid %d is being terminated"

Cause: Information message.

Action: None.

08842 "Unable to fork Oracle Web Status Monitor '%s'"

Cause: System is running low in memory and swap space.

Action: Check the system and terminate some non-active process to free some space.

08843 "Set environment variable OWSCTL_SLEEP to higher than %d , and restart WRB processes"

Cause: OWSCTL_SLEEP value is less as per the current load.

Action: None.

08844 "`%s' file is not an executable"

Cause: If the named file was not an executable.

Action: None.

08845 "Current process has insufficient privilege to start `%s'"

Cause: Insufficient privilege.

Action: None.

08846 "The `%s' file does not exist"

Cause: File does not exist.

Action: None.

08847 "The `%s' command is exited abnormally"

Cause: Exited abnormally.

Action: None.

08848 "The `%s' command is successfully executed"

Cause: Exited normally.

Action: None.

08849 "Waited %d secs. Didn't receive initialization complete message."

Cause: The process probably couldn't start up successfully.

Action: None.

08850 "%s `%s` started successfully."

Cause: Started Successfully.

Action: None

08851 " Please check NT Event Log for details."

Cause: Listener service failed on NT.

Action: Please check the Event Log of the Listener machine for details. To see Event Log: Start+Programs+Administrative Tools+Event Viewer.

09000 - 09099 : Oracle Application Server STATUS (owsstat) Messages

09001 "Hostname must be provided with -h option"

Cause: Hostname argument is missing for owsstat.

Action: Use -h to provide hostname.

09002 "Unable to get host information for host '%s'"

Cause: Unable to get host information.

Action: Check if the hostname is correct.

09003 "Unable to get proxy host information '%s'"

Cause: Unable to get proxy host information.

Action: Check if the hostname set in environment variable http_proxy is correct.

09004 "Unable to find trigger script '%s'"

Cause: Trigger script specified does not exist.

Action: None.

09005 "Unable to execute trigger '%s' against url %s"

Cause: Trigger script does not exist or not executable.

Action: Check if the trigger script exist and executable.

09006 "Unable to get redirection host information '%s'"

Cause: Unable to get redirection host information.

Action: Check if the redirection host exists and is running.

09007 "Select call is interrupted"

Cause: owsstat is interrupted.

Action: None.

09008 "Argument followed by option '%s' must be a positive number"

Cause: Information Message.

Action: None.

09100 - 09189 : Oracle Web Configuration writer

09100 "Complete successfully"

Cause: Information Message.

Action: None.

09101 "WRB file '%s' not found"

Cause: Information Message.

Action: Check if the file indicated exist and readable.

09102 "Cartridge section '%s' already exist"

Cause: Information Message.

Action: Remove the existing cartage section before adding it in.

09103 "Cartridge section '%s' does not exist"

Cause: Information Message.

Action: None.

09104 "Cartridge section name is empty"

Cause: Information Message.

Action: Cartridge section name must NOT be empty.

09105 "Unable to get environment variable ORAWEB_HOME"

Cause: Information Message.

Action: ORAWEB_HOME environment variable must be set always.

09106 "Unable to read WRB file '%s'"

Cause: Information Message.

Action: Check if the WRB file indicated is readable.

09107 "Unable to write WRB file '%s'"

Cause: Information Message.

Action: Check if the WRB file indicated is writable.

09108 "Empty name is found in name/value pair"

Cause: Information Message.

Action: Use non-empty name for name/value pair in cartridge section.

09109 "Cartridge section is empty"

Cause: Information Message.

Action: None.

09110 "Empty name/value pair is found"

Cause: Information Message.

Action: None.

09111 "Cartridge section name '%s' is reserved and is not writable"

Cause: Information Message.

Action: Please specify the section name other than the reserved one.

09112 "Cartridge section name '%s' is reserved and is not readable"

Cause: Information Message.

Action: Please specify the section name other than the reserved one.

09113 "Malformed cartridge section name '%s'"

Cause: Information Message.

Action: Cartridge section name must be in form of [section_name].

09114 "Null cartridge structure pointer passed"

Cause: Information Message.

Action: None.

09115 "Empty cartridge name is not allowed"

Cause: Information Message.

Action: None.

09116 "Empty cartridge object path is not allowed"

Cause: Information Message.

Action: None.

09117 "Empty cartridge entry point is not allowed"

Cause: Information Message.

Action: None.

09118 "Cartridge '%s' already exist"

Cause: Information Message.

Action: None.

09119 "Cartridge name '%s' is reserved for Oracle Application Server"

Cause: Information Message.

Action: Please use cartridge name other than the reserved one.

09120 "Cartridge service for cartridge '%s' already exist"

Cause: Information Message.

Action: Please make sure the cartridge to be added does not exist.

09121 "Cartridge protocol for cartridge '%s' already exist"

Cause: Information Message.

Action: Please make sure the cartridge to be added does not exist.

09122 "Empty list of hosts is provided while num_hosts is greater than zero"

Cause: Information Message.

Action: None.

09123 "Unknown cartridge protocol '%s'"

Cause: Information Message.

Action: Please see the **mycart.sample** for valid protocol.

09124 "Empty list of application dirmap is provided while num_app_maplings is greater than zero"

Cause: Information Message.

Action: None.

09125 "Empty cartridge virtual path is not allowed"

Cause: Information Message.

Action: None.

09126 "Empty cartridge physical path is not allowed"

Cause: Information Message.

Action: Please provide the cartridge physical path.

09127 "Cartridge virtual path '%s' already exist"

Cause: Information Message.

Action: Please make sure the cartridge to be added does not exist.

09128 "Cartridge virtual path variable '%s' already exist"

Cause: Information Message.

Action: Please make sure the cartridge to be added does not exist.

09129 "Empty cartridge virtual path variable name found in name/value pair"

Cause: Information Message.

Action: None.

09130 "Invalid cartridge virtual path protection string '%s'"

Cause: Information Message.

Action: Please see the **mycart.sample** for correct protection string syntax.

09131 "Unknown cartridge service '%s'"

Cause: Information Message.

Action: Please see the **mycart.sample** for valid services.

09132 "Cartridge virtual path protection '%s' already exist"

Cause: Information Message.

Action: Please make sure the cartridge to be added does not exist.

09133 "Invalid logger sys value '%s'"

Cause: Information Message.

Action: Please check **mycart.sample** for valid logger sys value.

09134 "Invalid logger attribute value '%s'"

Cause: Information Message.

Action: Please check **mycart.sample** for valid logger attribute value.

09135 "Invalid logger level value '%d'"

Cause: Information Message.

Action: Please check **mycart.sample** for valid logger level value.

09136 "Invalid logger destination type '%s'"

Cause: Information Message.

Action: Please check **mycart.sample** for valid logger destination type.

09137 "Unable to read cartridge information file '%s'"

Cause: Information Message.

Action: Please check if the cartridge info. file exists and readable.

09138 "Parse error in cartridge information file '%s'"

Cause: Information Message.

Action: Please check if the cartridge info. file is in correct syntax.

09139 "Cartridge system section '%s' already exist"

Cause: Information Message.

Action: Please check if the cartridge to be added does not exist.

09140 "Cartridge user defined section '%s' already exist"

Cause: Information Message.

Action: Please check if the cartridge to be added does not exist.

09141 "Invalid Transaction name"

Cause: Information Message.

Action: Please check **mycart.sample** for valid transaction name.

09142 "Invalid Begin Transaction URL"

Cause: Information Message.

Action: Please check **mycart.sample** for valid begin transaction url.

09143 "Invalid Commit Transaction URL"

Cause: Information Message.

Action: Please check **mycart.sample** for valid commit transaction url.

09144 "Invalid Rollback Transaction URL"

Cause: Information Message.

Action: Please check **mycart.sample** for valid rollback transaction url.

09145 "Invalid Transaction timeout '%d'"

Cause: Information Message.

Action: Please check **mycart.sample** for valid transaction timeout value.

09146 "No BelongTo Transaction URL found"

Cause: Information Message.

Action: BelongTo Transaction url must be present for transaction info.

09147 "Invalid BelongTo Transaction URL"

Cause: Information Message.

Action: Please check **mycart.sample** for valid belongto transaction value.

09148 "Invalid directory mapping type"

Cause: Information Message.

Action: Please check **mycart.sample** for valid directory mapping type.

09149 "Empty web listener name. Need web listener name to register listener dirmap info."

Cause: Web listener dirmap info. found in cartridge info. file.

Action: Please use -s to provide listener name to **wrcfreg** or fill up the web listener name field if you are in new cartridge add form.

09150 "Web listener configuration file '%s' not found"

Cause: Information Message.

Action: Check if the file indicated exists.

09151 "Web listener configuration file '%s' read error"

Cause: Information Message.

Action: Check if the web conf. file is readable.

09152 "Empty dirmap virtual path"

Cause: Information Message.

Action: Please provide the non-empty directory mapping virtual path.

09153 "Empty dirmap physical path"

Cause: Information Message.

Action: Please provide the non-empty directory mapping physical path.

09154 "Dirmap virtual path '%s' already exist"

Cause: Information Message.

Action: Make sure the directory mapping virtual does not exist or use -i to ignore.

09155 "Dirmap virtual path '%s' protection already exist"

Cause: Information Message.

Action: Make sure the dirmap protection does not exist or use -i to ignore.

09156 "Invalid dirmap virtual path protection string '%s'"

Cause: Information Message.

Action: Please refer to **mycart.sample** for correct protection string syntax.

09157 "Unable to write Web listener configuration file '%s'"

Cause: Information Message.

Action: Make sure the web conf. file is writable.

09158 "wrcf context is not initialized correctly"

Cause: Information Message.

Action: Please contact World Wide Support.

09159 "Invalid directory mapping protection type '%s'"

Cause: Information Message.

Action: Please refer to **mycart.sample** for valid directory mapping protection type.

09160 "Unable to get environment variable ORAWEB_SITE"

Cause: Information Message.

Action: ORAWEB_SITE environment should always be set.

09161 "Unable to access external software '%s' server '%s'"

Cause: Information Message.

Action: Check if the external web listener software is installed correctly and accessible.

09162 "Parameter Name '%s' not found in section '%s'"

Cause: Information Message.

Action: None.

09163 "Unable to initialize WRCF context.\nInvalid file name: `%s'"

Cause: Information Message.

Action: None.

09164 "Runtime : `%s' is not yet registered with Web Request Broker"

Cause: Information Message.

Action: None.

09165 "Application : `%s' is not yet registered with Web Request Broker"

Cause: Information Message.

Action: None.

09166 "Runtime information is not available for the Application : `%s'"

Cause: Information Message.

Action: None.

09167 "Application information is not available for the Cartridge : `%s'"

Cause: Information Message.

Action: None.

09168 "Application : `%s' is already registered."

Cause: Information Message.

Action: None.

09169 "Cartridge : `%s' is already registered."

Cause: Information Message.

Action: None.

09170 "Error: Runtime [%s] differs from Runtime[%s] specified in %s"

Cause: Runtime specified on command line using `-g` option is not same as runtime specified using 'ServerRuntime' parameter in application configuration file.

Action: Please make sure that you have the correct runtime specified in application configuration file and avoid using `-g` option.

09190 - 09199 : wrcreg syntax messages

09190 "Syntax: Unknown section at line %d"

Cause: Information Message.

Action: Check syntax.

09191 "Syntax: Section not ended at line %d"

Cause: Information Message.

Action: Check syntax.

09192 "Syntax: Section not ended at line %d"

Cause: Information Message.

Action: Check syntax.

09193 "Syntax: Malformed section at line %d"

Cause: Information Message.

Action: Check syntax.

09194 "Syntax: Malformed 'name = value' at line %d"

Cause: Information Message.

Action: Check syntax.

09195 "Syntax: Invalid cartridge parameter '%s' at line %d"

Cause: Information Message.

Action: Check syntax.

09196 "Syntax: Invalid dirmap parameter '%s' at line %d"

Cause: Information Message.

Action: Check syntax.

10000 - 10099 : Web Request Broker Execution Engine (wrbc) defined in wrer.h

10000 "Low Memory. Unable to allocate %d bytes"

Cause: Out of swap space?

Action: Create additional Virtual Memory.

10001 "Error in WRB Configuration Provider"

Cause: Configuration provider may be down.

Action: Restart the Web Request Broker.

10002 "Error in loading the cartridge shared object %s"

Cause: Cartridge not available at the specified location or unresolved symbols found in the cartridge shared object.

Action: Check the location of the cartridge shared object and fix unresolved symbols.

10003 "Incorrect entry function specified '%s'"

Cause: The Entry function which defines the cartridges callback functions was incorrectly specified.

Action: Correct the entry function name the WRB Administration and restart the WRB.

10005 "Init callback or Entry Function does not return WRB_DONE"

Cause: Init callback or Entry func returned WRB_ABORT which stopped the cartridge from initializing.

Action: Check the Init callback and Entry function to determine why WRB_ABORT was returned.

10006 "Shutdown callback returned WRB_ERROR"

Cause: Cartridge returned WRB_ERROR or WRB_ABORT on shutdown.

Action: Investigate the reasons for the ungraceful cartridge shutdown.

10007 "Error in creating new request for URI %s"

Cause: Internal error.

10008 "Request %s returned WRB_ABORT"

Cause: WRB_ABORT was returned by the cartridge when executing the request.

Action: Investigate the reason for the cartridge returning WRB_ABORT.

10100 - 10199 : Web Request Broker Services

10103 "Unable to invoke the WRB API call. Enterprise option required."

Cause: The particular API can be invoked only with the Enterprise option for the Web Request Broker.

Action: Update to the Enterprise option for the WRB by contacting owshelp@us.oracle.com.

10104 "Service %s successfully loaded"

Cause: Informational message.

Action: Informational message.

10105 "Service %s successfully unloaded"

Cause: Informational message.

Action: Informational message.

10200 - 10299 : WRB TX Services

10200 "DAD %s has insufficient information"

Cause: The specified DAD did not have a username and password specified in the configuration file.

Action: DADs used by TX_REG calls, the username and password fields in the dads are mandatory.

10201 "TX_OPEN fails xa_open -> %d"

Cause: Error in connecting to the Resource Manager (database).

Action: Check if the DAD is valid. Connect using alternate clients (svrmgrl) using the same information provided in the DAD.

10204 "End transaction fails XID: %s, RM %s, xa_end -> %d"

Action: Look into xa trace files in the log directory for more info.

10205 "Error in closing resource manager %s xa_close ->%d"

Action: Look into xa trace files in the log directory for more info.

10206 "Error in rolling back txn %s"

Action: Look into xa trace files in the log directory for more info.

10207 "Error in starting RM %s xa_start -> %d"

Cause: Potential reasons can be error in configuring the Oracle database, or the transaction timing out.

Action: Look into xa trace files in the log directory for more info.

10208 "RM %s in the transactional context not opened"

Action: Look into xa trace files in the log directory for more info.

10209 "Error in resuming transaction XID: %s RM %s xa_start -> %d"

Cause: Potential reasons can be error in configuring the Oracle database, or the transaction timing out.

Action: Look into xa trace files in the log directory for more info.

10210 "Error in suspending transaction XID: %s RM %s xa_end -> %d"

Cause: Potential reasons can be error in configuring the Oracle database, or the transaction timing out.

Action: Look into xa trace files in the log directory for more info.

10211 "Error in committing transaction XID: %s RM %s xa_commit -> %d"

Action: Look into xa trace files in the log directory for more info.

10212 "Error in preparing transaction XID: %s RM %s xa_prepare -> %d"

Action: Look into xa trace files in the log directory for more info.

10213 "Configuration based tx error Name: %s BeginURI: %s CommitURI: %s RollbackURI %s"

Cause: Configuration based transactions not fully specified.

Action: Use Oracle Application Server manager to specify the configuration based transactions fully.

10251 "OTS initialization failed with exception %s"

Cause: Ots initialization can fail for multiple reasons including the transactional DADs associated with the application, the cartridge is invoked in a non Enterprise Edition of Oracle Application Server etc.

Action: Check the transactional DADs associated with the application and confirm that the DADs point to valid database instances. Also confirm that the cartridge is invoked in an Enterprise Edition of the App Server.

10252 "OTS termination failed with exception %s"

Cause: OTS termination can fail if pending transactions exist or transactions commits resulted in a hazardous situation.

Action: Contact support.

10254 "Transaction suspend failed with exception %s"

Cause: Transactions are suspended for supporting conversational transactions by the Application server runtime or by the developer using tx_suspend.

Action: Transaction errors are logged to the \$ORACLE_HOME/ots/<Version>/admin directory. The files are named as xa_<DAD><mmddyy>.trc where DAD is the database that resulted in the transaction error and ts<mmddyy>.trc files. Please contact support with the information in the trc files.

10255 "Transaction resume failed with exception %s"

Cause: Suspended transactions are resumed by the Application server runtime for conversational transactions or by the developer using tx_resume.

Action: Transaction errors are logged to the \$ORACLE_HOME/ots/<Version>/admin directory. The files are named as xa_<DAD><mmddyy>.trc

where DAD is the database that resulted in the transaction error and ts<mmddyy>.trc files. Please contact support with the information in the trc files.

10256 "Transaction internalization failed with exception %s"

Cause: Transactions can migrate from one process to another thru externalization/internalization.

Action: Transaction errors are logged to the \$ORACLE_HOME/ots/<Version>/admin directory. The files are named as xa_<DAD><mmddyy>.trc where DAD is the database that resulted in the transaction error and ts<mmddyy>.trc files. Please contact support with the information in the trc files.

10257 "Transactions externalization failed with exception %s"

Cause: Transactions can migrate from one process to another thru externalization/internalization.

Action: Transaction errors are logged to the \$ORACLE_HOME/ots/<Version>/admin directory. The files are named as xa_<DAD><mmddyy>.trc where DAD is the database that resulted in the transaction error and ts<mmddyy>.trc files. Please contact support with the information in the trc files.

10258 "Transaction begin failed with exception %s"

Cause: A Transaction begin can fail for the following reasons. One of the databases that is configured as a part of the transactional applications is not available. "otsfacsrv" process is not up and running.

Action: Check all the databases are up and running. Check that the otsfacsrv process is up and running. Transaction errors are logged to the \$ORACLE_HOME/ots/<Version>/admin directory. The files are named as xa_<DAD><mmddyy>.trc where DAD is the database that resulted in the transaction error and ts<mmddyy>.trc files. Please contact support with the information in the trc files.

10260 "Transaction commit failed with exception %s"

Cause: A Transaction commit can fail for the following reasons. A database that we are committing to is down. "otsfacsrv" process is down. The transaction commit is in doubt.

Action: Check all the database instances are up and running. Check that otsfacsrv process is up and running. Transaction errors are logged to the \$ORACLE_HOME/ots/<Version>/admin directory. The files are named as xa_<DAD><mmddyy>.trc where DAD is the database that resulted in the transaction error and ts<mmddyy>.trc files. Please contact support with the information in the trc files.

10261 "Transaction rollback failed with exception %s"

Cause: A Transaction rollback can fail for the following reasons. A database that we are rollingback to is down. "otsfacsrv" process is down.

Action: Check all the database instances are up and running. Check that otsfac-srv process is up and running. Transaction errors are logged to the \$ORACLE_HOME/ots/<Version>/admin directory. The files are named as xa_<DAD><mmddyy>.trc where DAD is the database that resulted in the transaction error and ts<mmddyy>.trc files. Please contact support with the information in the trc files.

10264 "Connection to DAD %s failed with exception %s"

Cause: Trying to establish a connection with a DAD can fail for the following reasons. The database instance referred to by the dad is down. The resources required to establish the connections has been exhausted.

Action: Check if the database instance in question is up and running. Check if enough virtual memory exists on the node. Transaction errors are logged to the \$ORACLE_HOME/ots/<Version>/admin directory. The files are named as xa_<DAD><mmddyy>.trc where DAD is the database that resulted in the transaction error and ts<mmddyy>.trc files. Please contact support with the information in the trc files.

10265 "Failed to destroy the connection to dad %s. Exception %s"

Cause: Destroying a connection to a DAD can fail for the following reasons. An indoubt transaction can be present, The database instance can be down.

Action: Check if the database instance in question is up and running. Transaction errors are logged to the \$ORACLE_HOME/ots/<Version>/admin directory. The files are named as xa_<DAD><mmddyy>.trc where DAD is the database that resulted in the transaction error and ts<mmddyy>.trc files. Please contact support with the information in the trc files.

10266 "Begin of a Stateful transaction failed"

Cause: Beginning stateful transactions can fail because of a failure in creating a session.

Action: Check the log file wrb.log for session related error messages.

10267 "Declarative Transactions exist tx APIs disallowed"

Cause: TX APIs are disallowed when declarative transactions are defined for a transaction.

Action: Remove the Declarative Transactions from the application configuration to enable the tx_begin, tx_commit and tx_rollback APIs.

10271 "An Icx request failed with transaction exception %s"

Cause: A transaction needs to be suspended in some cases when making an ICX request and the suspend failed causing the Icx request to fail.

Action: Transaction errors are logged to the \$ORACLE_HOME/ots/<Version>/admin directory. The files are named as xa_<DAD><mmdyy>.trc where DAD is the database that resulted in the transaction error and ts<mmdyy>.trc files. Please contact support with the information in the trc files.

10272 "An Icx request failed with transaction exception %s"

Cause: A transaction needs to be resumed in some cases when making an ICX request and the suspend failed causing the Icx request to fail.

Action: Transaction errors are logged to the \$ORACLE_HOME/ots/<Version>/admin directory. The files are named as xa_<DAD><mmdyy>.trc where DAD is the database that resulted in the transaction error and ts<mmdyy>.trc files. Please contact support with the information in the trc files.

10275 "Ots successfully initialized"

Cause: Debugging message.

10276 "Ots successfully terminated"

Cause: Debugging message.

10277 "Ots successfully established a connection to DAD %s"

Cause: Debugging message.

10278 "Ots successfully disconnected from DAD %s"

Cause: Debugging message.

10300 - 10599 : HTTP Daemon Adapter messages

10300 "Unable to find ADPTid for request \"%s\""

Cause: The ADPTid variable set for each request by the Netscape Adapter was not found.

10301 "Error in %s for %s. Request: \"%s\""

Cause: The service function mentioned returned ADPAPP_ERROR.

Action: Investigate ADP service code (e.g. dispatcher, or logger).

10302 "Unable to find client information. Request \"%s\""

Cause: Client IP address, or hostname information is not available for host-based authentication. DNS could be turned off for Domain-authentication, or the server is unable to retrieve IP address of client.

Action: Turn on DNS.

10303 "Unsupported user-based Authentication scheme \"%s\". Request \"%s\""

Cause: The server cannot handle the authentication scheme used. Only Basic is handled by Netscape FastTrack v2.x or before.

Action: Have browser client use acceptable authentication scheme.

10304 "Maximum simultaneous requests reached"

Cause: The maximum allowable simultaneous requests are already being processed.

Action: Wait for current requests to finish.

10305 "Error in reading obj.conf file: %s"

Cause: Possible syntax error in **obj.conf**.

Action: Fix syntax problem.

10306 "Heartbeat thread initialization failed"

Cause: Spawning off of thread failed. Thread package returned failure.

Action: Investigate compatibility of listener executable with thread package.

10307 "File Descriptor Check thread initialization failed"

Cause: Spawning off of thread failed. Thread package returned failure.

Action: Investigate compatibility of listener executable with thread package.

10308 "The socket to the client has failed"

Cause: The client terminated the connection (hit STOP), or the connection was broken.

Action: Investigate network, or client action.

10500 "Unable to obtain request ID for this request. Request: \"%s\""

Cause: The ndwuid_create library call did not return NDWUID_SUCC.

Action:

10501 "Per-process service initialization failed"

Cause: An [IndivInit] function returned ADPAPP_ERROR.

Action: Investigate service code.

10502 "Global service initialization failed"

Cause: An [IndivInit] function returned ADPAPP_ERROR.

Action: Investigate service code.

10503 "Error in Host-Authetication-Fail callback. Request: \"%s\""

Cause: Callback returned ADPAPP_ERROR.

Action: Investigate callback code.

10504 "Error in Host-Authetication-Fail callback. Request: \"%s\""

Cause: Callback returned ADPAPP_ERROR.

Action: Investigate callback code.

10505 "Syntax error in Adapter Configuration File (adp.cfg)"

Action: Check syntax of adp.cfg file.

10506 "Symbol referencing errors in adapter configuration file"

Cause: Misspelled function names in **adp.cfg** files, or functions non-existent in service shared object.

Action: Investigate adp.cfg file, or service shared object symbols.

10507 "Heartbeat callback failed"

Cause: Dispatcher's heartbeat callback returned an error.

Action: Investigate dispatcher.

10508 "Heartbeat thread initialized"

Cause: The adapter heartbeat thread has been initialized successfully.

Action: None.

10509 "Heartbeat thread terminated"

Cause: The adapter heartbeat thread has been terminated successfully.

Action: None.

10510 "Per-process service initialization successful"

Cause: The individual init stage calls for all services returned successfully.

Action: None.

10511 "Next Block call back returned with an error"

Cause: The dispatcher's next block call back function returned with an error.

Action: The dispatcher may be experiencing problems getting data from the cartridge.

10512 "Adapter configuration file (adapter.app) not found"

Cause: The fully constructed path to adapter.app was not correct.

Action: Check environment variables.

10513 "Shared object/DLL in adapter.app file not found."

Cause: The dll/so for an adapter service listed in adapter.app was not found.

Action: Check full path name.

10550 "Adapter services initialized successfully"

Cause: The ADP setup and Init functions for all ADP services were successful.

Action: None.

10552 "The adapter terminated successfully"

Cause: The ADP termination cleanup and the Terminate functions for all ADP services were successful.

Action: None.

10600 - 10699 : WRB ICX Services

10600 "ICX: (%(1)s) Error in destroying the request"

Cause: Free memory error occurred

10601 "ICX: (%(1)s) Error in receiving the response header"

Cause: Network error occurred or the response headers received is in incorrect format.

10602 "ICX: (%(1)s) Error in processing the response header"

Cause: Response headers received are in incorrect format.

10603 "ICX: (%(1)s) Error in receiving the response body"

Cause: Network error occurred.

10604 "ICX: Error in loading library libndwsio.so"

Cause: Unable to set the cartridge implementation.

Action: Use HTTP instead of ORB by renaming **libndwsio.so** to do something else.

10605 "ICX: (%(1)s) Can not handle the request via ORB"

Cause: Cartridge not reachable through ORB. This is a warning, request can still be completed via HTTP.

10606 "ICX: (%(1)s) Error in completing the request via ORB"

Cause: Called cartridge cannot complete the request.

Action: None.

10607 "ICX: (%(1)s) Error in getting the hostname %(2)s"

Cause: Fail to resolve the hostname.

Action: None.

10608 "ICX: (%(1)s) Error in opening the socket"

Cause: None.

Action: None.

10609 "ICX: (%(1)s) Error in establishing a connection"

Cause: None.

Action: None.

10610 "ICX: component initialized"**Cause:** None.**Action:** None.**10611 "ICX: component terminated"****Cause:** None.**Action:** None.**10612 "ICX: %(1)s Getting the Object Reference"****Cause:** None.**Action:** None.**10613 "ICX: %(1)s Received the Object Reference"****Cause:** None.**Action:** None.**10614 "ICX: %(1)s Executing the request"****Cause:** None.**Action:** None.**10615 "ICX: %(1)s Executing the request complete"****Cause:** None.**Action:** None.**10616 "ICX: %(1)s Retry request with digest (or redirect)"****Cause:** None.**Action:** None.**10617 "ICX: %(1)s Yilding the Object Reference"****Cause:** None.**Action:** None.**10618 "ICX: %(1)s Yilding the Object Reference complete"****Cause:** None.**Action:** None.

10619 "ICX: %(1)s Exception occurred while making request"

Cause: None.

Action: None.

10620 "ICX: %(1)s Connection established with remote server"

Cause: None.

Action: None.

10621 "ICX: %(1)s Send Data complete"

Cause: None.

Action: None.

10622 "ICX: %(1)s Receive Data complete"

Cause: None.

Action: None.

10623 "ICX: %(1)s Error(%(2)d) occured while initializing SSL"

Cause: None.

Action: None.

10624 "ICX: %(1)s Error(%(2)d) occured while creating SSL context"

Cause: None.

Action: None.

10625 "ICX: %(1)s Error(%(2)d) occured while configuring SSL"

Cause: None.

Action: None.

10626 "ICX: %(1)s Error(%(2)d) occured while retrieving OSS context"

Cause: None.

Action: None.

10627 "ICX: %(1)s Error(%(2)d) occured while opening the wallet"

Cause: None.

Action: None.

10628 "ICX: (%(1)s) Error(%(2)d) occurred while retrieving persona"

Cause: None.

Action: None.

10629 "ICX: (%(1)s) Error(%(2)d) occurred while setting credential"

Cause: None.

Action: None.

10630 "ICX: (%(1)s) Error(%(2)d) occurred while hand shaking"

Cause: None.

Action: None.

10631 "ICX: (%(1)s) Error(%(2)d) occurred while retrieving peer credential"

Cause: None.

Action: None.

10632 "ICX: (%(1)s) peer credential selection differ from client requirement"

Cause: None.

Action: None.

10633 "ICX: (%(1)s) hand shake completed successfully"

Cause: None.

Action: None.

10650 "ICX: JNI layer initialized"

Cause: None.

Action: None.

10651 "ICX: JNI layer terminated"

Cause: None.

Action: None.

10652 "ICX: JNI request (%(1)s) created"

Cause: None.

Action: None.

10653 "ICX: JNI C make request call done"

Cause: None.

Action: None.

10654 "ICX: JNI create response object done"

Cause: None.

Action: None.

10655 "ICX: JNI response info setup done"

Cause: None.

Action: None.

10656 "ICX: JNI response header setup done"

Cause: None.

Action: None.

10657 "ICX: JNI response data setup done"

Cause: None.

Action: None.

10658 "ICX: JNI make request complete"

Cause: None.

Action: None.

10659 "ICX: JNI create request %(1)s failed"

Cause: None.

Action: None.

10660 "ICX: JNI icx entry function returns error"

Cause: None.

Action: None.

10661 "ICX: JNI make request %(1)s"

Cause: None.

Action: None.

10662 "ICX: JNI make request %(1)s failed"

Cause: None.

Action: None.

10663 "ICX: JNI make request %(1)s needs auth"

Cause: None.

Action: None.

10700 - 10799 : WRB CONTENT Service Error messages

10700 "Username/Password not specified for the repository"

Cause: The DAD specified might not have the optional username password arguments set.

Action: Configure the DAD to have the username password or specify the username password as arguments to the call.

10701 "Error in opening repository with us@cstr: %s@%s[%s]"

Cause: An Error occurred in opening the repository by using the specified combination of username password and connect string.

Action: Check the RDBMS server error message for more info.

10702 "Illegal mode in openDocument %d"

Cause: WRBCS_READ cannot be used together with WRBCS_WRITE or WRBCS_APPEND. WRBCS_APPEND is currently not implemented.

Action: Use the correct mode to open the document.

10703 "WRB Content services schema does not exist"

Cause: The WRB Content services schema was not installed into the database.

Action: Reinstall Oracle Application Server.

10704 "Error in closing repository[%s]"

Cause: Refer to the RDBMS error messages listed for more information.

Action: Refer to the RDBMS error messages listed for more information.

10705 "Document name '%s' should begin with a '/'"

Cause: Error in parsing the document name. Documents should be named in /a/b/c format to simulate a directory structure. Folders will be supported in a later release.

Action: Name the documents in /a/b/c format to simulate a directory structure.

10706 "RDBMS Error in creating the document %s[%s]"

Cause: Creating a document failed because of the RDBMS error listed.

Action: Refer to the RDBMS Error for more information.

10707 "RDBMS Error in opening the document for read %s[%s]"

Cause: Opening a document for read failed because of the RDBMS error listed.

Action: Refer to the RDBMS Error for more information

10708 "RDBMS Error in reading the document %s[%s]"

Cause: Reading the document failed because of the listed RDBMS Error.

Action: Refer to the RDBMS Error for more information.

10709 "RDBMS Error in writing to the document %s[%s]"

Cause: Write to the document failed because of the listed RDBMS Error.

Action: Refer to the RDBMS Error for more information.

10710 "RDBMS Error in flushing the document %s[%s]"

Cause: Flushing the document commits the document in the database. The listed RDBMS error occurred when flushing.

Action: Refer to the RDBMS Error for more information.

10711 "RDBMS Error in deleting the document %s[%s]"

Cause: Deleting the document.

10712 "RDBMS Error in getting attributes for %s[%s]"

Cause: Getting attributes failed because of the listed RDBMS Error.

Action: Refer to the RDBMS Error for more information.

10713 "RDBMS Error in setting fixed attributes for %s[%s]"

Cause: Setting fixed attributes failed because of the listed RDBMS Error.

Action: Refer to the RDBMS Error for more information.

10714 "RDBMS Error in setting attributes for %s[%s]"

Cause: Setting attributes failed because of the listed RDBMS Error.

Action: Refer to the RDBMS Error for more information.

10715 "RDBMS Error in listing documents [%s]"

Cause: Listing documents failed due to the listed RDBMS Error.

Action: Refer to the RDBMS Error for more information.

10716 "Attempt to set read-only attribute %s"

Cause: You cannot set read-only attributes.

Action: Check the WRB API Reference for a list of read-only attributes.

10717 "Error decrypting passwd for DAD %s"

Cause: The password is not correctly encrypted.

Action: Make sure the password is correctly encrypted.

WRERCNT_SUCC

10750 "WRB Content services successfully loaded"

Cause: Informational message.

10751 "WRB Content services successfully unloaded"

Cause: Informational message.

10800 - 10999 : Cartridge server / Cartridge server factory

10800 "Global context initialization failed"

Cause: The Application Server components Configuration provider Logger, Resource Manager may be down.

Action: Shutdown and restart the Application server.

10801 "Configuration provider error in reading section %s for Cartridge %s"

Cause: Configuration for the cartridge is incorrect.

Action: Reconfigure the cartridge and reload the application server.

10802 "Cartridge %s incorrectly configured"

Cause: Configuration for the cartridge is incorrect.

Action: Reconfigure the cartridge and reload the application server.

10803 "Cartridge instance factory for %s not initialized"

Cause: Factory implementation is incorrect or missing.

Action: Call World Wide support with the Bug number.

10804 "Cartridge instance failed to initialize"

Cause: A cartridge instance can fail for a variety of reasons including unresolved symbols in the cartridge implementation incorrect configuration.

Action: This is a generic message for instance creation failure look for more specific messages that point to the cause for the failure.

10805 "Implementation shared object/DLL not specified for cartridge %s"

Cause: Cartridge implementation either a shared object or a DLL has not been specified in the cartridge configuration.

Action: Reconfigure the cartridge and specify the implementation DLL.

Action: Reload the application server

10806 "Cartridge implementation %s for %s invalid. [Reason] %s"

Cause: The specified implementation for the cartridge is invalid for the reason specified. This is mostly due to unresolved symbols in the implementation.

Action: Remove the unresolved symbols in the implementation and retry the request to the cartridge.

10852 "Cartridge Server attempted to load an additional library %s for cartridge %s"

Cause: Cartridge Server attempted to load an additional shared object. Not permitted

Action: Make sure there is only one shared object defined for this cartridge server in the **wrb.app** file.

10885 "Exception <%s> thrown in the exec() callback of cartridge %s"

Cause: The exec() callback threw an exception possibly because of a programming error that would otherwise cause a coredump

Action: Run your code in standalone mode (no cartridge server involved) and try to correct the error.

10886 "Exception <%s> thrown in the authorize() callback of cartridge %s"

Cause: The authorize() callback threw an exception possibly because of a programming error that would otherwise cause a coredump

Action: Run your code in standalone mode (no cartridge server involved) and try to correct the error.

11000 - 11099 : Apache Adapter specific messages

11000 "The Apache adapter factory started successfully"

Cause: The factory in the Apache Dispatcher process that generates the adapter ORs has been started successfully.

Action: None.

11001 "The Apache adapter factory terminated successfully"

Cause: The factory in the Apache Dispatcher process that generates the adapter ORs has been shutdown.

Action: None.

11002 "The factory thread in Apache adapter not initialized"

Cause: An error occurred while starting the factory thread in Apache adapter.

Action: There might be problems with OMX initialization. Fatal error.

11003 "Apache master dispatcher received extra acknowledgments"

Cause: The apache master has received more acknowledgments than the child process started.

Action: The process will continue working but may eventually crash if this is due to a memory corruption.

11004 "Apache master dispatcher starting default number of child dispatchers"

Cause: An error occurred while getting information about the number of child dispatcher processes to start from the Config provider or this information is not provided.

Action: Check to make sure that the corresponding configuration information is present.

11005 "Apache master dispatcher couldn't read mimetype information"

Cause: An error occurred while reading the mimetypes information from the Apache master listener.

Action: Please check to make sure that the listener is configured properly. Fatal error.

11006 "Apache master dispatcher couldn't read the implementation name"

Cause: An error occurred while reading the implementation name information from the Apache master listener.

Action: Please check to make sure that the listener is configured properly. Fatal error.

11007 "Apache master dispatcher couldn't read directory mapping information"

Cause: An error occurred while reading the directory mapping information from the Apache master listener.

Action: Please check to make sure that the listener is configured properly. Fatal error.

11008 "Apache master dispatcher couldn't read port information"

Cause: An error occurred while reading the port and IP information from the Apache master listener.

Action: Please check to make sure that the listener is configured properly. Fatal error.

11009 "Apache master dispatcher encountered error while sending ACK to master listener"

Cause: An error occurred while sending an ACK to the master apache listener.

Action: Please check no other process is using the same port. Fatal error.

11010 "Ping to child dispatcher failed"

Cause: The master dispatcher encountered an error while pinging a child dispatcher. The master dispatcher will assume that the child process is dead and will attempt to free all its resources and start a new child process.

Action: None.

11011 "Apache master dispatcher process has been shutdown"

Cause: Apache master dispatcher process has been shutdown.

Action: None.

11012 "The ORB server thread started in master dispatcher"

Cause: The ORB server thread started in master dispatcher.

Action: None.

11013 "The ORB server thread terminated in master dispatcher"

Cause: The ORB server thread terminated in master dispatcher.

Action: None.

11014 "Error sending Virtual Path Mapping information to Apache listener"

Cause: An error occurred while sending Virtual Path Mapping information to Apache listener.

Action: Make sure that no other process is using the same port as the master dispatcher. Fatal error.

11015 "Error doing exec of child dispatcher executable"

Cause: The process forked by Master dispatcher couldn't exec the child dispatcher executable.

Action: Make sure that the child dispatcher executable is in the system path. Fatal error.

11016 "Apache master dispatcher timedout waiting for child process to initialize"

Cause: The process forked by Master dispatcher couldn't initialize properly or the Master Dispatcher timed out before they could initialize.

Action: Increase the timeout by setting the appropriate environment variable. If that doesn't help then check to make sure that the child processes are initializing properly. Fatal error.

11017 "Apache master dispatcher could not initialize server thread"

Cause: The Apache master dispatcher could not initialize properly.

Action: Look at the YS error message.

20000 - 20099 : GENERIC STRINGS for wladmin(NLS)

20000 "ALWAYS"

Cause: Informational message.

Action: None.

20001 "LAZY"

Cause: Informational message.

Action: None.

20002 "LAZY_WITH_CGI"

Cause: Informational message.

Action: None.

20003 "NEVER"

Cause: Informational message.

Action: None.

20100 - 20199 : GENERIC STRINGS for csadmin(NLS)

20100 "Java"

Cause: Informational message.

Action: None.

20101 "Web"

Cause: Informational message.

Action: None.

20102 "User"

Cause: Informational message.

Action: None.

20103 "add"

Cause: Informational message.

Action: None.

20104 "delete"

Cause: Informational message.

Action: None.

20105 "Cartridge Server Default settings successfully written"

Cause: Information Message.

Action: None.

20106 "%(1)s section does not exist in wrb.app"

Cause: The **wrb.app** is corrupted.

Action: Need to copy just the section from **servapp.dfl** to **wrb.app**.

20107 "ALL"

Cause: Informational message.

Action: None.

20108 "%(1)s must be a numeric string"

Cause: The entered string is supposed to be a number.

Action: Reenter the string, make sure it's a number.

20109 "\%(1)s\" specified in Virtual Path Protection section is not a valid Virtual Path for this Cartridge"

Cause: The above virtual path is not an entry in the Virtual Path section for this cartridge.

Action: Make an entry for this virtual path in the Virtual Path section first OR specify a virtual path which already exists for this cartridge.

020110 "Select"

Cause: Informational message.

Action: None.

020111 "Currently there are no Transactions for this Application.\n"

Cause: Informational message.

Action: None.

020112 "Transaction [%(1)s] already exists for Application [%(2)s]"

Cause: Transaction with the specified name already exists.

Action: Specify a different name for the transaction.

020113 "Transaction added successfully"

Cause: Informational message.

Action: None.

020114 "Transaction modified successfully"

Cause: Informational message.

Action: None.

020115 "Invalid value for Transaction Timeout Parameter"

Cause: Valid values for Transaction Timeout are positive integers.

Action: Specify a valid value for Transaction Timeout.

020116 "Failed to initialize Site Manager"

Cause: Internal Error: ndwmf_initialize() fails.

Action: Please make sure that the environment is correct and site.app resides in the correct place.

020117 "Transaction(s) deleted successfully"

Cause: Informational message.

Action: None.

020118 "No such Transaction exists"

Cause: This could potentially happen when the user modifies the name of the transaction but does not reload the tree applet.

Action: Reload the tree applet (For eg. using Shift+Reload within Netscape Browser).

020119 "Transaction Parameters modified successfully"

Cause: Informational message.

Action: None.

020120 "Realm"

Cause: Informational message.

Action: None.

020121 "Server"

Cause: Informational message.

Action: None.

020122 "ACL"

Cause: Informational message.

Action: None.

020123 "Currently there are no Certificate based Realms.\n"

Cause: Informational message.

Action: None.

020124 "Currently there are no Certificate based Servers.\n"

Cause: Informational message.

Action: None.

020125 "Currently there are no Certificate based ACLs.\n"

Cause: Informational message.

Action: None.

020126 "Realm [% (1)s] already exists"

Cause: Realm with the specified name already exists.

Action: Specify a different name for the Realm.

020127 "Server [% (1)s] already exists"

Cause: Server with the specified name already exists.

Action: Specify a different name for the Server.

020128 "ACL [% (1)s] already exists"

Cause: ACL with the specified name already exists.

Action: Specify a different name for the ACL.

020129 "Realm [% (1)s] added successfully"

Cause: Informational message.

Action: None.

020130 "Realm [% (1)s] modified successfully"

Cause: Informational message.

Action: None.

020131 "Realm [% (1)s] deleted successfully"

Cause: Informational message.

Action: None.

020132 "Server [% (1)s] added successfully"

Cause: Informational message.

Action: None.

020133 "Server [% (1)s] modified successfully"

Cause: Informational message.

Action: None.

020134 "Server [% (1)s] deleted successfully"

Cause: Informational message.

Action: None.

020135 "ACL [% (1)s] added successfully"

Cause: Informational message.

Action: None.

020136 "ACL [% (1)s] modified successfully"

Cause: Informational message.

Action: None.

020137 "ACL [% (1)s] deleted successfully"

Cause: Informational message.

Action: None.

020138 "No such Certificate based Realm exists"

Cause: This could potentially happen when the user modifies the name of the realm but does not reload the tree applet.

Action: Reload the tree applet (For eg. using Shift+Reload within Netscape Browser).

020139 "No such Certificate based Server exists"

Cause: This could potentially happen when the user modifies the name of the server but does not reload the tree applet.

Action: Reload the tree applet (For eg. using Shift+Reload within Netscape Browser).

020140 "No such Certificate based ACL exists"

Cause: This could potentially happen when the user modifies the name of the acl but does not reload the tree applet.

Action: Reload the tree applet (For eg. using Shift+Reload within Netscape Browser).

020141 "ACL Name"

Cause: Informational message.

Action: None.

020142 "ACL Expression"

Cause: Informational message.

Action: None.

020143 "Server Name"

Cause: Informational message.

Action: None.

020144 "Host"

Cause: Informational message.

Action: None.

020145 "Port"

Cause: Informational message.

Action: None.

020146 "SSL"

Cause: Informational message.

Action: None.

020147 "Admin User"

Cause: Informational message.

Action: None.

020148 "Admin Password"

Cause: Informational message.

Action: None.

020149 "Search Base"

Cause: Informational message.

Action: None.

020150 "Certificate Attribute"

Cause: Informational message.

Action: None.

020151 "Group Member Attribute"

Cause: Informational message.

Action: None.

020152 "Realm Name"

Cause: Informational message.

Action: None.

020153 "Server"

Cause: Informational message.

Action: None.

020154 "ACL"

Cause: Informational message.

Action: None.

020155 "Stateless"

Cause: Informational message.

Action: None.

020156 "Remote Interface"

Cause: Informational message.

Action: None.

020157 "Determine Scheduling/Distribution of Applications"

Cause: Informational message.

Action: None.

020158 "By Weights"

Cause: Informational message.

Action: None.

020159 "By Machine Load"

Cause: Informational message.

Action: None.

020160 "By Weights and Machine Load"

Cause: Informational message.

Action: None.

020161 "Select"

Cause: Informational message.

Action: None.

020162 "Host"

Cause: Informational message.

Action: None.

020163 "Min # of Servers"

Cause: Informational message.

Action: None.

020164 "Max # of Servers"

Cause: Informational message.

Action: None.

020165 "Weight"

Cause: Informational message.

Action: None.

020166 "%(1)s: Invalid Weight specified; (Valid Range : 0.004 - 1.000)."

Cause: Specified weight is invalid. Valid range for weights is (0.004 - 1.000).

Action: Specify weight in valid range.

020167 "Cancel"

Cause: Informational message.

Action: None.

020168 "Process Model parameter modified successfully"

Cause: Informational message.

Action: None.

020169 "Min # of Servers is greater than Max # of Servers"

Cause: Min # of Servers cannot be greater than Max # of Servers.

Action: Specify Min # of Servers to be less than or equal to Max # of Servers.

020170 "Min # of Instances is greater than Max # of Instances"

Cause: Min # of Instances cannot be greater than Max # of Instances.

Action: Specify Min # of Instances to be less than or equal to Max # of Instances.

020171 "Min # of Threads is greater than Max # of Threads"

Cause: Min # of Threads cannot be greater than Max # of Threads.

Action: Specify Min # of Threads to be less than or equal to Max # of Threads.

020172 "%(1)s: Min # of Servers is greater than Max # of Servers"

Cause: Min # of Servers cannot be greater than Max # of Servers.

Action: Specify Min # of Servers to be less than or equal to Max # of Servers for the specified host.

020173 "Min # of Instances is not valid positive integer"

Cause: Min # of Instances should be a valid positive integer.

Action: Specify a positive integer for Min # of Instances parameter.

020174 "Max # of Instances is not valid positive integer"

Cause: Max # of Instances should be a valid positive integer.

Action: Specify a positive integer for Max # of Instances parameter.

020175 "Min # of Threads is not valid positive integer"

Cause: Min # of Threads should be a valid positive integer.

Action: Specify a positive integer for Min # of Threads parameter.

020176 "Max # of Threads is not valid positive integer"

Cause: Max # of Threads should be a valid positive integer.

Action: Specify a positive integer for Max # of Threads parameter.

020177 "Minimum # of Servers is not valid positive integer"

Cause: Minimum # of Servers should be a valid positive integer.

Action: Specify a positive integer for Minimum # of Servers parameter.

020178 "Maximum # of Servers is not valid positive integer"

Cause: Maximum # of Servers should be a valid positive integer.

Action: Specify a positive integer for Maximum # of Servers parameter.

020179 "%(1)s: Minimum # of Servers is not valid positive integer"

Cause: Minimum # of Servers should be a valid positive integer.

Action: Specify a positive integer for Minimum # of Servers parameter for the specified host.

020180 "%(1)s: Maximum # of Servers is not valid positive integer"

Cause: Maximum # of Servers should be a valid positive integer.

Action: Specify a positive integer for Maximum # of Servers parameter for the specified host.

020181 "Process Model parameter cannot be changed while OAS is running"

Cause: Oracle Application Server should be stopped in order to modify Process Model configuration parameter.

Action: Stop OAS; retry.

020182 "Invalid DAD Name specified (only alpha-numeric and \"_\" allowed)."

Cause: A valid DAD name is one with alpha-numeric and "_" characters.

Action: Specify valid DAD name.

020183 "Max # of Clients is not valid positive integer."

Cause: Max # of Clients should be a valid positive integer.

Action: Specify a positive integer for Max # of Clients parameter.

020184 "Listener could not be created as %(1)s is not set."

Cause: Specified environment variable is not set in the environment/registry.

Action: Set this environment variable to right value and retry.

020185 "%(1)s failed: %(2)s"

Cause: The above-mentioned wrfc API invocation returned an error.

Action: Please take corrective action specified by wrfc error.

020186 "Broker Timeout"

Cause: Informational message.

Action: None.

020187 "Failure Recovery configuration updated successfully."

Cause: Informational message.

Action: None.

020188 "Updated Display Name successfully."

Cause: Informational message.

Action: None.

020189 "Section: %(1)s does not exist."

Cause: The specified section does not exist in wrb.app.

Action: Please reload the tree applet using Shift+Reload in browser.

020190 "Security Parameters updated successfully."

Cause: Informational message.

Action: None.

020191 "Start-up Instances should be positive integer between 0 - 100 ."

Cause: Start-up Instances should be an integer between 0 - 100.

Action: Specify a valid positive integer for Start-up Instances parameter.

020192 "ThreadSafe ."

Cause: Informational message

Action: None

020193 "Currently there are no Sessions for this Cartridge. \n."

Cause: Informational message

Action: None

020194 " Session [% (1)s] already exists for cartridge [% (2)s]."

Cause: Session with the specified name already exists.

Action: Specify a different name for the session.

20200 - 20299 : Oracle Application Server Manager Messages

20200 "OAS manager can not initialize wrcl"

Cause: The **site.app** file may not exist or may not be readable.

Action: Check to make sure the **site.app** file exists and is readable.

20201 "OAS manager not initialized correctly"

Cause: The Oracle Application Server Manager was not initialized properly.

Action: Find out why Oracle Application Server Manager was not initialized previously.

20202 "OAS manager can not read %s name value pair in the %s section in site.app"

Cause: **site.app** is not readable.

Action: Change the read permission of the **site.app** file.

20203 "OAS manager can not write %s name value pair in the %s section in site.app"

Cause: **site.app** is not writable.

Action: Change the write permission of the **site.app** file.

20204 "OAS manager can not delete %s section in site.app"

Cause: **site.app** is not writable.

Action: Change the write permission of the **site.app** file.

20205 "Component name is not specified"

Cause: Component name is missing.

Action: Please specify a component name.

20206 "%s already exists"

Cause: The specified component already exists.

Action: Please delete the component first before the add.

20207 "Site information is missing in site.app"

Cause: There is no [root] or site section in **site.app**.

Action: Please correct the problem in **site.app**.

20208 "Machine name is not specified"

Cause: Machine name is missing.

Action: Please specify a machine to perform the action.

20209 "OAS manager can not read listener configuration file owl.cfg"

Cause: Owl.cfg is not readable.

Action: Change the read permission of the **owl.cfg** file.

20210 "stopped successfully"

Cause: Informational message.

Action: None.

20211 "stopped unsuccessfully. Cause is "

Cause: Informational message.

Action: None.

20212 "The listener can not be started. Please start the OAS processes first"

Cause: The Oracle Application Server processes to be started before the listener can be started.

Action: Start the Oracle Application Server processes first.

20213 "OAS manager can not read %s name value pair in the %s section in wrb.app"

Cause: **wrb.app** is not readable.

Action: Change the read permission of the **wrb.app** file.

20214 "The OAS processes can not be started, because the CORBA orb processes can not be started"

Cause: The Oracle ORB processes cannot be started.

Action: Run stop site command and try to start the site again.

20215 "The OAS processes are already up. Please stop them first"

Cause: The Oracle Application Server process are up and running.

Action: Run stop Oracle Application Server before start the Oracle Application Server again.

20216 "Up"

Cause: Informational Message.

Action: None.

20217 "ORB Servers"

Cause: Informational Message.

Action: None.

20218 "reloaded successfully"

Cause: Informational message.

Action: None.

20219 "reloaded unsuccessfully. Cause is "

Cause: Informational message.

Action: None.

20220 "The HTTP Listeners are still up. Please stop them first"

Cause: The HTTP listeners are up and running.

Action: Stop HTTP listeners before stopping the Oracle Application Server processes.

20221 "Some applications are still up. Please stop them first"

Cause: One or more applications are still running.

Action: Stop Applications before stopping the Oracle Application Server again.

20222 "The node manager is not running. Please start the node manager."

Cause: Node Manager is not running.

Action: Start the Node Manager.

20223 "Failed to delete node. Please make sure Node Manager is up."

Cause: Informational message.

Action: None.

20224 "OAS process '%s' could not be found."

Cause: The process has a invalid name. It cannot be started or stopped.

Action: Check the name and try again.

20225 “ ORB configuration parameter(s) cannot be changed while OAS is running.”

Cause: OAS should be stopped in order to modify orb configuration parameter.

Action: Stop OAS; retry.

20226 “ Add Listener”

Cause: Informational message.

Action: None.

20227 “Register Listener”

Cause: Informational message”

Action: None.

20228 “ Unregister Listener”

Cause: Informational message.

Action: None

20229 “ There is an error during ORB initialization. Please make sure the ORB security parameters are configured correctly.”

Cause: The ORB security parameters are not configured correctly. for example the security parameters are configured correctly.

Action: Reset the ORB security parameters.

20230 “Basic”

Cause: Informational message

Action: None.

20231 “ Digest”

Cause: Informational message”

Action: None

20232 “ Crypto (SSL)”

Cause: Informational message.

Action: None

20233 “IP”

Cause: Informational message.

Action: none.

20234 “Domain”

Cause: Informational message.

Action: None

20235 “ Initial Start-up Instances”

Cause: Informational messages.

Action: None.

20236 “ Tunning parameters updated sucessfully.”

Cause: Informational messages.

Action: None

20237 “ Server parameters updated sucessfully.”

Cause: Informational messages.

Action: None.

20238 “ Note: Priority set for indivisual cartridge will override this setting.”

Cause: Informational messages.

Action: None

20239 “ Tuning parameter updated sucessfully.”

Cause: Informational message.

Action: None.

20240 “Start-up Instances is not valid positive integer.”

Cause: Start-up Instances should be a valid positive integer.

Action: Specify a positive integer for Start-up Instances parameter for the specified host.

20241 “Bean parameters updated sucessfully.”

Cause: Informational message.

Action: None.

20242 “ Timeout should be a valid positive integer.”

Cause: Timeout should be valid positive integer.

Action: Specify a positive integer for Timeout parameter for the specified host.

20300 - 24999 : ECO/Java

25000 - 25999 : RM Proxy

25000 "Memory allocation failed"

Cause: Cannot allocate requested memory.

Action: Reduce the number of running processes and retry operation.

25001 "The free list does not contained any more entries"

Cause: OMX sends more requests to RM proxy than allowed.

Action: Check that the number of threads in the process is not greater than the total number of free list entries.

25002 "Cartridge '%s' is an invalid name"

Cause: Invalid cartridge name given to RM proxy.

Action: Check that cartridge name is valid in **wrb.app**.

25003 "Unable to get the IP address where RM proxy is located"

Cause: RM proxy is not able to obtain the host's IP address.

Action: Check the failed routine to make sure it obtained a valid hostname.

25004 "Broker throws exception '%s' in get cartridge routine"

Cause: Broker throws an exception when RM proxy calls `cartcorba_getmany()`.

Action: Check the exception.

25005 "Broker throws exception '%s' in yield cartridge routine"

Cause: Broker throws an exception when RM proxy calls `cartcorba_ymany()`.

Action: Check the exception.

25006 "RM proxy failed to return a valid object reference to client."

Cause: Object reference received from broker is NULL.

Action: Check broker code to figure out why it cannot give a valid object reference.

25007 "Cartridge name (in COSNAM format) is invalid"

Cause: Invalid cartridge name given to RM proxy.

Action: Check that cartridge name is valid and in **wrb.app**.

25008 "Exception '%s' in dumping RM proxy state"

Cause: RM proxy receives an exception in show state routine.

Action: Check the exception.

25009 "CANNOTPROCEED exception raised. Reason: %s"

Cause: RM proxy cannot proceed due to 'reason.'

Action: Check the reason.

25010 "Failed to get cartridge '%s' for '%d' times"

Cause: RM proxy cannot get cartridge from Broker after max retries.

Action: Check that maximum instance and servers are not reached.

25011 "Error encountered in reading wrb.app: %s"

Cause: wrb.app is not correct.

Action: Verify wrb.app has valid information.

25012 "Broker returns %d for requesting cartridge '%s'"

Cause: Broker was not able to satisfy cartridge request.

Action: Check broker's log messages to see why it cannot return cartridge.

25013 "%s %s"

Cause: Tracing requests in RM proxy.

Action: None.

25014 "Parsing authentication string failed. Cartridge: %s. AuthenticationString: %s. Error Code: %d."

Cause: Authentication server parse authentication string failed.

Action: Check authentication string is valid.

25015 "Setting up authentication information failed. Routine: %s. AuthType: %d. Error Code: %d. More Information: %s."

Cause: Setup authentication information failed.

Action: Check authentication information passed in or Authentication server error messages.

25016 "Authentication string is not available in wrb.app for cartridge %s"

Cause: No authentication string found for this cartridge.

Action: Make sure authentication string for a cartridge is set.

25017 "Authentication failed for username %s. Error Code=%d. Authenticated=%d."

Cause: Authentication server authenticating token failed.

Action: Check that client's authentication information is valid

25018 "Authentication access is not granted for cartridge %s."

Cause: Cartridge is setup so that access is not granted for external use.

Action: Change authentication string to grant access, if applicable.

25019 "Auth provider expects plain cleartext password while a MD5 encrypted password is passed in for cartridge %s."

Cause: Wrong password type used.

Action: Use cleartext password instead of MD5.

25020 "Protect string and client's requested method do not matched. Protect string=%s. Client method=%d."

Cause: Protect string and client's method do not matched.

Action: Either change protect string or use the correct method.

25021 "%s %s"

Cause: Converting IP address string failed - internal error.

Action: Check valid IP address is given for conversion routine.

25022 "%s failure"

Cause: Create failures are usually due to insufficient system resources.

Action: Check system resources, such as memory etc..

25023 " %s failure"

Cause: Init failures are typically due to insufficient system resources or errors in the configuration file (wrb.app).

Action: Check system resources, such as memory etc. and wrb.app.

25024 " RM/Proxy initialization sucessful."

Cause: Informational message.

Action: None.

25025 “ RM/Proxy failed to register with Name Server”

Cause: The orb or Name Server may be down.”

Action: Check to see if the orb and Name server are up.

25026 “ RM/Proxy sucessfully registered with Name Server.”

Cause: Informational message.

Action: None.

25027 “ RM/Proxy failed to unregister with Name Server.

Cause: The orb or name server may be down.

Action: Check to see if orb and Name Server are up.

25028 “ RM/Proxy sucessfully unregistered with Resource Manager.”

Cause: Informational message.

Action: None.

25029 “ RM/proxy failed to register with Resource Manager.”

Cause: The orb or Resource Manager may be down.

Action: Check to see if orb and Resource Manager are up.

25030 “ RM/Proxy sucessfully registered with Resource Manager.”

Cause: Informational message.

Action: none.

25031 “ RM/Proxy failed to unregister with Resource manager.”

Cause: The orb or Resource Manager may be down.

Action: Check to see if orb and Resource Manager are up.

25032 “ RM/Proxy sucessfully unregistered with Resource Manager”

Cause: Informational message.

Action: None.

25033 “ No AINC Name in configuration file. Creation of all AINC Cartridges will be disabled”

Cause: The OAS configuration file does not contain the name of the AINC cartridges.

Action: Fix OAS configuration file.

25034 “ Added application %s to name context tree.”

Cause: Informational message

Action: None.

25035 “ Sucessfully read all the cartridge information.”

Cause: Informational message.

Action: None.

25069 “RM/Proxy is up and accepting requests.”

Cause: Informational message.

Action: None.

25070 “ During RM/Proxy reinit, %s reinit failure.”

Cause: Reinit failure are typically due to insufficient system resources or errors in the configuration file (wrb.app).

Action: Check the system resources such as the memory etc. and wrb.app. for Logger or Configuration Provider reinit errors, check to see that the orb and Logger or the configuration Provider (respectively) are up.

25071 “ Reinit sucessful.”

Cause: Informational message.

Action: None.

25080 “Internal shutdown of RM/Proxy.”

Cause: Informational message.

Action: None.

25081 “ Remove called on RM/Proxy. Shutdown thread created.”

Cause: Informational message.

Action: None.

25082 “ Shutdown thread, preparing for shutdown.”

Cause: Informational message.

Action: None.

25083 “ Shutdown thread, waking up any waiting client threads”

Cause: Informational message.

Action: None.

25084 “ Shutdown thread, done waking up any waiting client threads.”

Cause: Informational message.

Action: None.

25085 “ Shutdown main in progress : no exp.”

Cause: Informational message.

Action: None.

25086 “ Shutdown main in progress: heartbeat thread shutdown done.”

Cause: Informational message.

Action: none.

25087 “ Shutdown main in progress: shutdown thread done.”

Cause: Informational message.

Action: None

25088 “ Shutdown main in progress: exp free done.”

Cause: Informational message.

Action: None.

25100 "Outstanding Requests"

Cause: Message used by show state. not an error.

25101 "Objects to be relinquished"

Cause: Message used by show state. not an error.

25150 “ Method %s not supported.”

Cause: The method called is not supported.

Action: Do not call this method.

25151 “ Insufficient memory (Function %s).”

Cause: There is insufficient memory on the machine.

Action: Shutdown system, allocate more memory, and restart.

25152 “ Resolve for application failed as there is no AINC name in configuration file.”

Cause: A resolve was called for an application that requires the AINC cartridge, but the AINC cartridge name was not in the configuration file.

Action: The AINC cartridge name is put in the configuration file by the application deployment tool. Either no application that requires an AINC has been deployed, or there was some problem during the deployment- redeploy the application.

25153 “ Caught exception: %s in function: %s”

Cause: See exception message for detail.

Action: see exception message for detail.

26000 - 26099 : Monitoring daemon messages

Some of the following messages include a string “or=”. This states that the following value is the IOR pointer. If this value is null, your object reference was null.

26002 "CORBA runtime or call to NameService failed (exception=%s)"

Cause: CORBA runtime or NameService not running, or configuration problem.

26004 "Could not list NameService entries (name=%s, exception=%s)"

Cause: CORBA NameService is probably not running.

26800 - 27999 : Management helper library messages and config provider server messages

Some of the following messages include a string “or=” or “ns=”.

- “or=”—The following value is the IOR pointer. If this value is null, your object reference was null.
- “ns=”—The following value is the Names Server object reference. If this value is null, the Names Server object reference is invalid.

26900 "Select"

Cause: Informational message.

Action: None.

26901 "Name"

Cause: Informational message.

Action: None.

26902 "Description"

Cause: Informational message.

Action: None.

26903 "Components"

Cause: Informational message.

Action: None.

26904 "ALL"

Cause: Informational message.

Action: None.

26905 "Add"

Cause: Informational message.

Action: None.

26906 "DELETE"

Cause: Informational message.

Action: None.

26907 "OK"

Cause: Informational message.

Action: None.

26908 "Node Added successfully"

Cause: Informational message.

Action: None.

26909 "Failed to add node. Please check to make sure all inputs are correct, and Node Manager is up"

Cause: Informational message.

Action: None.

26910 "Node Deleted successfully"

Cause: Informational message.

Action: None.

26911 "Wrb Process Added successfully"

Cause: Informational message.

Action: None.

26912 "Wrb Process Deleted successfully"

Cause: Informational message.

Action: None.

26913 "Site"

Cause: Informational message.

Action: None.

26914 "Oracle Application Server"

Cause: Informational message.

Action: None.

26915 "HTTP Listeners"

Cause: Informational message.

Action: None.

26916 "Cartridges"

Cause: Informational message.

Action: None.

26917 "Applications"

Cause: Informational message.

Action: None.

26918 "Create New DAD"

Cause: Informational message.

Action: None.

26919 "Copy DAD"

Cause: Informational message.

Action: None.

26920 "Apply"

Cause: Informational message.

Action: None.

26921 "Advanced"

Cause: Informational message.

Action: None.

26922 "Delete DAD"

Cause: Informational message.

Action: None.

26923 "Confirm Delete"

Cause: Informational message.

Action: None.

26924 "Modify/Delete Existing DAD"

Cause: Informational message.

Action: None.

26925 "Select"

Cause: Informational message.

Action: None.

26926 "Currently there are no DADs in the system.\n"

Cause: Informational message.

Action: None.

26927 "Name\tDescription\tNode\tSystem Id"

Cause: Informational message.

Action: None.

26928 "Node"

Cause: Informational message.

Action: None.

26929 "System Id"

Cause: Informational message.

Action: None.

26930 "Status"

Cause: Informational message.

Action: None.

26931 "Name\tPort/Type\tNode\tSystem Id"

Cause: Informational message.

Action: None.

26932 "Port/Type"

Cause: Informational message.

Action: None.

26933 "Down"

Cause: Informational message.

Action: None.

26934 "Process Status\t\tConnections\t\tRequests\t\t\nName\tNode\tSID\tCPU\tMemory\t | Current\tLast Time\tTotal\t | Pending\tTotal\n"

Cause: Informational message.

Action: None.

26935 "Process Name\tReload Result\n"

Cause: Informational message.

Action: None.

26936 "Process Status"

Cause: Informational message.

Action: None.

26937 "Connections"

Cause: Informational message.

Action: None.

26938 "Requests"

Cause: Informational message.

Action: None.

26939 "Name"

Cause: Informational message.

Action: None.

26940 "SID"

Cause: Informational message.

Action: None.

26941 "CPU"

Cause: Informational message.

Action: None.

26942 "Memory"

Cause: Informational message.

Action: None.

26943 "Current"

Cause: Informational message.

Action: None.

26944 "Last Time"

Cause: Informational message.

Action: None.

26945 "Total"

Cause: Informational message.

Action: None.

26946 "Pending"

Cause: Informational message.

Action: None.

26947 "Process Name"

Cause: Informational message.

Action: None.

26948 "Reload Result"

Cause: Informational message.

Action: None.

26949 "Failed"

Cause: Informational message.

Action: None.

26950 "<HR><H4>Installing %s for User: %s ...</H4><HR>\n"

Cause: Informational message.

Action: None.

26951 "PL/SQL Packages"

Cause: Informational message.

Action: None.

26952 "Database Browser Packages"

Cause: Informational message.

Action: None.

26953 "LOGGER Packages"

Cause: Informational message.

Action: None.

26954 "Log Analyzer Packages"

Cause: Informational message.

Action: None.

26955 "HR and Train Demo packages"

Cause: Informational message.

Action: None.

26956 "Content Services packages"

Cause: Informational message.

Action: None.

26957 "Display Name"

Cause: Informational message.

Action: None.

26958 "Application"

Cause: Informational message.

Action: None.

26959 "Server Runtime"

Cause: Informational message.

Action: None.

26960 "Server Interface"

Cause: Informational message.

Action: None.

26961 "Application Version"

Cause: Informational message.

Action: None.

26962 "Execution String"

Cause: / Informational message.

Action: None.

26963 "Client Jar File"

Cause: Informational message.

Action: None.

26964 "Server Jar File"

Cause: Informational message.

Action: None.

26965 "Application File"

Cause: Informational message.

Action: None.

26966 "Cartridges"

Cause: Informational message.

Action: None.

26967 "Application Added Successfully"

Cause: Informational message.

Action: None.

26968 "Cartridge Added Successfully"

Cause: Informational message.

Action: None.

26969 "Application Deleted Successfully"

Cause: Informational message.

Action: None.

26970 "Cartridge Deleted Successfully"

Cause: Informational message.

Action: None.

26971 "The dad '%s' does not exist in application '%s!'"

Cause: Informational message.

Action: None.

**26972 "To start/stop/status the Oracle Web Listener:\nusage: owscctl
[start | stop | reload | status] [listener name]\n\n"**

Cause: Informational message.

Action: None.

26973 "owscctl: Please set your environment variable ORACLE_HOME.\n"

Cause: Informational message.

Action: None.

26974 "\"\$APP\$\""

Cause: Informational message.

Action: None.

26975 "\"\$CARTX\$\""

Cause: Informational message.

Action: None.

26976 "\"Configuration\""

Cause: Informational message.

Action: None.

26977 "\"Server\""

Cause: Informational message.

Action: None.

26978 "\"Cartridges\""

Cause: Informational message.

Action: None.

26979 "\"Logging\""

Cause: Informational message.

Action: None.

26980 "\"Java Environment\""

Cause: Informational message.

Action: None.

26981 "\"Web Parameters\""

Cause: Informational message.

Action: None.

26982 "\"Jar of Beans\""

Cause: Informational message.

Action: None.

26983 "\"Java Parameters\""

Cause: Informational message.

Action: None.

26984 "\"CCorba Parameters\""

Cause: Informational message.

Action: None.

26985 "\"PLSQL Parameters\""

Cause: Informational message.

Action: None.

26986 "\"Cartridge Parameters\""

Cause: Informational message.

Action: None.

26987 "\"Virtual Path\""

Cause: Informational message.

Action: None.

26988 "\"Environment Variables\""

Cause: Informational message.

Action: None.

26989 "To start/stop/status the Oracle WebServer WRB or Cartridge process:\n"

Cause: Informational message.

Action: None.

26990 "usage: owscctl [start | stop | status] [[-e] wrb | cartridge | -p process_name] | ncx\n\n"

Cause: Informational message.

Action: None.

26991 "To start/stop/status the Oracle Web Status Monitor:\nusage: owscctl [start | stop | status] -stat [listener name]\n\n"

Cause: Informational message.

Action: None.

26992 "Register"

Cause: Informational message.

Action: None.

26993 "Listener Name"

Cause: Informational message.

Action: None.

26994 "Port"

Cause: Informational message.

Action: None.

26995 "Register Checked Listeners"

Cause: Informational message.

Action: None.

26996 "No %s Listeners found under directory %s"

Cause: Informational message.

Action: None.

26997 "No %s Listeners found"

Cause: Informational message.

Action: None.

26998 "Unregister"

Cause: Informational message.

Action: None.

26999 "Server Software"

Cause: Informational message.

Action: None.

27000 "External Home"

Cause: Informational message.

Action: None.

27001 "Unregister Checked Listeners"

Cause: Informational message.

Action: None.

27002 "No Registered Listeners found"

Cause: Informational message.

Action: None.

27004 "Retry"

Cause: Informational message.

Action: None.

27005 "Transactions"

Cause: Informational message.

Action: None.

27006 "Transactions Parameters successfully modified"

Cause: Informational message.

Action: None.

27007 "Error: Physical Path [% (1)s] should be terminated with [% (2)s]"

Cause: The specified physical path is missing the specified terminator.

Action: Terminate physical path with specified character and retry.

27008 "Error: Virtual Path [% (1)s] should be terminated with [% (2)s]"

Cause: The specified virtual path is missing the specified terminator.

Action: Terminate virtual path with specified character and retry.

27009 "Error: Physical Path [% (1)s] does not exist"

Cause: The specified physical path is not valid.

Action: Specify valid physical path and retry.

27010 "Error: Virtual Path [% (1)s] should begin with [% (2)s]"

Cause: The specified virtual path is missing the specified first character.

Action: Begin virtual path with specified character and retry.

27011 "'%s' entry cannot be empty"

Cause: The specified field is missing.

Action: Fill specified field and retry.

27012 "Application Name"

Cause: Informational message.

Action: None.

27013 "Cartridge Name"

Cause: Informational message.

Action: None.

27014 "Configure File"

Cause: Informational message.

Action: None.

27015 "Display Name"

Cause: Informational message.

Action: None.

27016 "DAD Name"

Cause: Informational message.

Action: None.

27017 "Cartridge Location"

Cause: Informational message.

Action: None.

27018 "Cartridge Stubs"

Cause: Informational message.

Action: None.

27019 "Cartridge Implementation"

Cause: Informational message.

Action: None.

27020 "Shared Object"

Cause: Informational message.

Action: None.

27021 "Entry Point"

Cause: Informational message.

Action: None.

27022 "Physical Path"

Cause: Informational message.

Action: None.

27023 "EJB Jar File"

Cause: Informational message.

Action: None.

27024 "Jar File"

Cause: Informational message.

Action: None.

27025 "%s cannot have spaces"

Cause: Specified item cannot have spaces.

Action: Remove space(s) from specified item.

27026 "Specified %s does not exist."

Cause: Specified item does not exist.

Action: Specify existing item.

27027 "Invalid Location specified for class files"

Cause: Invalid location specified for class files.

Action: Specify valid location.

27028 "JCO Application Install Failed!"

Cause: Unable to create location file for JCO installation.

Action: Make sure the destination disk space is available.

27029 "EJB Application Install Failed!"

Cause: Unable to create location file for EJB installation.

Action: Make sure the destination disk space is available.

27030 "Could not create location file:\nYou may have run out of space on server disk\n"

Cause: No disk space left for location file.

Action: Make sure the destination disk space is available.

27031 "Virtual Path"

Cause: Informational message.

Action: None.

27032 "Invalid Physical Path specified."

Cause: Specified physical path does not exist.

Action: Specify an existing/valid physical path.

27033 "<HR><H4> Truncating Logger Tables for User: %s .. </H4><HR>"

Cause: Informational message

Action: None

28000 - 29000 : Session

028200 "Oracle Database Error : %(1)s"

Cause: External (Database) error.

Action: See the associated error and take the appropriate action.

028201 "Boot failed because neither Server Manager, nor SQLDBA could be run"

Cause: Either Server Manager or SQLDBA is necessary to be able to install the necessary PL/SQL packages.

Action: Install either Server Manager or SQLDBA in the ORACLE_HOME where the PL/SQL cartridge administration is installed.

028202 "Failed. Specify correct value for %(1)s and retry"

Cause: Value for mandatory parameter: NULL.

Action: Fill in the specified field and re-submit the form.

028203 "Failed.Specify correct ORACLE_SID or CONNECT_STRING and retry"

Cause: Either ORACLE_SID or CONNECT_STRING is necessary to connect to Oracle database.

Action: Specify either ORACLE_SID or CONNECT_STRING and re-submit form.

028204 "DAD %(1)s successfully written"

Cause: Informational Message.

Action: None.

028205 "Successfully executed necessary SQL scripts. Please verify log in %(1)s"

Cause: The install program successfully executed all necessary SQL scripts (files). The program, however, cannot detect errors which may have occurred while installing the PL/SQL packages.

Action: Check the output in the file specified and verify that there are not unexpected error messages.

028206 "DBA Username and Password are invalid"

Cause: DBA username and password submitted are invalid.

Action: Check and resubmit with correct info.

028207 "Note: Please check for errors in the log above before clicking on the OK button."

Cause: Informational Message.

Action: None.

28208 " If necessary consult database manuals for detailed explanation of error messages."

Cause: Informational message.

Action: None.

028231 "\"Tx Property\""

Cause: Informational message.

Action: None.

028232 "\"Transactions\""

Cause: Cause: Informational message.

Action: None.

028233 "\"Tuning\""

Cause: Informational message.

Action: None.

028234 "\"Security\""

Cause: Informational message.

Action: None.

028235 "\"Cartridge Library\""

Cause: Informational message.

Action: None.

29000 - 29299 : OTS Administration Error Messages

29030 "Can't access configuration information"

Cause: ORACLE_HOME environment variable may have the wrong value, or some remote node has not been added to the site.

Action: Check the ORACLE_HOME environment variable and make sure if add a DTC on a remote node, the remote node must have been added to the site.

29031 "Can't read configuration information from global configuration file, configuration file may be damaged"

Cause: Cannot read primary node information from **site.app**.

Action: Double check the **site.app** and make sure the primary node is configured.

29032 "Can't get the remote node information! Make sure node %s has been added to this website"

Cause: Cannot read the remote node information from **site.app**.

Action: Make sure the remote node has been added to this web site and the corresponding section is in **site.app**.

29033 "Can't access the template html file %s"

Cause: Cannot access the html template.

Action: Check if the html template file is in \$ORAWEB_HOME/admin/cgi and the permission is correct.

29034 "No configuration information for DTC %s"

Cause: No this section in **wrb.app**.

Action: Add the section first.

29035 "No configuration information for OTS Server %s"

Cause: No [ots.otssrv] section in **wrb.app**.

Action: This section is default, add the section first.

29040 "Can't configure the DTC %s, error code ORA-%s. Please refer to oracle error messages for details"

Cause: If the 8.0.4 database acting as DTC has smaller initialization parameters than it required. The DTC will be shut down first, the initialization file will

be changed, and the DTC will be started again. The shutdown, modification of initialization file or startup may go wrong.

Action: First, only the DBA can shutdown/startup database instances. Check the DTC configuration parameters and make sure the Oracle SID, Oracle home, dba user name and password, parameter file and connect string are valid. Refer to the ORA error message for further database related information.

29041 "DTC configuration succeed, but can't update wrb.app, double check if wrb.app is open and can't be written."

Cause: Cannot modify the global configuration file **wrb.app**.

Action: Check if the **wrb.app** has been locked by some other process.

29042 "No Distributed Transaction Coordinator configured!"

Cause: No DTC is configured.

Action: Add DTC first.

29043 "Can't configure DTC %s. Please refer to the help page for system setup details."

Cause: Adding DTC goes wrong!

Action: Double check the system setup and retry.

29044 "Add DTC %s failed, check if there is another DTC has the same name."

Cause: Two DTCs cannot have same names.

Action: Use a different DTC name. Since currently the DTC name is ORACLE SID, you cannot add two DTCs have the same SID.

29046 "DTC doesn't have desired parameters, check your initSID.ora"

Cause: After configure and restart, DTC still doesn't have the desired parameters"

Action: Check the initSID.ora and ots.ora include file

YXCFER_DB_START

29050 "Can't start DTC %s, error code ORA-%d"

Cause: Cannot start the database instance.

Action: Start database using other tools, for example, the server manager.

29051 "Can't stop DTC %s, error code ORA-%d"

Cause: Cannot stop the database instance.

Action: Stop database instance using other tools, for example, the server manager.

29052 "Illegal transactional dad section [DAD_%s]"

Cause: The transactional DAD section is illegal.

Action: Make sure the transactional dad section is legal.

29053 "No transactional DAD configured!"

Cause: No transactional DAD configured in global configuration file **wrb.app**.

Action: Add new transactional DAD.

29060 "Illegal URL to redirect the request"

Cause: Cannot redirect the HTTP request to remote node where DTC resides on.

Action: Make sure the remote node has been add to this site and the HTTP listener on remote node is running.

29070 "Illegal Input, integer expected"

Cause: Illegal input.

Action: Integer expected.

29071 "Can't access the [ots.otssrv] section in wrb.app"

Cause: Illegal **wrb.app** file.

Action: ots.otssrv section must be in **wrb.app** for OTS to work.

29072 "DTC %s not found!"

Cause: There is no this DTC in global configuration file wrb.app. The Oracle Application Server administration Java applet need to be reloaded to reflect the current DTC list.

Action: Reload the Oracle Application Server administration Java Applet.

29074 "Empty or illegal input field!"

Cause: Illegal input.

Action: Check the input and try again.

29075 "No space is allowed in input field"

Cause: Space in input field.

Action: Delete the space in input.

29080 "Can't logon to %s. Please check the user name, password and connect string, also make sure the TNS Listener is running."

Cause: OCI logon failed.

Action: Check the user name, password, connect string and TNS listener.

29084 "Illegal global database name in transactional DAD. Global database name is eight character or less (e.g. SALES)"

Cause: An illegal global database name is being used. The DTC cannot use this name to create a database link that points to the remote database.

Action: The database name should be eight characters or less (e.g. SALES)

OMN-205-OMN-11034 : ORB Error Messages

OMN-205, ERROR: yeevComplete: global limit over, dropped *num* events

Cause: The global limit has ended and will start sending events again.

Action: None.

OMN-320, ERROR: unexpected log type *num* in *str*

Cause: An internal error has occurred.

Action: Due to this type of error, please contact Oracle Worldwide Customer Support.

OMN-323, ERROR: yeevldGetRec: unexpected EOF reading file *str*

Cause: There is a problem reading the file.

Action: Due to this type of error, please contact Oracle Worldwide Customer Support.

OMN-324, ERROR: yeevldLimitCheck: failed to open new *str*: *str*

Cause: An error opening the rollover log file has occurred.

Action: As implied by the error.

OMN-330, ERROR: *str*: Error on sysfpOpen of *str*, mode *str*, kind *str*, reason *str*

Cause: An osd operation error has occurred.

Action: None.

OMN-331, ERROR: *str*: Error on sysfpFlush to *str*

Cause: An osd error has occurred.

Action: Check the contents of the specified file.

OMN-1112, ERROR: ydIntrHdlr: program interrupted, shutting down

Cause: A user interrupt has been detected.

Action: None.

OMN-1116, ERROR: ydSyncHandler: sync operations completed with an error

Cause: An error has occurred when synchronizing with existing mnorbsrvs.

Action: Check the existing mnorbsrv processes.

OMN-1153, ERROR: ydrtRoute: exception *str* from *str num*

Cause: An internal error has occurred.

Action: Due to this type of error, please contact Oracle Worldwide Customer Support.

OMN-1174, ERROR: ydrtGoodSpot: launch of host *str str* failed

Cause: The selected destination may or may not be ready.

Action: None.

OMN-1510, ERROR: Either -l or -s must be specified

OMN-1511, ERROR: Only one target allowed with -i, -D, -q, -Q, -P or -k

OMN-1512, ERROR: Only one server may be specified with -p, -y or -P

OMN-1520, ERROR: Only one of -i or -o may be specified

OMN-1521, ERROR: -a may only be used with -o

OMN-1522, ERROR: Error opening *str* for *str - str*

OMN-1543, ERROR: mnochsrv: *str*

OMN-1544, ERROR: mnochsrv: invalid handle

OMN-1545, ERROR: mnochsrv: still executing - *str*

OMN-1560, ERROR: mncnmsrv: Name Server is already initialized

OMN-1561, ERROR: mncnmsrv: Start up the names server without any options, or use '-f' to force reinitialization

OMN-1563, ERROR: mncnmsrv: Unable to contact cell root context, Exiting

OMN-1564, ERROR: mncnmsrv: Start up the name server without any options

OMN-1565, ERROR: mncnmsrv: Error creating back link from cell to local context

OMN-1566, ERROR: mncnmsrv: There is probably already a name server running

OMN-1567, ERROR: mncnmsrv: ysFnTemp returned a duplicate name

OMN-1568, ERROR: mncnmsrv: Problem opening the file associated with naming ctx"

OMN-1569, ERROR: mncnmsrv: names directory *str* does not exist

OMN-1570, ERROR: mncnmsrv: Name server not initialized, rerun with -i <cellname> option

OMN-1571, ERROR: *str str*: unexpected *str* from *str num*

OMN-1572, ERROR: mncnmsrv: Name server exiting unexpectedly

OMN-1573, ERROR: mncnmsrv: data-dir *str* is not a directory; using default

OMN-1578, ERROR: mncnmsrv: Localhost is not the boothost, bailing out.

OMN-1580, ERROR: mncnmsrv: *str* deleting file *str* from *str*

OMN-1600, ERROR: ydmtdInit: exception *str* trying to bind to name service**Cause:** An internal error has occurred.**Action:** None.**OMN-1601, ERROR: ydmtdSrcThr: exception *str* discovering OraOrbs. Stopping discovery****Cause:** An internal error has occurred.**Action:** None.**OMN-1602, ERROR: ydmtdCliThr: exception *str* servicing client requests. The metric daemon will shutdown****Cause:** An internal error has occurred.**Action:** Due to this type of error, please contact Oracle Worldwide Customer Support.**OMN-1605, ERROR: ydmtdOraOrbThr: *str* polling OraOrb queue. OraOrb metric info will no longer be updated****Cause:** An internal error has occurred.**Action:** None.**OMN-1607, ERROR: ydmtdReapThr: exception *str* reaping stopped****Cause:** An internal error has occurred.**Action:** None.**OMN-1608, ERROR: ydmtdReapThr: exception *str* trying to contact NameService. Reaping will not occur****Cause:** The name server may be down.**Action:** Start the mncnmsrv process.**OMN-1615, ERROR: ydmtdOraOrbThr: *str* servicing OraOrb *str*. Removing OraOrb from the tree****Cause:** An internal error has occurred.**Action:** None.**OMN-1619, ERROR: ydmtdInit: Unable to contact ORB daemon****Cause:** The ORB daemon may be down.**Action:** Start the mnorbsrv process.

OMN-1620, ERROR: ydmtddReap: Removing NULL entry *str/str*

Cause: The metric daemon is finding NULL entries in the ORB- name space.

Action: Shut down the ORB.

OMN-5000, ERROR: Unexpected internal error: *str* from file *str*; line *num*; aborting...

Cause: An internal error has occurred.

Action: Due to this type of error, please contact Oracle Worldwide Customer Support.

OMN-5001, ERROR: Unable to open output file '*str*'

Cause: A file system error has occurred.

Action: Check the file/directory permissions, existence, etc.

OMN-5002, ERROR: \"*str*\", line *num*: *str*: *str*

Cause: A file system error has occurred.

Action: Check the file/directory permissions, existence, etc.

OMN-5003, ERROR: write error during output

Cause: A write failure to output file during preprocessing has occurred.

Action: Check -o path permissions and existence.

OMN-5006, ERROR: Access denied to output directory '*str*'

Cause: Stub file destination directory does not exist or is not writeable.

Action: Redirect output to a different directory or change permissions.

OMN-5007, ERROR: unrecognized style '*str*'

Cause: Unrecognized language mapping the naming style. Acceptable styles are "ansi" (default) and "oracle".

Action: Correct the command line and try again.

OMN-5008, ERROR: Unable to create output file '*str*'

Cause: The stub already exists and is read only.

Action: Change the permissions on the target file or change the output directory.

OMN-5009, ERROR: Not a directory: 'str'

Cause: The pathname given to -o option does not name a directory.

Action: Create the desired directory or change the output pathname.

OMN-5010, ERROR: \"str\", line num: unterminated comment

Cause: The end of the file was reached in the middle of a comment.

Action: Close the comment and recompile.

OMN-5011, ERROR: \"str\", line num: unterminated character constant

Cause: The character literal was not terminated before the end of the line.

Action: Close the literal and recompile.

OMN-5012, ERROR: \"str\", line num: unterminated string literal

Cause: Closing the quote for string literal was not found before the end of the line.

Action: Close the string literal and recompile.

OMN-5014, ERROR: \"str\", line num: unterminated macro call

Cause: Badly formed function-like macro call.

Action: Correct the macro reference and recompile.

OMN-5015, ERROR: \"str\", line num: macro 'str' used with wrong number (num) of arguments

Cause: The wrong number of arguments was passed to a function-like macro.

Action: Correct the macro reference and recompile.

OMN-5016, ERROR: \"str\", line num: invalid directive

Cause: An unrecognized preprocessing directive has been encountered.

Action: Correct the directive and recompile.

OMN-5017, ERROR: \"str\", line num: unexpected 'str'

Cause: Improper syntax in the middle of a preprocessing directive. For example, a #elif, #else, or #endif was encountered outside the context of a #if, #ifdef, or #ifndef.

Action: Correct the directive and recompile.

OMN-5018, ERROR: *str***\", line** *num***: #error** *str*

Cause: A #error directive encountered.

Action: No action is required.

OMN-5019, ERROR: pragma ignored

Cause: Unrecognized pragma encountered, or pragma has no effect given the current compilation environment. (Certain command line options may disable certain pragmas).

Action: No action is required.

OMN-5020, ERROR: *str***\", line** *num***: invalid format of 'str' directive**

Cause: A syntax error in a preprocessing directive has occurred.

Action: Correct the syntax and recompile.

OMN-5021, ERROR: *str***\", line** *num***: illegal redefinition of macro 'str' at** *str:num*

Cause: Encountered a definition of a previously defined macro. A macro can only be defined once under the rules of ANSI C.

Action: Correct the macro definition and recompile.

OMN-5022, ERROR: *str***\", line** *num***: bad syntax in #define**

Cause: A syntax error in #define preprocessing directive has occurred.

Action: Correct the syntax and recompile.

OMN-5023, ERROR: *str***\", line** *num***: duplicate parameter 'str' in #define**

Cause: The same parameter name appears more than once in the argument list of a function-like macro definition.

Action: Change the parameter name and recompile.

OMN-5024, ERROR: *str***\", line** *num***: '#' operator is not followed by a parameter name**

Cause: The # preprocessing operator (stringification) must be followed by the symbol to be stringified.

Action: Correct the error and recompile.

OMN-5025, ERROR: \"str\", line num: '##' operator at beginning of macro definition

Cause: Missing the first operand of the ## preprocessing operator. (## concatenates its left and right operands).

Action: Correct the error and recompile.

OMN-5026, ERROR: \"str\", line num: '##' operator at end of macro definition

Cause: Missing the second operand of the ## preprocessing operator. (## concatenates its left and right operands).

Action: Correct the error and recompile.

OMN-5027, ERROR: \"str\", line num: #include files nested too deep

Cause: Maximum include file nesting exceeded. This limitation is imposed by the file system. If there are too many levels of include file nesting, the compiler will eventually be unable to open additional files.

Action: Reorganize #include hierarchy to decrease nesting levels.

OMN-5028, ERROR: \"str\", line num: str: include file not found

Cause: Unable to locate the file named in #include directive.

Action: Make sure the named file exists in the current directory or one of the directories supplied via the -I option. If so, check the file and directory privileges.

OMN-5029, ERROR: \"str\", line num: more than one #else directive in the same group

Cause: A #if/ifdef/ifndef directive must be paired with at most one #else directive.

Action: Correct the directive and recompile.

OMN-5030, ERROR: \"str\", line num: missing #endif

Cause: No #endif preprocessing directive was found for a #if/ifdef/ifndef.

Action: Correct the error and recompile.

OMN-5031, ERROR: \"str\", line num: 'defined' is used without an identifier

Cause: A syntax error in 'defined' preprocessing operation has occurred. The correct syntax is: defined (symbol).

Action: Correct the syntax and recompile.

OMN-5032, ERROR: \"str\", line *num*: bad syntax in str

Cause: A syntax error in preprocessing directive has occurred, such as unmatched parentheses.

Action: Correct the syntax and recompile.

OMN-5033, ERROR: \"str\", line *num*: bad expression syntax in #if

Cause: A syntax error in conditional expression of a #if directive has occurred.

Action: Correct the syntax and recompile.

OMN-5034, ERROR: \"str\", line *num*: string literals not allowed in #if expressions

Cause: String literals are not valid tokens in the conditional expression of a #if directive.

Action: Correct the error and recompile.

OMN-5035, ERROR: \"str\", line *num*: unknown escape sequence

Cause: An escaped character that is not one of the special literals, such as '\n' or '\t', has been encountered.

Action: Correct the error and recompile.

OMN-5036, ERROR: \"str\", line *num*: only integral constants are allowed in #if expressions

Cause: A non-integral constant has been encountered in the conditional expression of a #if preprocessing directive.

Action: Correct the error and recompile.

OMN-5037, ERROR: \"str\", line *num*: illegal character in octal constant

Cause: Octal character constants must start with '\', followed by one or more octal digits (0-7).

Action: Correct the character constant and recompile.

OMN-5038, ERROR: \"str\", line *num*: illegal character in hex constant

Cause: Hexidecimal character constants start with '\x', followed by 1 or more hex "digits" (0-9, a-f, case insensitive).

Action: Correct the character and recompile.

OMN-5039, ERROR: \"str\", line *num*: invalid macro name 'str'

Cause: An attempt to redefine a predefined preprocessing name, such as "defined".

Action: Change the macro name and recompile.

OMN-5045, ERROR: \"str\", line *num*: illegal character - '%c'

Cause: Unexpected characters have been encountered in source file.

Action: If nothing is apparent, check the input file for hidden control characters.

OMN-5046, ERROR: \"str\", line *num*: parse error on 'str'

Cause: An IDL syntax error at or near the indicated token has occurred.

Action: Correct the syntax error and recompile.

OMN-5047, ERROR: \"str\", line *num*: parse error on end of input

Cause: Unexpected end of file. For example, file ended in the middle of an interface or other type declaration.

Action: Correct the error and recompile.

OMN-5048, ERROR: Unrecoverable syntax error, please correct and recompile

Cause: Unable to continue parsing after a syntax error.

Action: Correct the syntax error and recompile.

OMN-5050, ERROR: \"str\", line *num*: 'str' is an ambiguous reference; possible interpretations are:

Cause: Unable to resolve an unqualified or partially qualified name because there is more than one qualifying match. For example, if an interface inherits the same name from two base interfaces, it is ambiguous if not qualified by the defining interface.

Action: Select the proper interpretation of the name and change the reference to be appropriately qualified.

OMN-5051, ERROR: \"str\", line *num*: 'strstr' originally defined at *str.num*

Cause: An attempt to redefine an IDL type or constant. Each IDL entity must be defined exactly once. This marks the occurrence of the original definition.

Action: Correct the error and recompile.

OMN-5052, ERROR: \"str\", line *num*: redefinition of 'str'

Cause: An attempt to redefine an IDL type or constant. Each IDL entity must be defined exactly once. This marks the occurrence of the second definition.

Action: Correct the error and recompile.

OMN-5053, ERROR: \"str\", line *num*: 'str' is not defined

Cause: A reference to an undefined IDL name has been made.

Action: Correct the error and recompile.

OMN-5054, ERROR: \"str\", line *num*: 'str' is not a type

Cause: Reference to a non-type (such as a constant or module) where a type name is required.

Action: If you believe the name is a type reference, make sure it has not been hidden by a declaration of the same name in an inner scope. Correct the error and recompile.

OMN-5055, ERROR: \"str\", line *num*: 'str' does not introduce a scope

Cause: There is a badly formed qualified name. In a qualified name of the form A::B::C, every component except the last one must name a scope. Modules, interfaces, structs, unions, exceptions, and their aliases qualify as scopes.

Action: Correct the name and recompile.

OMN-5056, ERROR: \"str\", line *num*: illegal type for constant declaration

Cause: IDL constants must be of integral, floating point, or string type. They cannot be of complex types such as struct, array, or sequence.

Action: Correct the error and recompile.

OMN-5057, ERROR: \"str\", line *num*: Malformed numeric literal, 'str'

Cause: An invalid literal syntax has occurred.

Action: Correct the syntax and recompile.

OMN-5058, ERROR: \"str\", line *num*: type of constant expression conflicts with target type

Cause: The type of a constant declaration and the type of its value must match. For example, a "long" constant variable cannot be initialized with a floating point expression.

Action: Change the type of the constant or the type of the expression.

OMN-5061, ERROR: \"str\", line num: 'str' is not a constant

Cause: The named IDL entity is not a constant. Identifiers used in places like constant initializers and union case labels must designate IDL constants.

Action: Correct the error and recompile.

OMN-5063, ERROR: \"str\", line num: invalid operand(s) to binary %c

Cause: Operand(s) to the indicated unary operator are not of the expected type.

Action: Correct the error and recompile.

OMN-5064, ERROR: \"str\", line num: division by zero

Cause: Divide by zero detected in a constant expression.

Action: Correct the error and recompile.

OMN-5065, ERROR: \"str\", line num: invalid operand(s) to binary str

Cause: Operand(s) to the indicated binary operator are not of the expected type.

Action: Correct the error and recompile.

OMN-5066, ERROR: \"str\", line num: illegal shift value (*unsigned num*)

Cause: Right operand of a shift expression must be in the range: $0 \leq \text{operand} < 32$.

Action: Correct the error and recompile.

OMN-5067, ERROR: \"str\", line num: invalid operand to binary %c

Cause: Operand to the indicated binary operator not of the expected type.

Action: Correct the error and recompile.

OMN-5069, ERROR: \"str\", line num: context expressions are not supported in this version

Cause: The compiler currently does not support IDL context expressions on attributes and operations.

Action: Remove the context expression and recompile.

OMN-5070, ERROR: \"str\", line num: 'str' is not an exception

Cause: The identifier in an operation's raises clause does not name an exception.

Action: Correct the error and recompile.

OMN-5071, ERROR: \"str\", line *num*: duplicate declaration of parameter 'str' is illegal

Cause: Each parameter in an operation parameter list must have a distinct name; a duplicate was detected.

Action: Rename one of the conflicting parameters and recompile.

OMN-5072, ERROR: \"str\", line *num*: illegal type for union discriminator

Cause: A bad type for the union discriminator type. Union discriminators must be of integral, character, boolean, or enumeration type.

Action: Correct the type and recompile.

OMN-5073, ERROR: \"str\", line *num*: 'str' is not an interface

Cause: An identifier in an interface inheritance specification (e.g. base interface list) does not name an interface.

Action: Correct the specification and recompile.

OMN-5074, ERROR: \"str\", line *num*: base interfaces may not be forward declarations

Cause: An identifier in an interface inheritance specification names an incomplete interface. An interface's full definition must occur before it can be used as a base interface.

Action: Correct the interface identifier and recompile.

OMN-5075, ERROR: \"str\", line *num*: the same base interface is specified more than once

Cause: An interface name appears more than once in an inheritance specification. An interface cannot appear as a direct base interface more than once.

Action: Correct the interface name and recompile.

OMN-5076, ERROR: \"str\", line *num*: illegal name conflict from base 'str' with:

Cause: A derived interface inherits the same operation or attribute name from more than one base interface. CORBA does not permit this at present.

Action: Correct the error and recompile.

OMN-5077, ERROR: \"str\", line *num*: definition of 'str' occludes inherited attribute or operation

Cause: A derived interface may not redefine an inherited operation or attribute name.

Action: Correct the error and recompile.

OMN-5079, ERROR: \"str\", line *num*: invalid recursive use of type 'str' in declaration of field 'str'

Cause: Illegal use of a struct, union, or exception type inside its own scope. Recursive type references may only appear as a field declaration as a sequence element type, such as struct S { sequence<S> f; };

Action: Correct the type and recompile.

OMN-5080, ERROR: \"str\", line *num*: invalid recursive use of type 'str' in declaration of field 'str' of struct/union 'str'

Cause: Illegal use of a struct, union, or exception type inside its own scope. Recursive type references may only appear as a field declaration as a sequence element type, such as struct S { sequence<S> f; };

Action: Correct the type and recompile.

OMN-5081, ERROR: \"str\", line *num*: floating point types are not currently supported

Cause: The compiler does not currently support the IDL float and double types.

Action: Correct the type and recompile.

OMN-5082, WARNING: \"str\", line *num*: unrecognized #pragma directive 'str'

Cause: Unrecognized pragma in input file. Unrecognized pragmas are ignored.

Action: No action is required.

OMN-5083, ERROR: \"str\", line *num*: repository id in #pragma ID cannot be an empty string

Cause: The string literal representing the repository id in a #pragma ID directive cannot be an empty string.

Action: Correct the error and recompile.

OMN-5084, ERROR: \"str\", line *num*: invalid format for repository id

Cause: Invalid repository id format in #pragma ID. See Chapter 6 of the CORBA 2.0 specification, or the Oracle Media Net documentation for valid formats.

Action: Correct the error and recompile.

OMN-5085, ERROR: unrecognized object adaptor on -a: 'str'

Cause: An unexpected object adaptor specification is encountered. Valid values are "boa" (CORBA Basic Object Adaptor) and "coa" (Oracle's Common Object Adaptor).

Action: Correct the command line and recompile.

OMN-5086, ERROR: \"str\", line *num*: illegal undefinition of predefined macro 'str'

Cause: Attempt to undefine one of the predefined macros __LINE__, __FILE__, __DATE__, __TIME__, __STDC__.

Action: Correct the error and recompile.

OMN-5087, ERROR: unsupported CORBA version on -c: 'str'

Cause: A code generation has been requested for an unsupported version of CORBA. Supported versions are 1.2 and 2.0.

Action: Correct the command line request and recompile.

OMN-5088, ERROR: -c ignored, only applicable with Basic Object Adaptor (BOA)

Cause: The CORBA version option is combined with Oracle's Common Object Adaptor. The CORBA version number is only germane when code is generated for the CORBA Basic Object Adaptor (BOA).

Action: Change object adaptors or remove the explicit CORBA version option.

OMN-5089, ERROR: \"str\", line *num*: 'str' must be an operation name

Cause: Identifier in a #pragma IAO_DB_CREATE is not the name of an operation.

Action: Change the identifier to a previously declared operation name.

OMN-5090, ERROR: \"str\", line *num*: 'str' must be an attribute name

Cause: Identifier in a #pragma IAO_DB_ATTR is not the name of an attribute.

Action: Change the identifier to a previously declared attribute name.

OMN-5091, ERROR: \"str\", line *num*: operation 'str' has no parameters

Cause: The operation named in a pragma IAO_DB_CREATE has no parameters. The operation must have one or more parameters, which are associated with attribute key strings by this pragma.

Action: Correct the pragma and recompile.

OMN-5092, ERROR: \"str\", line *num*: operation 'str' has no parameter 'str'

Cause: The operation named in a pragma IAO_DB_CREATE has no parameter with the given name.

Action: Correct the pragma and recompile.

OMN-5094, ERROR: \"str\", line *num*: conflicts with previous pragma declaration

Cause: The operation named in one of the IAO_DB pragmas is already in use by another IAO_DB pragma. For example, an operation already named in an IAO_DB_CREATE specification cannot also be the target of an IAO_DB_LIST pragma.

Action: Correct the pragma and recompile.

OMN-5095, ERROR: \"str\", line *num*: association key for 'str' may not be an empty string

Cause: The attribute/parameter key specified in one of the IAO_DB pragmas must be a non-empty string literal.

Action: Correct the pragma and recompile.

OMN-5096, ERROR: \"str\", line *num*: parameter 'str' is already associated with \"str\"

Cause: The indicated parameter association key in a pragma IAO_DB_CREATE has already been associated with another parameter.

Action: Correct the pragma and recompile.

OMN-5097, ERROR: \"str\", line *num*: create operations must return an object reference

Cause: The operation named in a pragma IAO_DB_CREATE must return an object reference (the created object).

Action: Correct the pragma and recompile.

OMN-5098, ERROR: \"str\", line *num*: list operations must return a sequence of object references

Cause: The operation named in a pragma IAO_DB_LIST must return a sequence of object references.

Action: Correct the pragma and recompile.

OMN-5099, ERROR: \"str\", line *num*: list operations must have one inout struct parameter (iterator)

Cause: The operation named in a pragma IAO_DB_LIST must have an inout parameter to act as the list iterator.

Action: Correct the pragma and recompile.

OMN-5100, ERROR: \"str\", line *num*: union field already declared with name 'str'

Cause: Each field of a union must be uniquely named.

Action: Correct the field name and recompile.

OMN-5101, ERROR: Unrecognized stub generation language: 'str'

Cause: A request for a code generation in an unsupported language has occurred. The compiler will generate code for C and C++ only.

Action: Change the language to "c" or "cplus" and retry.

OMN-5104, ERROR: \"str\", line *num*: Wildcard must be last character in context id: \"str\"

Cause: Wildcard character (asterisk) found in a position other than the end of a context id. Pattern matching is performed only at the end of a context id, as per CORBA.

Action: Correct the context id and recompile.

OMN-5105, ERROR: \"str\", line *num*: struct/exception field 'str' previously declared

Cause: Duplicate struct or exception field names exist.

Action: Correct the name and recompile.

OMN-5108, ERROR: \"str\", line *num*: Mixed floating point and integral types in expression

Cause: Constant expression contains both floating point and integral operands, which CORBA does not permit.

Action: Correct the error and recompile.

OMN-5109, ERROR: Unable to open file 'str': Insufficient privileges

Cause: Could not open file due to permissions.

Action: Check the file permissions.

OMN-5110, ERROR: Unable to open file '*str*': File not found

Cause: Unable to open the output file because the file could not be found.

Action: Correct the error and recompile.

OMN-5111, ERROR: Unable to open file '*str*': Unexpected file system error

Cause: Unable to open the file due to an unknown file system problem.

Action: Correct the file system error and recompile.

OMN-5112, ERROR: Unable to open file '*str*' for writing

Cause: The target output file is not writeable.

Action: Check the file permissions and recompile.

OMN-5113, ERROR: Unrecognized argument to command line option '*str*'

Cause: Unable to interpret the command line option value.

Action: Correct the command line and recompile.

OMN-5500, PANIC: unexpected internal error: *str* from file *str*, line *num*; aborting...

Cause: An internal error has occurred.

Action: Due to this type of error, please contact Oracle Worldwide Customer Support.

OMN-5501, ERROR: unable to locate interface repository server with tag '*str*'

Cause: No interface repository with the given implementation id is registered with the ORB daemon.

Action: Start up a new server with the expected tag, or change the tag you are using to a registered server. Use `mnorbls` to determine what tags are in use.

OMN-5502, ERROR: unable to get current working directory: *str*

Cause: Unable to determine the current working directory pathname. It is necessary for translating all load file names into absolute pathnames.

Action: Check the directory privileges and try again.

OMN-5503, ERROR: file/directory not found: '*str*'

Cause: Unable to locate a file or directory to load into the server.

Action: Check the pathnames and permissions and try again.

OMN-5504, ERROR: IFR data file '*str*' appears corrupted

Cause: A file was found which appears to be an IFR data file (has .ifr suffix and expected header), but the data in the file is unreadable. The file is either corrupted, or is of an IFR data format more recent than the server it is being loaded into.

Action: Regenerate the data and try again. If you suspect a newer data format, try a more recent version of the IFR server.

OMN-5505, ERROR: unexpected exception raised during load of '*str*': *str*

Cause: The server sent back an unexpected/unrecognized exception when attempting to load the specified file/directory.

Action: Check pathnames, network state, etc. and try again. It may be necessary to restart and reload the server.

OMN-5506, ERROR: unexpected exception raised while attempting to get load list: *str*

Cause: The server sent back an unexpected/unrecognized exception when the client attempted to retrieve the server's load list.

Action: The server is either down or in a corrupt state. Restart it.

OMN-5507, ERROR: shutdown failed - exception received: *str*

Cause: mnirctl was unable to shutdown the requested server. Instead, the stated exception was raised. The server may be corrupted or the connection may be down.

Action: Kill the server manually.

OMN-5508, ERROR: load conflict occurred while loading '*str*':

Cause: Attempt to load data into the server failed due to conflicts between the existing server contents and the new data. The names of the offending symbols and the nature of the conflict are reported in subsequent messages.

Action: If a name is undefined, load a definition into the server. If a name is already defined, do not load the offending file, or restart the server and change it's contents so there is no conflict.

OMN-5509, ERROR: symbol undefined: *str*

Cause: Attempt to load data into the server resulted in an unresolved symbol reference.

Action: Before loading the offending file, load a definition of the the specified symbol.

OMN-5510, ERROR: symbol redefined: *str*

Cause: A definition of the given name is already loaded in the IFR.

Action: Do not load the offending file. Use a different IFR server, or restart the server and change its contents.

OMN-5511, ERROR: an IFR server with tag '*str*' already exists

Cause: There is already a server running with the same tag (implementation id) as the one just started. IFR servers must have unique tags because they do not share data.

Action: Use the running server, if it contains the right data. Bring down the existing server, or restart the current one with a different tag.

OMN-5512, ERROR: unexpected exception raised instantiating a new repository for '*str*': *str*

Cause: An unexpected exception was raised when the IFR server tried to initialize itself. The server is probably out of memory (unlikely) or the memory is corrupted.

Action: Restart the server.

OMN-5513, ERROR: IFR data file appears corrupted (unreadable): '*str*'

Cause: A file which appeared to be an IFR data file was unreadable. That is, the file had a ".ifr" suffix, but the header or data was unreadable. The file may be corrupted, may not be an IFR data file, or may not match an IFR data format this server knows how to handle (e.g. server only understands up to v.2, but the file is v.3).

Action: If you believe the file is really an IFR data file, try regenerating it with a version of the compiler you know is compatible with the server. If the file is not an IFR data file, do not attempt to load it (or it's containing directory into the server).

OWB-01001-OWB-02002 : ODBC Error Messages

OWB - 01001 Logon failed

Cause: The cartridge cannot use either the *dsn*, *username* or *password* in the URL to log on to the target database. The logon might have failed because of incorrect data, such as in incorrect *username*, or an improperly configured database.

Action: Make the necessary corrections.

OWB - 01002 Unable to find *database* in the URL

Cause: The *database* parameter was missing from the URL.

Action: For Unix: Add a database name/value to the URL. The database value can be Oracle7, Sybase10, or Informix7ol, Informix7se, or MSSQL6.

Action: For NT: the *database* parameter is not required on the Windows NT platform. Contact Oracle Worldwide Customer Support Services.

OWB - 01003 Unable to find *dsn* (data source name) in the URL

Cause: The *dsn* parameter was missing from the URL.

Action: Add a data source name/value pair to the URL. *orcl* must be defined as the system data source name.

OWB - 01004 Unable to find SQL statement in the URL

Cause: The *sql* parameter was missing from the URL.

Action: Add the SQL parameter and a SQL statement to the URL.

OWB - 01005 Unable to find *username* in the URL

Cause: The *username* parameter was missing from the URL.

Action: Add the username parameter and your username to the URL. For an example, see the [URL Example](#).

OWB - 01006 Unable to find *password* in the URL

Cause: The *password* parameter was missing from the URL.

Action: Add the password parameter and your password to the URL. For an example, see the [URL Example](#).

OWB - 01010 Unable to find *variable* in the URL

Cause: There is a variable missing from the URL.

Action: Add a name/value pair for the variable to the URL.

OWB - 01011 Memory allocation failed

Cause: The cartridge could not obtain enough system memory.

Action: Ensure your system has sufficient RAM and swap space.

OWB - 01012 No data found

Cause: There is no data found by executing the SQL statement.

Action: Check the SQL statement and outputstring format.

OWB - 01013 Not enough data for *outputstring* in the SQL statement

Cause: The number of columns in the result set is too small. The number of columns must equal the number of variables needed in *outputstring*.

Action: Ensure your SQL statement will retrieve enough data for *outputstring*.

OWB - 01014 Syntax error for *outputstring*

Cause: Incorrect syntax was used in specifying the parameter *outputstring*.

Action: Modify your SQL statement to correct the syntax. For an example, see the [URL Example](#).

OWB - 01015 GET method is not allowed

Cause: The request is using the GET method. This can cause a security loophole.

Action: Modify the request to use POST instead of GET.

OWB - 01016 Invalid data source name (DSN)

Cause: The data source name (dsn) is invalid or undefined.

Action: Define the system data source name before using it.

OWB - 02001 Driver Manager failed

Cause: The ODBC driver manager returned an error.

Action: See the associated error message.

OWB - 02002 Driver failed

Cause: The ODBC driver returned an error.

Action: See the associated error message.

URL Example

```
http://mark1:8888/odbc/stringprint?dsn=orcl7&username=scott&password=tiger
&sql=select+name,age+from+emp+where+deptno=:department
&department=IT&outputstring=Employee+%1+is+%2+years+old.&maxrows=7
```